

MC92308


Product Preview

OFDM Demodulator

The MC92308 is a Orthogonal Frequency Division Multiplex Demodulator for 2K transmission mode according to the ETSI specification for digital terrestrial broadcasting (PR ETS 300744). The MC92308 contains all the functionality required to demodulate the information transmitted in one UHF channel.

Feature Summary

- Usable for 8MHz/7MHz/6MHz channels by adjusting the clock rate
- Digital I/Q separation on-chip
- Supports QPSK, 16-QAM and 64-QAM
- Supports all guard interval lengths (1/32, 1/16, 1/8, 1/4)
- Accepts 8-bit TTL-compatible twos-complement data input
- Provides the required control signals for Automatic Gain Control and ADC clock frequency control
- Performs channel estimation and correction by using the embedded pilot carriers
- I²C serial bus compatible interface (M-Bus) and parallel interface for external programming and control of the device
- Transmission Parameter Signalling is decoded and made available to the system controller via M-Bus or parallel microprocessor interface
- Companion to DVB compliant 2K-FFT Processor (MC92307)
- Output interface for DBV compliant FEC
- Fast synchronization at power-on and after channel switch
- Low implementation margin
- 0.5μ CMOS Process at 3.3V



Ordering Information

Device	Package
MC92308CI	160MQUAD





Figure 1. OFDM Frontend Processing

This document contains information on a product under development. Motorola reserves the right to change or discontinue this product without notice.





160MQUAD

Table 1. MC92308 Pin Description

SIGNAL	FUNCTIONALITY	TYPE	POLTY
CLK	Common clock input (36.57 MHz)	TTL - IN	high
RESB	Reset (synchronous)	TTL - IN	low
CLKEN18	ADC data strobe	TTL - IN	high
ADCDATA[7:0]	Input for samples from ADC	TTL - IN	high
CLKCTLP	ADC clock synchronization loop (+)	TTL - OUT	high
CLKCTLN	ADC clock synchronization loop (-)	TTL - OUT	low
AGCCTLP	Analog AGC loop (+)	TTL - OUT	high
AGCCTLN	Analog AGC loop (-)	TTL - OUT	low
FFTSTART	FFT start signal	TTL - OUT	high
FFTDO[7:0]	Complex data output to FFT (muxed)	TTL - OUT	high

Table 1. MC92308 Pin Description (Continued)

SIGNAL	FUNCTIONALITY	TYPE	POLTY
FFTDI[11:0]	Complex data input from FFT (muxed)	TTL - IN	high
SYMSYNC	Symbol start signal from FFT	TTL - IN	high
G1DATA[2:0]	Data output for Viterbi decoder	TTL - OUT	high
G2DATA[2:0]	Data output for Viterbi decoder	TTL - OUT	high
FECCLK	Clock for Viterbi Decoder (free running)	TTL - OUT	high
FECVALID	Data valid signal for Viterbi Decoder	TTL - OUT	high
MSDA	I ² C compatible control bus, data pin	TTL - OD	-
MSCL	I ² C compatible control bus, clock pin	TTL - IN	high
MBUSID[3:0]]	I ² C compatible control bus, variable ID selector	TTL - IN	high
MSEL	Enable Microprocessor parallel interface	TTL - IN	high
MDATA[7:0]	Microprocessor interface bidirectional databus	TTL - bidir	high
MADDR[5:0]	Microprocessor interface address bus	TTL - IN	high
MCSB	Microprocessor interface chip select	TTL - IN	low
MWRB	Microprocessor interface write enable	TTL - IN	low
MRDB	Microprocessor interface read enable	TTL - IN	low

Notes:

Motorola reserves the right to make changes without further notice to any products herein. Motorola makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Motorola assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation consequential or incidental damages. "Typical" parameters which may be provided in Motorola data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. Motorola does not convey any license under its patent rights nor the rights of others. Motorola products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the Motorola product could create a situation where personal injury or death may occur. Should Buyer purchase or use Motorola products for any such unintended or unauthorized application, Buyer shall indemnify and hold Motorola and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that Motorola was negligent regarding the design or manufacture of the part. Motorola and  are registered trademarks of Motorola, Inc. Motorola, Inc. is an Equal Opportunity/Affirmative Action Employer.

How to reach us:

USA/EUROPE/Locations Not Listed: Motorola Literature Distribution;
P.O. Box 5405, Denver Colorado 80217. 1-800-441-2447 or 303-675-2140

Mfax[™]: RMFAX0@email.sps.mot.com -TOUCHTONE (602) 244-6609
INTERNET:<http://mot-sps.com/sps/General/sales.html>

JAPAN: Nippon Motorola Ltd.; Tatsumi-SPD-JLDC, 6F Seibu-Butsuryu-Center,
3-14-2 Tatsumi Koto-Ku, Tokyo 135, Japan. 81-3-3521-8315

ASIA/PACIFIC: Motorola Semiconductors H.K. Ltd.; 8B Tai Ping Industrial Park,
51 Ting Kok Road, Tai Po, N.T., Hong Kong. 852-26629298



MOTOROLA

MC92308