

### FEATURES

- Configurable high-side, low-side and push-pull operation
- Current limited output (< 450 mA)
- Reverse polarity protection
- 150 mA output current
- 5  $\mu$ s input filter for spike suppression
- Wide supply voltage range from 8 to 30 V
- Driver shut-down with over temperature
- Integrated free-wheeling diode for inductive loads
- Sensor supply voltage output of 5 V, 10 mA

### APPLICATIONS


- Digital sensors
- Light barriers
- Proximity switches

### PACKAGES



DFN6 2x2mm

### BLOCK DIAGRAM



### DESCRIPTION

The iC-DX is a monolithic switch capable of driving ohmic, inductive and capacitive loads and features integrated reverse polarity protection. The supply voltage  $V_B$  of the device can range from 8 to 30 V.

Output source/sink-current is at least 150 mA, with saturation voltages of typically 2 V.

With input OE on high level state, the output works as a push-pull stage under control of pin IN. If pin IN is set either to high or low level, the output acts as


a high-side (PNP) or low-side (NPN) driver which is activated by a high logic level on input OE.

Output transitions are slew-rate limited to minimize interference on lines. The output is current limited to 450 mA maximum and short circuit protected by shutting down the device with excessive temperature.

A regulated 5 V supply which can be loaded up to 10 mA is available at pin VOUT.

### PACKAGES DFN6 2x2

#### PIN CONFIGURATION



#### PIN FUNCTIONS

##### No. Name Function


- |   |      |                        |
|---|------|------------------------|
| 1 | VOUT | Regulated +5 V Voltage |
| 2 | GND  | Ground                 |
| 3 | IN   | Input                  |
| 4 | OE   | Output Enabled         |
| 5 | OUT  | Driver Output          |
| 6 | VB   | Supply Voltage         |

The *Thermal Pad* is to be connected to a Ground Plane (GND) on the PCB.

**Only pin 1 marking on top or bottom defines the package orientation (top label and coding is subject to change).**

### PACKAGE DIMENSIONS DFN6 2x2

#### RECOMMENDED PCB-FOOTPRINT



dra\_dfn6-1\_pack\_5, 20:1

**ABSOLUTE MAXIMUM RATINGS**

Beyond these values damage may occur; device operation is not guaranteed.

Item No.	Symbol	Parameter	Conditions	Min.   Max.		Unit
				Min.	Max.	
G001	VB	Supply Voltage		-36	36	V
G002	V()	Voltage at IN, OE		-0.3	7	V
G003	Tj	Junction Temperature		-40	150	°C
G004	Ts	Storage Temperature		-40	150	°C
G005	Vd()	ESD Susceptibility	HBM, 100 pF discharged through 1.5 k $\Omega$	2		kV

**THERMAL DATA**

Operating Conditions: VB = 8..30 V

Item No.	Symbol	Parameter	Conditions	Min.   Typ.   Max.			Unit
				Min.	Typ.	Max.	
T01	Ta	Operating Ambient Temperature Range	no thermal shutdown	-40		+150	°C

All voltages are referenced to ground unless otherwise stated.

All currents flowing into the device pins are positive; all currents flowing out of the device pins are negative.

**ELECTRICAL CHARACTERISTICS**Operating Conditions:  $V_B = 8..30\text{ V}$ ,  $T_j = -40..150^\circ\text{C}$ , unless otherwise stated

Item No.	Symbol	Parameter	Conditions				Unit
				Min.	Typ.	Max.	
<b>General</b>							
001	Vc()lo	Clamp Voltage lo at IN, OE, VOUT	I() = 1 mA			1V	
002	VB	Permissible Supply Voltage	Referenced to GND	8	24	30	V
003	I(VB)	Supply Current in VB	no load, IN = lo, OE = lo IN = lo, OE = hi IN = hi, OE = hi			0.9 1.2 1.5	mA mA mA
004	V(VB)on	Turn-on threshold	increasing VB	6		8	V
005	Ilk(GND)rp	Reverse Polarity Leakage Current	V(VB) = 0; V(OUT) = 0; V(GND) = 0...30 V			300	uA
006	Ilk(OUT)rp	Reverse Polarity Leakage Current	V(VB)=0;V(GND)=0; V(OUT)= 0...30 V			300	uA
007	Ilk(VB)rp	Reverse Polarity Leakage Current	V(OUT) = 0 ; GND open; ; V(VB)= 0...30 V			300	uA
<b>Output characteristics</b>							
101	Vs(IOUT)lo	Saturation voltage Low-Side driver	IN = lo, OE = hi I(OUT) = 100 mA I(OUT) = 150 mA			1.5 2	V V
102	Vs(IOUT)hi	Saturation voltage High-Side driver	IN = hi, OE = hi I(OUT) = -100 mA I(OUT) = -150 mA	-1.5 -2			V V
103	Isc()lo	Short-Circuit Current lo in OUT	V(OUT) = 3 V...VB	150		450	mA
104	Isc()hi	Short-Circuit Current Hi in OUT	V() = 0...VB - 3 V	-450		-150	mA
105	Ilk()	Leakage Current at OUT	OUTPUT Disabled V(OUT) = -6...0 V V(OUT) = 0 V...VB V(OUT) > VB...30 V	-100 -40 0		0 40 100	uA uA uA
106	SR()	Slew Rate (switch off → on, switch on → off )	VB = 30 V, Cl = 2.2 nF, I(OUT) = 0			40	V/μs
107	Vfw(OUT)lo	Freewheeling Voltage	I(OUT) = -1 mA, with reference to VB	-47		-36	V
108	Vfw(OUT)hi	Freewheeling Voltage	I(OUT) = 1 mA, with reference to GND	36		47	V
<b>Temperature monitor</b>							
201	Toff	Overtemperature shutdown	increasing Tj	150		185	°C
<b>Inputs OE, IN</b>							
301	Vt()hi	Input Threshold Voltage hi at IN, OE				2	V
302	Vt()lo	Input Threshold Voltage lo at IN, OE		0.8			V
303	Vt()hys	Hysteresis at IN, OE	Vt()hys = Vt()hi - Vt()lo	200			mV
304	Ipd()	Pull-Down Current at IN, OE	V() > 0.4 V	2		150	uA
305	tpio	Propagation Delay IN, OE → OUT		2.1		6.5	μs
306	tsup()	Permissible Spurious Pulse Width at IN, OE				1.6	μs
307	ttrig()	Required Pulse Width at IN, OE		4			μs
<b>Series regulator output VOUT</b>							
401	V(VOUT)	Regulated output voltage	VB = 9..30 V, I(VOUT) = 10 .. 0 mA VB = 8..9 V, I(VOUT) = 10 .. 0 mA	4.7 4.5		5.3 5.3	V V
402	C(VOUT)	Capacitor at VOUT	I(VOUT) = 0 I(VOUT) > 0	0 0.1		10 10	μF μF
403	Isc(VOUT)	Short circuit current at VOUT	VOUT connected to GND			-125	mA

### DESCRIPTION OF FUNCTIONS

iC-DX is a current limited switching channel which enables digital sensors to drive peripheral elements. They are designed to cope with high driver currents. The switches are reverse-polarity protected, feature a free-wheeling circuit for inductive loads, and a current limited output.

#### Reverse polarity protection

The pins VB, OUT and GND on the *line side* of the chip are reverse polarity protected. As far as the maximum voltage ratings are not exceeded, no possible supply combination at the *line side* pins can damage the chip.




Figure 1: OUT characteristic when Low side active




Figure 2: OUT characteristic when high side active

#### Output characteristics of OUT

The switching channel is current limited to a value between 150mA and 450mA. (cf. Electrical Characteristics Nos. 103, 104). The current limitation works only for voltages higher than 3V at OUT resp. lower than  $V_{BO} - 3V$ . For smaller output voltages the current limitation is reduced in order to minimise the saturation voltages without increasing the power dissipation. Figures 1 and 2 show the characteristic of the switching channels when activated. Region "A" is the saturation range, where the current limitation is not fully active yet and region "B" is the current limited range. Region "C" corresponds to the free-wheeling circuit activated. The switching channel is designed so that the low side can only sink current and high side can only source current (no reverse current).

#### Free-wheeling circuit for inductive loads

The free-wheeling circuit is always present and does not depend on the current output status. It is activated by voltages higher than 36 V at OUT referenced to GND or lower than -36 V at OUT referenced to VB. In that case the correspondent channel will switch on without current limitation (see Figure 3).




Figure 3: Free-wheeling characteristic

### OPERATION MODES

The iC-DX can be operated in high-side, low-side and push-pull switch mode. Figure 4 shows the high-side operation where IN pin must be kept high and the OE pin controls the switch. Figure 5 shows the low-side operation where IN pin must be kept low and the OE pin controls the switch. Figure 6 shows the push-pull operation where OE pin must be kept high and the IN pin controls the switch.




Figure 4: Configuration as high side

# iC-DX

## UNIVERSAL DIGITAL SENSOR OUTPUT DRIVER




Figure 5: Configuration as low side




Figure 6: Configuration as Pushpull

### TIMING DESCRIPTION

The iC-DX has a built-in spurious pulse suppression that prevents short (undesired) pulses at the input pins from reaching the output. Every pulse at OE or IN pins shorter than  $1.6\ \mu\text{s}$  (cf. Electrical Characteristics No. 306) will be ignored and the output will not react. The minimum required pulse length to be sure that the output reacts is  $4\ \mu\text{s}$  (cf. Electrical Characteristics No. 307). That means that every pulse longer than  $4\ \mu\text{s}$  will be propagated to the output but with an additional propagation delay of  $1.2\ \mu\text{s}$  maximum. The resulting maximum propagation delay is  $5.2\ \mu\text{s}$  (cf. Electrical Characteristics No. 305).




Figure 7: Timing diagram in push-pull operation mode




Figure 8: Block diagram with EN and NEP internal signals

# iC-DX

## UNIVERSAL DIGITAL SENSOR OUTPUT DRIVER

preliminary



Rev A2, Page 8/9

iC-Haus expressly reserves the right to change its products and/or specifications. An info letter gives details as to any amendments and additions made to the relevant current specifications on our internet website [www.ichaus.de/infoletter](http://www.ichaus.de/infoletter); this letter is generated automatically and shall be sent to registered users by email.

Copying – even as an excerpt – is only permitted with iC-Haus' approval in writing and precise reference to source.

iC-Haus does not warrant the accuracy, completeness or timeliness of the specification and does not assume liability for any errors or omissions in these materials.

The data specified is intended solely for the purpose of product description. No representations or warranties, either express or implied, of merchantability, fitness for a particular purpose or of any other nature are made hereunder with respect to information/specification or the products to which information refers and no guarantee with respect to compliance to the intended use is given. In particular, this also applies to the stated possible applications or areas of applications of the product.

iC-Haus conveys no patent, copyright, mask work right or other trade mark right to this product. iC-Haus assumes no liability for any patent and/or other trade mark rights of a third party resulting from processing or handling of the product and/or any other use of the product.

As a general rule our developments, IPs, principle circuitry and range of Integrated Circuits are suitable and specifically designed for appropriate use in technical applications, such as in devices, systems and any kind of technical equipment, in so far as they do not infringe existing patent rights. In principle the range of use is limitless in a technical sense and refers to the products listed in the inventory of goods compiled for the 2008 and following export trade statistics issued annually by the Bureau of Statistics in Wiesbaden, for example, or to any product in the product catalogue published for the 2007 and following exhibitions in Hanover (Hannover-Messe).

We understand suitable application of our published designs to be state-of-the-art technology which can no longer be classed as inventive under the stipulations of patent law. Our explicit application notes are to be treated only as mere examples of the many possible and extremely advantageous uses our products can be put to.

**iC-DX**

UNIVERSAL DIGITAL SENSOR OUTPUT DRIVER

preliminary



Rev A2, Page 9/9

**ORDERING INFORMATION**

Type	Package	Order Designation
iC-DX	DFN6	iC-DX DFN6

For technical support, information about prices and terms of delivery please contact:

**iC-Haus GmbH**  
**Am Kuemmerling 18**  
**D-55294 Bodenheim**  
**GERMANY**

**Tel.: +49 (61 35) 92 92-0**  
**Fax: +49 (61 35) 92 92-192**  
**Web: <http://www.ichaus.com>**  
**E-Mail: [sales@ichaus.com](mailto:sales@ichaus.com)**

**Appointed local distributors: [http://www.ichaus.com/sales\\_partners](http://www.ichaus.com/sales_partners)**