

## SI-3002N Series


# 3-Terminal, Full-Mold, Low Dropout Voltage Dropper Type

### ■Features

- Compact full-mold package (equivalent to TO220)
- Output current: 2.0A
- Low dropout voltage:  $V_{DIF} \leq 1V$  (at  $I_o = 2.0A$ )
- Built-in foldback overcurrent, overvoltage, thermal protection circuits

### ■Applications

- For stabilization of the secondary stage of switching power supplies
- Electronic equipment



### ■Absolute Maximum Ratings

( $T_a = 25^\circ C$ )

Parameter	Symbol	Ratings			Unit
		SI-3052N	SI-3092N	SI-3122N/3152N	
DC Input Voltage	$V_{IN}$	25	30	35	V
DC Output Current	$I_o$	2.0 <sup>*1</sup>			A
Power Dissipation	$P_{D1}$	20(With infinite heatsink)			W
	$P_{D2}$	1.5(Without heatsink, stand-alone operation)			W
Junction Temperature	$T_j$	-40 to +125			$^\circ C$
Ambient Operating Temperature	$T_{op}$	-30 to +100			$^\circ C$
Storage Temperature	$T_{stg}$	-40 to +125			$^\circ C$
Thermal Resistance (junction to case)	$R_{th(j-c)}$	5.0			$^\circ C/W$
Thermal Resistance (junction to ambient air)	$R_{th(j-a)}$	66.7(Without heatsink, stand-alone operation)			$^\circ C/W$

■Electrical Characteristics

(Ta=25°C unless otherwise specified)

Parameter	Symbol	Ratings												Unit
		SI-3052N			SI-3092N			SI-3122N			SI-3152N			
		min.	typ.	max.	min.	typ.	max.	min.	typ.	max.	min.	typ.	max.	
Input Voltage	V <sub>IN</sub>	6 <sup>2</sup>		15 <sup>1</sup>	10 <sup>2</sup>		25 <sup>1</sup>	13 <sup>2</sup>		27 <sup>1</sup>	16 <sup>2</sup>		27 <sup>1</sup>	V
Output Voltage	V <sub>O</sub>	4.90	5.00	5.10	8.82	9.00	9.18	11.76	12.00	12.24	14.70	15.00	15.30	V
	Conditions	V <sub>IN</sub> =8V, I <sub>O</sub> =1.0A			V <sub>IN</sub> =12V, I <sub>O</sub> =1.0A			V <sub>IN</sub> =15V, I <sub>O</sub> =1.0A			V <sub>IN</sub> =18V, I <sub>O</sub> =1.0A			
Dropout Voltage	V <sub>DIF</sub>			0.5			0.5			0.5			0.5	V
	Conditions	I <sub>O</sub> ≤1.5A												
	Conditions			1.0			1.0			1.0			1.0	
Line Regulation	ΔV <sub>OLINE</sub>		10	30		18	48		24	64		30	90	mV
	Conditions	V <sub>IN</sub> =6 to 15V, I <sub>O</sub> =1.0A			V <sub>IN</sub> =10 to 20V, I <sub>O</sub> =1.0A			V <sub>IN</sub> =13 to 25V, I <sub>O</sub> =1.0A			V <sub>IN</sub> =16 to 25V, I <sub>O</sub> =1.0A			
Load Regulation	ΔV <sub>OLOAD</sub>		40	100		70	180		93	240		120	300	mV
	Conditions	V <sub>IN</sub> =8V, I <sub>O</sub> =0 to 2.0A			V <sub>IN</sub> =12V, I <sub>O</sub> =0 to 2.0A			V <sub>IN</sub> =15V, I <sub>O</sub> =0 to 2.0A			V <sub>IN</sub> =18V, I <sub>O</sub> =0 to 2.0A			
Temperature Coefficient of Output Voltage	ΔV <sub>O</sub> /ΔT <sub>a</sub>		±0.5			±1.0			±1.5			±1.5		mV/°C
	Conditions	V <sub>IN</sub> =8V, I <sub>O</sub> =5mA, T <sub>J</sub> =0 to 100°C			V <sub>IN</sub> =12V, I <sub>O</sub> =5mA, T <sub>J</sub> =0 to 100°C			V <sub>IN</sub> =15V, I <sub>O</sub> =5mA, T <sub>J</sub> =0 to 100°C			V <sub>IN</sub> =18V, I <sub>O</sub> =5mA, T <sub>J</sub> =0 to 100°C			
Ripple Rejection	R <sub>REJ</sub>		54			54			54			54		dB
	Conditions	V <sub>IN</sub> =8V, f=100 to 120Hz			V <sub>IN</sub> =12V, f=100 to 120Hz			V <sub>IN</sub> =15V, f=100 to 120Hz			V <sub>IN</sub> =18V, f=100 to 120Hz			
Quiescent Circuit Current	I <sub>q</sub>		3	10		3	10		3	10		3	10	mA
	Conditions	V <sub>IN</sub> =8V, I <sub>O</sub> =0A			V <sub>IN</sub> =12V, I <sub>O</sub> =0A			V <sub>IN</sub> =15V, I <sub>O</sub> =0A			V <sub>IN</sub> =18V, I <sub>O</sub> =0A			
Overcurrent Protection Starting Current <sup>*3,4</sup>	I <sub>S1</sub>	2.1			2.1			2.1			2.1			A
	Conditions	V <sub>IN</sub> =8V			V <sub>IN</sub> =12V			V <sub>IN</sub> =15V			V <sub>IN</sub> =18V			

\*1: V<sub>IN(max)</sub> and I<sub>O(max)</sub> are restricted by the relation P<sub>D(max)</sub>=(V<sub>IN</sub>-V<sub>O</sub>)•I<sub>O</sub>=20(W).

\*2: Refer to the dropout voltage.(Refer to Setting DC Input Voltage on page 7.)


\*3: I<sub>S1</sub> is specified at -5(%) drop point of output voltage V<sub>O</sub> on the condition that V<sub>IN</sub>=V<sub>O</sub>+3V, I<sub>O</sub>=1.0A.

\*4: A foldback type overcurrent protection circuit is built into the IC regulator. Therefore, avoid using it for the following applications as it may cause starting errors:


- (1) Constant current load (2) Plus/minus power (3) Series power (4)V<sub>O</sub> adjustment by raising ground voltage

■External Dimensions


(unit:mm)




■Block Diagram



■Standard External Circuit




■ $T_a$ - $P_D$  Characteristics




■Typical Characteristics

( $T_a=25^{\circ}\text{C}$ )


**$I_o$  vs.  $V_{DIF}$  Characteristics**




**Temperature Coefficient of Output Voltage(SI-3052N)**




**Output Voltage(SI-3052N)**




**Output Voltage(SI-3122N)**




**Overcurrent Protection Characteristics(SI-3052N)**



**Overcurrent Protection Characteristics(SI-3122N)**



**Thermal Protection Characteristics(SI-3052N)**



**Note on Thermal Protection:**

The thermal protection circuit is intended for protection against heat during instantaneous short-circuiting. Its operation is not guaranteed for continuous heating condition such as short-circuiting over extended periods of time.