





Neon Indicator Lamps

Configuration	Part Number	Old Ref. Number	Design Current mA	Maximum Breakdown Voltage	
				VAC	VDC
Wire Terminal-Standard Brightness					
	2ML	NE -38S	0.3	65	90
	A1A	NE -2	0.6	65	90
	A1A-T	NE -2T	0.6	65	90
	A1B		0.3	65	90
	A1D		0.3	65	90
	A1D-T		0.3	65	90
	K4A	AR -9	0.3	80	115
	A2B	NE -2V	0.7	65	90
	A2B-T	NE -2VT	0.7	65	90
	A9A	NE -2E	0.7	65	90
	A9A-T	NE -2E T	0.7	65	90
	A9A-C	NE -2E 1	0.7	65	90
A9A-C T	NE -2E 1T	0.7	65	90	
Wire Terminal-High Brightness					
	1MH	NE -38	1.2	95	135
	A1C		1.2	95	135
	A1C -T		1.2	95	135
	G2B-1		1.2	95	135
	G2B-2		1.4	95	135
	A3C	NE -2U	1.9	95	135
	A3C -T	NE -2UT	1.9	95	135
	C2A	NE -2H	1.9	95	135
	C2A-T	NE -2HT	1.9	95	135
	C2A-C	NE -2H 1	1.9	95	135
	D2A		2.6	95	135

Footnotes

- Life value is to approximately 50% of initial light output. Values shown apply to use on AC unless otherwise shown. Life on DC is approximately 60% of AC values when DC current is equal to RMS AC value. When equal DC and RMS AC voltages and equal resistances are utilized, life will be approximately the same.
- For DC operation of high brightness lamps use a minimum of 150 circuit volts.
Maximum initial breakdown voltage 95 VAC, 135 VDC in light.
- Tinned leads.
- High brightness.
- Formed tip.
- Dark effect reduced.
- Lamp drops through a Ø.310" cylinder of .500" minimum length.