

RQL1001JLAQH

SiGe MMIC
High Frequency Low Noise Amplifier


REJ03G1539-0100
Rev.1.00
May 16, 2007

Features

- Small SMD package CMPAK-6.
- Ideal for wireless LAN(2.4 GHz / 5 GHz band), Cordless Phone, GPS antenna, IMS band applications
- Low noise, High gain,
 $NF = 1.2 \text{ dB}$, $PG = 19.5 \text{ dB}$, $f = 2.45 \text{ GHz}$
 $NF = 2.1 \text{ dB}$, $PG = 16.5 \text{ dB}$, $f = 5.85 \text{ GHz}$
- Having of power control terminal (Vctrl)

Outline

RENESAS Package code: PTSP0006JA-A
(Package name: CMPAK-6)



1. RFout
2. GND
3. Vctrl
4. GND
5. RFin
6. GND

Note: Marking is "JL".

Absolute Maximum Ratings

($T_a = 25^\circ\text{C}$)

Item	Symbol	Ratings	Unit
Supply Voltage	V_{CC}	4	V
Maximum Current	I_{CC}	20	mA
Maximum Input Power	$P_{in \text{ max}}$	+5	dBm
Total Power Dissipation	P_t	80 ^{Note}	mW
Operating Case Temperature	$T_{c(op)}$	-10 to +85	$^\circ\text{C}$
Storage Temperature	T_{stg}	-55 to +150	$^\circ\text{C}$

Note: Value on PCB (FR-4 : 40 x 40 x 1.6 mm double side)


Electrical Characteristics

(Ta = 25°C)


Item	Symbol	Min.	Typ	Max.	Unit	Test Conditions
Noise Figure	NF	—	1.2	—	dB	f = 2.45 GHz, V _{CC} = 3 V, V _{ctrl} = 2.7 V
		—	2.1	—		f = 5.85 GHz, V _{CC} = 3 V, V _{ctrl} = 3.0 V
Power Gain	PG	—	19.5	—	dB	f = 2.45 GHz, V _{CC} = 3 V, V _{ctrl} = 2.7 V
		—	16.5	—		f = 5.85 GHz, V _{CC} = 3 V, V _{ctrl} = 3.0 V
Input Return Loss ^{note1}	S11	—	12	—	dB	f = 2.45 GHz, V _{CC} = 3 V, V _{ctrl} = 2.7 V
		—	10	—		f = 5.85 GHz, V _{CC} = 3 V, V _{ctrl} = 3.0 V
Output Return Loss ^{note2}	S22	—	20	—	dB	f = 2.45 GHz, V _{CC} = 3 V, V _{ctrl} = 2.7 V
		—	25	—		f = 5.85 GHz, V _{CC} = 3 V, V _{ctrl} = 3.0 V
1 dB Compression Point at output	P1dB	—	+3.5	—	dBm	f = 2.45 GHz, V _{CC} = 3 V, V _{ctrl} = 2.7 V
		—	+2	—		f = 5.85 GHz, V _{CC} = 3 V, V _{ctrl} = 3.0 V
Third Order Intercept Point at output	OIP3	—	+13.5	—	dBm	f = 2.45 GHz, Δf = 1 MHz, V _{CC} = 3 V, V _{ctrl} = 2.7 V
		—	+11	—		f = 5.85 GHz, Δf = 1 MHz, V _{CC} = 3 V, V _{ctrl} = 3.0 V

Notes: 1, 2. Value on our specification circuit. (Refer to P.3, P.5)

Circuit Block Diagram



2.45 GHz Characteristics




Component ID	Value	Part Code	Tolerance	Rated Voltage	Manufacture
C1	3 pF	CM05CH3R0C50AH	-0.25 to +0.25 pF	50 V	KYOCERA
C2	1 pF	CM05CH1R0C50AH	-0.25 to +0.25 pF		
C3, C5, C7	1000 pF	CM05B102K50AH	-10 to +10%	10 V	NICHICON
C4, C6	10 pF	CM05CH100J50AH	-5 to 5%		
C8, C9	1 μF	F921A105MPA	-10 to +10%		


Component ID	Value	Part Code	Tolerance	I _{max}	Manufacture
L1	1 nH	LL1005-FHL1N0S	-0.3 to 0.3 nH	500 mA	TOKO

Component ID	Value	Part Code	Tolerance	Power Rating	Manufacture
R1	1.5 kΩ	RK73B1ETTD152J	-5 to +5%	0.063 W	KOA


Pin - Pout Characteristics




3rd. Order Intermodulation Distortion




Power Gain, Noise Figure vs. Frequency




Power Gain, Noise Figure vs. Control Voltage



S Parameter vs. Frequency




S Parameter vs. Frequency



Test condition : $V_{CC} = 3\text{ V}$, $V_{ctrl} = 2.7\text{ V}$
2.0 to 3.0 GHz (0.1 GHz step)


5.85 GHz Characteristics




Component ID	Value	Part Code	Tolerance	Rated Voltage	Manufacture
C1	1 pF	CM05CH1R0C50AH	-0.25 to +0.25 pF	50 V	KYOCERA
C2, C5, C7, C9	1000 pF	CM05B102K50AH	-10 to +10%		
C3	0.4 pF	CM05CH0R4C50AH	-0.25 to +0.25 pF		
C4	0.5 pF	CM05CH0R5C50AH	-0.25 to +0.25 pF		
C6, C8	10 pF	CM05CH100J50AH	-5 to 5%	10 V	NICHICON
C10, C11	1 μF	F921A105MPA	-10 to +10%		

Component ID	Value	Part Code	Tolerance	Power Rating	Manufacture
R1	1.5 kΩ	RK73B1ETTD152J	-5 to +5%	0.063 W	KOA


Pin - Pout Characteristics




3rd. Order Intermodulation Distortion




Power Gain, Noise Figure vs. Frequency




Power Gain, Noise Figure vs. Control Voltage



S Parameter vs. Frequency





S Parameter vs. Frequency





Test condition : $V_{CC} = 3\text{ V}$, $V_{ctrl} = 3\text{ V}$
5.0 to 6.0 GHz (0.1 GHz step)

Evaluation Board


f = 2.45 GHz



f = 5.85 GHz



Package Dimensions



Ordering Information

Part Name	Quantity	Shipping Container
RQL1001JLTL-E	3000 pcs	φ178 mm reel, 8 mm emboss taping

Note: For some grades, production may be terminated. Please contact the Renesas sales office to check the state of production before ordering the product.

Notes:

1. This document is provided for reference purposes only so that Renesas customers may select the appropriate Renesas products for their use. Renesas neither makes warranties or representations with respect to the accuracy or completeness of the information contained in this document nor grants any license to any intellectual property rights or any other rights of Renesas or any third party with respect to the information in this document.
2. Renesas shall have no liability for damages or infringement of any intellectual property or other rights arising out of the use of any information in this document, including, but not limited to, product data, diagrams, charts, programs, algorithms, and application circuit examples.
3. You should not use the products or the technology described in this document for the purpose of military applications such as the development of weapons of mass destruction or for the purpose of any other military use. When exporting the products or technology described herein, you should follow the applicable export control laws and regulations, and procedures required by such laws and regulations.
4. All information included in this document such as product data, diagrams, charts, programs, algorithms, and application circuit examples, is current as of the date this document is issued. Such information, however, is subject to change without any prior notice. Before purchasing or using any Renesas products listed in this document, please confirm the latest product information with a Renesas sales office. Also, please pay regular and careful attention to additional and different information to be disclosed by Renesas such as that disclosed through our website. (<http://www.renesas.com>)
5. Renesas has used reasonable care in compiling the information included in this document, but Renesas assumes no liability whatsoever for any damages incurred as a result of errors or omissions in the information included in this document.
6. When using or otherwise relying on the information in this document, you should evaluate the information in light of the total system before deciding about the applicability of such information to the intended application. Renesas makes no representations, warranties or guarantees regarding the suitability of its products for any particular application and specifically disclaims any liability arising out of the application and use of the information in this document or Renesas products.
7. With the exception of products specified by Renesas as suitable for automobile applications, Renesas products are not designed, manufactured or tested for applications or otherwise in systems the failure or malfunction of which may cause a direct threat to human life or create a risk of human injury or which require especially high quality and reliability such as safety systems, or equipment or systems for transportation and traffic, healthcare, combustion control, aerospace and aeronautics, nuclear power, or undersea communication transmission. If you are considering the use of our products for such purposes, please contact a Renesas sales office beforehand. Renesas shall have no liability for damages arising out of the uses set forth above.
8. Notwithstanding the preceding paragraph, you should not use Renesas products for the purposes listed below:
 - (1) artificial life support devices or systems
 - (2) surgical implantations
 - (3) healthcare intervention (e.g., excision, administration of medication, etc.)
 - (4) any other purposes that pose a direct threat to human lifeRenesas shall have no liability for damages arising out of the uses set forth in the above and purchasers who elect to use Renesas products in any of the foregoing applications shall indemnify and hold harmless Renesas Technology Corp., its affiliated companies and their officers, directors, and employees against any and all damages arising out of such applications.
9. You should use the products described herein within the range specified by Renesas, especially with respect to the maximum rating, operating supply voltage range, movement power voltage range, heat radiation characteristics, installation and other product characteristics. Renesas shall have no liability for malfunctions or damages arising out of the use of Renesas products beyond such specified ranges.
10. Although Renesas endeavors to improve the quality and reliability of its products, IC products have specific characteristics such as the occurrence of failure at a certain rate and malfunctions under certain use conditions. Please be sure to implement safety measures to guard against the possibility of physical injury, and injury or damage caused by fire in the event of the failure of a Renesas product, such as safety design for hardware and software including but not limited to redundancy, fire control and malfunction prevention, appropriate treatment for aging degradation or any other applicable measures. Among others, since the evaluation of microcomputer software alone is very difficult, please evaluate the safety of the final products or system manufactured by you.
11. In case Renesas products listed in this document are detached from the products to which the Renesas products are attached or affixed, the risk of accident such as swallowing by infants and small children is very high. You should implement safety measures so that Renesas products may not be easily detached from your products. Renesas shall have no liability for damages arising out of such detachment.
12. This document may not be reproduced or duplicated, in any form, in whole or in part, without prior written approval from Renesas.
13. Please contact a Renesas sales office if you have any questions regarding the information contained in this document, Renesas semiconductor products, or if you have any other inquiries.



RENESAS SALES OFFICES

<http://www.renesas.com>

Refer to "<http://www.renesas.com/en/network>" for the latest and detailed information.

Renesas Technology America, Inc.
450 Holger Way, San Jose, CA 95134-1368, U.S.A
Tel: <1> (408) 382-7500, Fax: <1> (408) 382-7501

Renesas Technology Europe Limited
Dukes Meadow, Millboard Road, Bourne End, Buckinghamshire, SL8 5FH, U.K.
Tel: <44> (1628) 585-100, Fax: <44> (1628) 585-900

Renesas Technology (Shanghai) Co., Ltd.
Unit 204, 205, AZIA Center, No.1233 Lujiazui Ring Rd, Pudong District, Shanghai, China 200120
Tel: <86> (21) 5877-1818, Fax: <86> (21) 6887-7898

Renesas Technology Hong Kong Ltd.
7th Floor, North Tower, World Finance Centre, Harbour City, 1 Canton Road, Tsimshatsui, Kowloon, Hong Kong
Tel: <852> 2265-6688, Fax: <852> 2730-6071

Renesas Technology Taiwan Co., Ltd.
10th Floor, No.99, Fushing North Road, Taipei, Taiwan
Tel: <886> (2) 2715-2888, Fax: <886> (2) 2713-2999

Renesas Technology Singapore Pte. Ltd.
1 Harbour Front Avenue, #06-10, Keppel Bay Tower, Singapore 098632
Tel: <65> 6213-0200, Fax: <65> 6278-8001

Renesas Technology Korea Co., Ltd.
Kukje Center Bldg. 18th Fl., 191, 2-ka, Hangang-ro, Yongsan-ku, Seoul 140-702, Korea
Tel: <82> (2) 796-3115, Fax: <82> (2) 796-2145

Renesas Technology Malaysia Sdn. Bhd
Unit 906, Block B, Menara Amcorp, Amcorp Trade Centre, No.18, Jalan Persiaran Barat, 46050 Petaling Jaya, Selangor Darul Ehsan, Malaysia
Tel: <603> 7955-9390, Fax: <603> 7955-9510