



ELECTRONICS, INC.
 44 FARRAND STREET
 BLOOMFIELD, NJ 07003
 (973) 748-5089

NTE1295 Integrated Circuit TV Signal Processor

Description:

The NTE1295 is an integrated circuit in an 18-Lead DIP type package designed for color TV deflection signal processing circuit. It can be operated with 12V power supply and is suitable for compact and medium-sized color TV sets.

Features:

- Built-In Vertical Deflection Driver Circuit
- Incorporating Vertical and Horizontal Oscillator Circuit, Operations Highly Stable Against Changes in Supply Voltage and Temperature.
- Highly Stable Synchronous Separation Circuit Against Noise
- Built-In High Tension Protector Circuit (X-Ray Protection)
- 12V Supply Voltage Operation.

Absolute Maximum Ratings: ($T_A = +25^\circ\text{C}$, Note 1 unless otherwise specified)

Supply Voltage	
V_{7-8}	10.5V
V_{15-8}	14.4V
Circuit Voltage	
V_{1-8}	0 to 10V
V_{10-8}	0 to V_{15-8}
V_{12-8}	0 to V_{15-8}
V_{17-8}	-0.6 to 6.0V
V_{18-8}	-3 to +2V
Supply Current	
I_7	15mA
I_{15}	20mA
Circuit Current	
I_2	-3 to +3mA
I_3	-5 to 0mA
I_4	-5 to +5mA
I_5	-1 to +1mA
I_6	-20 to 0mA
I_9	-15 to 0mA
I_{12}	-1 to +150mA
I_{13}	0 to 40mA
Power Dissipation, P_D	450mW
Operating Ambient Temperature Range, T_{opr}	-20° to +70°C
Storage Temperature Range, T_{stg}	-55° to +150°C

Note 1. \oplus and \ominus are flow-in and flow-out currents to/from the circuit, respectively.

Electrical Characteristics: ($T_A = +25^\circ\text{C}$ unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Circuit Current	I_7	Apply 12V with 240Ω to Pin7	7.5	11.2	15.0	mA
	I_{15}	$V_{15-8} = 12\text{V}$	15.5	23.0	32.0	mA
Protector Operating Voltage	V_{5-8}	Apply 12V with 240Ω to Pin7	0.64	0.70	0.76	V
Oscillation Starting Voltage (V • O _{sc})	$V_{\text{OSC-S}}$	$f_{\text{VO}} = 40$ to 70Hz, 1.0V _{P-P} or More	–	–	6.2	V
Vertical Oscillation Frequency	f_{VO}	$V_{\text{CC1}} = 12\text{V}$	53	55	58	Hz
f_{VO} Change with Supply Voltage	$\Delta f_{\text{VO}}/V_{\text{CC}}$	$f_{\text{VO}} _{9.6\text{V}}$ to $f_{\text{VO}} _{14.4\text{V}}$	0	0.93	1.3	Hz
Pulse Width (V • O _{sc})	τ	$V_{\text{CC1}} = 12\text{V}$	500	600	820	μs
Vertical Pull-In Range	f_{VP}	$R_{\text{OSC}} = 10.93\text{k}\Omega$, ($f_{\text{VO}} = 48 \pm 1.5\text{Hz}$)	–	–	50	Hz
Vertical Sawtooth Wave Amplification	$V_{(\text{saw})}$	$R_{\text{SAW}} = 26.4\text{k}\Omega$	1.8	2.0	2.2	V _{P-P}
f_{VO} Change with Ambient Temperature	$\Delta f_{\text{VO}}/T_A$	$T_A = -20^\circ$ to $+70^\circ\text{C}$, Note 2	–220	–170	0	ppm/°C
$V_{(\text{saw})}$ Change with Ambient Temperature	$\Delta V_{(\text{saw})}/T_A$	$T_A = -20^\circ$ to $+70^\circ\text{C}$, Note 2	–	–	30	mV _{P-P} /°C
Vertical Output Tr Drive Current	I_9		–	–	7.5	mA
Oscillation Starting Voltage (H • O _{sc})	$V_{\text{OSC-S}}$	$f_{\text{HO}} = 10$ to 20kHz, 1.4V _{P-P} or More ($V_{\text{CC2}} = 6.5\text{V}$)	–	–	6	V
Horizontal Oscillation Frequency	f_{HO}	$V_{\text{CC2}} = 12\text{V}$	15.0	15.6	16.25	kHz
f_{HO} Change with Supply Voltage	$\Delta f_{\text{HO}}/V_{\text{CC}}$	$f_{\text{HO}} _{13\text{V}}$ to $f_{\text{HO}} _{10\text{V}}$	0	25	45	Hz
Pulse Width Duty Ratio (H • O _{sc})	τ	$V_{\text{CC2}} = 12\text{V}$	32.0	36.0	39.5	%
f_{HO} Control Sensitivity	β	$I_O = \pm 100\text{mA}$	19	21	23	Hz/μA
f_{HO} Change with Ambient Temperature	$\Delta f_{\text{HO}}/T_A$	$T_A = -20^\circ$ to $+70^\circ\text{C}$, Note 2	–210	–100	0	ppm/°C
AFC Loop Gain	f_{AFC}	$\mu \times \beta$	5800	7700	9600	Hz/rad

Note 2. Design reference value.



