



DISCRETE POWER DIODES and THYRISTORS
DATA BOOK



ST103S SERIES

INVERTER GRADE THYRISTORS

Stud Version

Features

- All diffused design
- Center amplifying gate
- Guaranteed high dv/dt
- Guaranteed high di/dt
- High surge current capability
- Low thermal impedance
- High speed performance

105A

Typical Applications

- Inverters
- Choppers
- Induction heating
- All types of force-commutated converters

Major Ratings and Characteristics

| Parameters | ST103S | Units |
|-------------------|-------------|-------------------|
| $I_{T(AV)}$ | 105 | A |
| @ T_C | 85 | °C |
| $I_{T(RMS)}$ | 165 | A |
| I_{TSM} | 3000 | A |
| @ 50Hz | 3150 | A |
| I^2t | 45 | KA ² s |
| @ 60Hz | 41 | KA ² s |
| V_{DRM}/V_{RRM} | 400 to 800 | V |
| t_q range | 10 to 25 | μs |
| T_J | - 40 to 125 | °C |



case style
TO-209AC (TO-94)

ST103S Series




Fig. 1 - Current Ratings Characteristics




Fig. 2 - Current Ratings Characteristics




Fig. 3 - On-state Power Loss Characteristics




Fig. 4 - On-state Power Loss Characteristics

ST103S Series




Fig. 5 - Maximum Non-repetitive Surge Current




Fig. 6 - Maximum Non-repetitive Surge Current




Fig. 7 - On-state Voltage Drop Characteristics




Fig. 8 - Thermal Impedance Z_{thJC} Characteristic




Fig. 9 - Reverse Recovered Charge Characteristics




Fig. 10 - Reverse Recovery Current Characteristics

ST103S Series




Fig. 11 - Frequency Characteristics




Fig. 12 - Frequency Characteristics




Fig. 13 - Frequency Characteristics




Fig. 14 - Maximum On-state Energy Power Loss Characteristics




Fig. 15 - Gate Characteristics

ST103S Series

Outline Table

