



WIT910

900MHz Frequency Hopping Transceiver OEM Module

Features:

- **900 MHz Frequency Hopping Spread Spectrum technology**
- **20+ mile range w/omni-directional antennas**
- **3.3 Volt operation**
- **Low power consumption**
- **Small size, light weight**
- **172.8 Kbps channel data rate**
- **RS-232 style asynchronous interface**
- **FCC certified for unlicensed operation**

Benefits:

- **License-free operation**
- **Immunity to jamming and multipath fading**
- **Supports long range applications**
- **Ideal for battery powered devices**
- **Supports large number of nodes**
- **Easy to integrate**
- **Shortens time to market**

Combining 900MHz frequency hopping technology and 500mW of transmit power, the WIT910 is the latest in a long line of wireless OEM transceiver modules from RFM. With the same physical dimensions of the industry-leading WIT2410 module, smaller than a business card and just 8.6mm thick, the WIT910 provides immunity to both jamming and multipath fading. The WIT910 also provides a low power consumption mode suitable for battery operation.



WIT910

General Specifications

RF Frequency	902 to 927 MHz																								
Radio Certification	FCC Part 15.247, license free																								
Operating Range	Indoor: 1000'+ Outdoor: >20 miles with omni-directional antenna																								
Network Topology	Star network																								
Network Protocol	Dynamically Assigned TDMA																								
Error Detection and Correction	24 bit CRC and ARQ																								
Serial Data Interface	Asynchronous (RS-232) CMOS signals, 3.3v; 5v tolerant																								
I/O Data Rate	Up to 86.4 Kbps, software selectable																								
Channel Data Rate	172.8 Kbps																								
# of Frequency Channels	54																								
RF Bandwidth	460 KHz																								
Transmit Power Output	500mW, 100mW, 10mW, software selectable																								
Receiver Sensitivity	-103 dBm for 10-5 BER																								
Supply voltage	3.3 v to 10 v, 5 v nominal																								
Current Consumption (500mW Transmit Power, 57.6Kbps I/O)	<table border="0"> <tr> <td>Remote</td> <td>Sleep</td> <td>250µA</td> <td>Base</td> <td>Continuous</td> <td>125mA</td> </tr> <tr> <td>Operation</td> <td>Stby</td> <td>43mA</td> <td>Operation</td> <td>Peak (Tx)</td> <td>600mA</td> </tr> <tr> <td></td> <td>Typical</td> <td><100mA</td> <td></td> <td></td> <td></td> </tr> <tr> <td></td> <td>Peak (Tx)</td> <td>600mA</td> <td></td> <td></td> <td></td> </tr> </table>	Remote	Sleep	250µA	Base	Continuous	125mA	Operation	Stby	43mA	Operation	Peak (Tx)	600mA		Typical	<100mA					Peak (Tx)	600mA			
Remote	Sleep	250µA	Base	Continuous	125mA																				
Operation	Stby	43mA	Operation	Peak (Tx)	600mA																				
	Typical	<100mA																							
	Peak (Tx)	600mA																							
Size	80.2mm x 46.5mm x 8.6mm																								
Weight	35g																								
Operating Temperature	-40 C to 70 C																								
Humidity	20% to 90% (non-condensing)																								

Connector Pinout

Pin	Signal	Type	Description
1	Gnd	-	Signal and chassis ground
2	TxD	Input	Transmit data
3	RxD	Output	Receive data
4	CFG	Input	Configuration selector. Used to switch radio between data and control mode
5	RTS	Input	Request to send. Used for receive flow control by the host
6	Sleep	Input	Sleeps/wakes the radio transceiver
7	DCD	Output	Data carrier detect. For remotes, indicates successful synchronization
8	CTS	Output	Clear to send. Used for receive flow control by the radio
10	Reset	Input	Resets module
16	Vcc		Positive supply. Min 3.3 v, Nom 5.0 v, Max 10.0

Powerful

With a full 1/2 Watt transmit power and a receive sensitivity of -103dBm, the WIT910 can achieve ranges in excess of 20 miles using 3dB omni-directional antennas. When long range isn't needed, the WIT910, measuring just 80.2mm x 46.5mm x 8.6mm and weighing just 35 grams is a powerful performer at low power, consuming less than 100mA at 3.3 volts.

With the same size and mounting dimensions of the industry-leading WIT2410 module, the WIT910 can be used in place of the WIT2410 in existing designs, creating a 900MHz product with practically no development effort.

Versatile

All of the module parameters are configurable under software control. Even transmit power can be selected through a straightforward command set. Point-to-point and point-to-multipoint modes are supported. Standard communication rates between the 910 and the host are supported between 1200 bps and 57.6 Kbps. Non-standard rates are supported as well.

Reliable

The WIT910 provides both reliable communication and reliable operation. With Frequency Hopping Spread Spectrum technology, the WIT910 provides immunity to jamming as well as immunity to multipath fading. Using Automatic Retransmit Request (ARQ) in addition to a 512 byte buffer, transparent error-free communication is automatic. The built-in data scrambling adds a measure of security.

Reliable operation is assured through our stringent QA processes. All WIT910s are manufactured in an ISO9000 certified facility; another reason CIRRONETTM is the choice of hundreds of designers.

Simple

Simple to use and simple to integrate. Although the WIT910 offers great flexibility, the factory default settings work for many applications. For those other applications, software control makes changing settings simple.

The WIT910, with its small size and low power consumption, is simple to integrate into your product. The RS-232 style interface with standard CMOS signal levels makes the electronic integration easy. Since the WIT910 is FCC certified, your 910-based product does not have to repeat the FCC type approval.