E-Series 1:9 Transformer 10 - 75 MHz



Features


- Surface Mount
- 1:9 Impedance Ratio
- CT on Secondary



Description


M/A-COM's ETC9-1T-5 is a 1:9 RF transmission line step-up transformer in a low cost, surface mount package. Ideally suited for high volume cellular and wireless applications. Typical applications include single to balanced mode conversion and impedance matching.

SM-22 Package



Schematic

information.



Electrical Specifications @25°C

Parameter	Units	Maximum	Minimum	Typical
Frequency Range	MHz	_	_	_
Insertion Loss $(f_L - f_U)$ 10- 75 MHz	dB	2.0	_	0.8
Amplitude Unbalance 10-75 MHz	dB	1.0	_	0.1
Phase Unbalance 10-75 MHz	Degrees	7°	_	_
Return Loss 10-75 MHz	dB	14	_	20.50

S 0806 F

- North America Tel: 800.366.2266 Europe Tel: +353.21.244.6400
- India Tel: +91.80.4155721 China Tel: +86.21.2407.1588

 Visit www.macomtech.com for additional data sheets and product

ADVANCED: Data Sheets contain information regarding a product M/A-COM Technology Solutions is considering for development. Performance is based on target specifications, simulated results, and/or prototype measurements. Commitment to develop is not guaranteed.

PRELIMINARY: Data Sheets contain information regarding a product M/A-COM Technology.

and/or prototype measurements. Commitment to develop is not guaranteed.

PRELIMINARY: Data Sheets contain information regarding a product M/A-COM Technology
Solutions has under development. Performance is based on engineering tests. Specifications are
typical. Mechanical outline has been fixed. Engineering samples and/or test data may be available.

Commitment to produce in volume is not guaranteed.

Absolute Maximum Ratings


Parameter	Absolute Maximum	
RF Power	250 mW	
DC Current	30 mA	
Operating Temperature	-20°C to +85°C	
Storage Temperature	-20°C to +85°C	

Functional Configuration


Function	Pin No.	
Secondary Dot	1	
Secondary CT	2	
Secondary	3	
Primary	4	
Primary Dot	5	

Typical Performance @ 25°C


Insertion Loss




Phase Unbalance



Amplitude Unbalance



Return Loss



S 0806 F

- North America Tel: 800.366.2266 Europe Tel: +353.21.244.6400
- India Tel: +91.80.4155721 China Tel: +86.21.2407.1588

 Visit www.macomtech.com for additional data sheets and product information.

ADVANCED: Data Sheets contain information regarding a product M/A-COM Technology Solutions is considering for development. Performance is based on target specifications, simulated results, and/or prototype measurements. Commitment to develop is not guaranteed. PRELIMINARY: Data Sheets contain information regarding a product M/A-COM Technology Solutions has under development. Performance is based on engineering tests. Specifications are typical. Mechanical outline has been fixed. Engineering samples and/or test data may be available. Commitment to produce in volume is not guaranteed.