


Customer Name	<b>Standard Specification</b>	FUJITSU MEDIA DEVICES LIMITED	
System	W-CDMA V (850) Tx (100/50ohm)	DATE	Mar. 07, 2007
FMD Part Number	FAR-F5KB-836M50-B4ER	Version 2.0d	

**Table 1. Electrical specifications**


Passband: 824 ~ 849 MHz						
Item	Condition (MHz)	Specification			Unit	Remarks
		Min.	Typ.	Max.		
Insertion Loss	824~849	-	1.7	2.5	dB	
Ripple	824~849	-	0.5	1.4	dB	
Absolute attenuation	DC~779	40	73	-	dB	
	779~804	40	69	-	dB	
	869~894	38	44	-	dB	
	894~6000	30	47	-	dB	
VSWR (Input)	824~849	-	1.6	2.0	-	
VSWR (Output)	824~849	-	1.6	2.0	-	
Amplitude balance ( S <sub>21</sub> /S <sub>31</sub>  )	824~849	-1.0	-0.1/+0.1	+1.0	dB	
Phase balance (∠S <sub>21</sub> -∠S <sub>31</sub> +180)	824~849	-10	-1/+1	+10	deg.	
Input Impedance	Balanced	100			Ohm	
Output Impedance	Unbalance	50			Ohm	
Input Power	824~849	-	-	+13	dBm	
Operating Temperature		-30 ~ +85			°C	
Device size		1.4typ. x 1.0typ. x 0.5Max.			mm	



Customer Name	<b>Standard Specification</b>	FUJITSU MEDIA DEVICES LIMITED	
System	W-CDMA V (850) Tx (100/50ohm)	DATE	Mar. 07, 2007
FMD Part Number	FAR-F5KB-836M50-B4ER	Version 2.0d	




**Fig.1 Pass-band Characteristics**




**Fig.2 VSWR**

Customer Name	<b>Standard Specification</b>	FUJITSU MEDIA DEVICES LIMITED	
System	W-CDMA V (850) Tx (100/50ohm)	DATE	Mar. 07, 2007
FMD Part Number	FAR-F5KB-836M50-B4ER	Version 2.0d	




**Fig.3 In-band Characteristics**




**Fig.4 Wide-band Characteristics**

Customer Name	<b>Standard Specification</b>	FUJITSU MEDIA DEVICES LIMITED	
System	W-CDMA V (850) Tx (100/50ohm)	DATE	Mar. 07, 2007
FMD Part Number	FAR-F5KB-836M50-B4ER	Version 2.0d	




**Fig.5 Input Impedance (Balance)**




**Fig.6 Output Impedance (Unbalance)**

Customer Name	<b>Standard Specification</b>	FUJITSU MEDIA DEVICES LIMITED	
System	W-CDMA V (850) Tx (100/50ohm)	DATE	Mar. 07, 2007
FMD Part Number	FAR-F5KB-836M50-B4ER	Version 2.0d	



**Fig.7 Amplitude Balance**



**Fig.8 Phase Balance**