

## Three Phase AC Controller Modules


## PSUT 35

$$I_{RMS} = 3 \times 35 \text{ A}$$

$$V_{RRM} = 600-1200 \text{ V}$$

Preliminary Data Sheet

$V_{RSM}$ $V_{DSM}$ (V)	$V_{RRM}$ $V_{DRM}$ (V)	Type
700	600	PSUT 35/06
900	800	PSUT 35/08
1300	1200	PSUT 35/12



Symbol	Test Conditions	Maximum Ratings
$I_{RMS}$	$T_C = 85^\circ\text{C}$ ; (per phase)	35 A
$I_{TAVM}$	$T_C = 85^\circ\text{C}$ ; 180° sine, per Thyristor	16 A
$I_{TSM}$	$T_{VJ} = 45^\circ\text{C}$ t = 10 ms (50 Hz), sine	200 A
	$V_R = 0$ t = 8.3 ms (60 Hz), sine	210 A
	$T_{VJ} = 125^\circ\text{C}$ t = 10 ms (50 Hz), sine	180 A
$\int i^2 dt$	$V_R = 0$ t = 8.3 ms (60 Hz), sine	190 A
	$T_{VJ} = 45^\circ\text{C}$ t = 10 ms (50 Hz), sine	200 A <sup>2</sup> s
	$V_R = 0$ t = 8.3 ms (60 Hz), sine	180 A <sup>2</sup> s
$(di/dt)_{cr}$	$T_{VJ} = 125^\circ\text{C}$ t = 10 ms (50 Hz), sine	160 A <sup>2</sup> s
	$V_R = 0$ t = 8.3 ms (60 Hz), sine	150 A <sup>2</sup> s
	$T_{VJ} = T_{VJM}$ repetitive, $I_T = 20 \text{ A}$ $f=50\text{Hz}$ , $t_p=200\mu\text{s}$ $V_D=2/3V_{DRM}$	100 A/ $\mu\text{s}$
$(dv/dt)_{cr}$	$I_G=0.15 \text{ A}$ non repetitive, $I_T = I_{TAVM}$ $di_G/dt=0.15\text{A}/\mu\text{s}$	500 A/ $\mu\text{s}$
	$T_{VJ} = T_{VJM}$ $V_D=2/3V_{DRM}$ $R_{GK} = \infty$ , method 1 (linear voltage rise)	500 V/ $\mu\text{s}$
$P_{GM}$	$T_{VJ} = T_{VJM}$ $t_p=30\mu\text{s}$	$\leq 5 \text{ W}$
	$I_T = I_{TAVM}$ $t_p=300\mu\text{s}$	$\leq 2.5 \text{ W}$
$P_{GAVM}$		0.5 W
$V_{RGM}$		10 V
$T_{VJ}$		-40... + 125 °C
$T_{VJM}$		125 °C
$T_{stg}$		-40... + 125 °C
$V_{ISOL}$	50/60 Hz, RMS t = 1 min	2500 V~
	$I_{ISOL} \leq 1 \text{ mA}$ t = 1 s	3000 V~
$M_d$	Mounting torque (M4)	1.5 - 1.8 Nm
		14 - 16 lb.in.
<b>Weight</b>	typ.	16 g

### Features

- Thyristor controller for AC (circuit W3C acc. to IEC) for mains frequency □
- Isolation voltage 3000 V~
- Planar glass passivated chips
- Low forward voltage drop
- Leads suitable for PC board soldering
- UL registered, E 148688

### Applications

- Switching and control of single and three phase AC circuits
- Light and temperature control
- Softstart AC motor controller
- Solid state switches

### Advantages

- Easy to mount with two screws
- Space and weight savings
- Improved temperature and power cycling capability
- High power density
- Small and light weight

Data according to IEC 60747 refer to a single thyristor unless otherwise stated

Symbol	Test Conditions	Characteristic Value
$I_{D,R}$	$T_{VJ} = T_{VJM}, V_R = V_{RRM}, V_D = V_{DRM}$	$\leq 5$ mA
$V_T$	$I_T = 20$ A, $T_{VJ} = 25^\circ\text{C}$	$\leq 1.6$ V
$V_{TO}$	For power-loss calculations only	0.85 V
$r_T$		27 m $\Omega$
$V_{GT}$	$V_D = 6$ V, $T_{VJ} = 25^\circ\text{C}$	$\leq 1.5$ V
	$T_{VJ} = -40^\circ\text{C}$	$\leq 2.5$ V
$I_{GT}$	$V_D = 6$ V, $T_{VJ} = 25^\circ\text{C}$	$\leq 25$ mA
	$T_{VJ} = -40^\circ\text{C}$	$\leq 50$ mA
$V_{GD}$	$T_{VJ} = T_{VJM}, V_D = 2/3 V_{DRM}$	$\leq 0.2$ V
$I_{GD}$	$T_{VJ} = T_{VJM}, V_D = 2/3 V_{DRM}$	$\leq 3$ mA
$I_L$	$T_{VJ} = 25^\circ\text{C}, t_p = 10\mu\text{s}$ $I_G = 0.1$ A, $di_G/dt = 0.1$ A/ $\mu\text{s}$	$\leq 75$ mA
$I_H$	$T_{VJ} = 25^\circ\text{C}, V_D = 6$ V, $R_{GK} = \infty$	$\leq 50$ mA
$t_{gd}$	$T_{VJ} = 25^\circ\text{C}, V_D = 1/2 V_{DRM}$ $I_G = 0.1$ A, $di_G/dt = 0.1$ A/ $\mu\text{s}$	$\leq 2$ $\mu\text{s}$
$R_{thJC}$	per thyristor; DC	1.3 K/W
	per module	0.22 K/W
$R_{thJK}$	per thyristor; sine 180° el	typ. 1.8 K/W
	per module	typ. 0.3 K/W
$d_s$	Creeping distance on surface	11.2 mm
$d_A$	Creeping distance in air	5.0 mm
$a$	Max. allowable acceleration	50 m/s <sup>2</sup>

### Package style and outline

Dimensions in mm (1mm = 0.0394")

