

HD74AC126/HD74ACT126

Quad Buffer/Line Driver with 3-State Output

REJ03D0247-0300

Rev.3.00

Nov.12.2004

Description

The HD74AC126/HD74ACT126 is an quad buffer and line driver designed to be employed as a memory address driver, clock driver and bus oriented transmitter/receiver which provides improved PC board density.

Features


- 3-State Outputs Drive Bus Lines or Buffer Memory Address Registers
- Outputs Source/Sink 24 mA
- HD74ACT126 has TTL-Compatible Inputs
- Ordering Information: Ex. HD74AC126

| Part Name | Package Type | Package Code | Package Abbreviation | Taping Abbreviation (Quantity) |
|---------------|--------------------|--------------|----------------------|--------------------------------|
| HD74AC126FPEL | SOP-14 pin (JEITA) | FP-14DAV | FP | EL (2,000 pcs/reel) |
| HD74AC126RPEL | SOP-14 pin (JEDEC) | FP-14DNV | RP | EL (2,500 pcs/reel) |


Notes: 1. Please consult the sales office for the above package availability.

2. The packages with lead-free pins are distinguished from the conventional products by adding V at the end of the package code.

Pin Arrangement



Logic Symbol



Pin Names

- D Data Inputs
- E 3-State Output Enable Inputs (Active High)
- O Outputs

Truth Table

| Inputs | | Output |
|--------|---|--------|
| E | D | |
| H | L | L |
| H | H | H |
| L | X | Z |

- H : High Voltage Level
- L : Low Voltage Level
- X : Immaterial
- Z : High Impedance

Absolute Maximum Ratings

| Item | Symbol | Ratings | Unit | Condition |
|--|-------------------|----------------------|-------------|---------------------|
| Supply voltage | V_{CC} | -0.5 to 7 | V | |
| DC input diode current | I_{IK} | -20 | mA | $V_I = -0.5V$ |
| | | 20 | mA | $V_I = V_{CC}+0.5V$ |
| DC input voltage | V_I | -0.5 to $V_{CC}+0.5$ | V | |
| DC output diode current | I_{OK} | -50 | mA | $V_O = -0.5V$ |
| | | 50 | mA | $V_O = V_{CC}+0.5V$ |
| DC output voltage | V_O | -0.5 to $V_{CC}+0.5$ | V | |
| DC output source or sink current | I_O | ± 50 | mA | |
| DC V_{CC} or ground current per output pin | I_{CC}, I_{GND} | ± 50 | mA | |
| Storage temperature | T_{stg} | -65 to +150 | $^{\circ}C$ | |

Recommended Operating Conditions: HD74AC126

| Item | Symbol | Ratings | Unit | Condition |
|---|------------|---------------|-------------|------------------|
| Supply voltage | V_{CC} | 2 to 6 | V | |
| Input and Output voltage | V_I, V_O | 0 to V_{CC} | V | |
| Operating temperature | T_a | -40 to +85 | $^{\circ}C$ | |
| Input rise and fall time (except Schmitt inputs) V_{IN} 30% to 70% V_{CC} | t_r, t_f | 8 | ns/V | $V_{CC} = 3.0V$ |
| | | | | $V_{CC} = 4.5 V$ |
| | | | | $V_{CC} = 5.5 V$ |

DC Characteristics: HD74AC126

| Item | Symbol | V _{CC} (V) | Ta = 25°C | | | Ta = -40 to +85°C | | Unit | Condition | | |
|--------------------------|-------------------------|---------------------|-----------|-------|------|-------------------|------|------|---|--|--------------------------|
| | | | min. | typ. | max. | min. | max. | | | | |
| Input Voltage | V _{IH} | 3.0 | 2.1 | 1.5 | — | 2.1 | — | V | V _{OUT} = 0.1 V or V _{CC} - 0.1 V | | |
| | | 4.5 | 3.15 | 2.25 | — | 3.15 | — | | | | |
| | | 5.5 | 3.85 | 2.75 | — | 3.85 | — | | | | |
| | V _{IL} | 3.0 | — | 1.50 | 0.9 | — | 0.9 | | V _{OUT} = 0.1 V or V _{CC} - 0.1 V | | |
| | | 4.5 | — | 2.25 | 1.35 | — | 1.35 | | | | |
| | | 5.5 | — | 2.75 | 1.65 | — | 1.65 | | | | |
| Output voltage | V _{OH} | 3.0 | 2.9 | 2.99 | — | 2.9 | — | V | V _{IN} = V _{IL} or V _{IH} I _{OUT} = -50 μA | | |
| | | 4.5 | 4.4 | 4.49 | — | 4.4 | — | | | | |
| | | 5.5 | 5.4 | 5.49 | — | 5.4 | — | | | | |
| | | 3.0 | 2.58 | — | — | 2.48 | — | | | V _{IN} = V _{IL} or V _{IH} | I _{OH} = -12 mA |
| | | 4.5 | 3.94 | — | — | 3.80 | — | | | | I _{OH} = -24 mA |
| | | 5.5 | 4.94 | — | — | 4.80 | — | | | | I _{OH} = -24 mA |
| | V _{OL} | 3.0 | — | 0.002 | 0.1 | — | 0.1 | V | V _{IN} = V _{IL} or V _{IH} I _{OUT} = 50 μA | | |
| | | 4.5 | — | 0.001 | 0.1 | — | 0.1 | | | | |
| | | 5.5 | — | 0.001 | 0.1 | — | 0.1 | | | | |
| | | 3.0 | — | — | 0.32 | — | 0.37 | | | V _{IN} = V _{IL} or V _{IH} | I _{OL} = 12 mA |
| | | 4.5 | — | — | 0.32 | — | 0.37 | | | | I _{OL} = 24 mA |
| | | 5.5 | — | — | 0.32 | — | 0.37 | | | | I _{OL} = 24 mA |
| | Input leakage current | I _{IN} | 5.5 | — | — | ±0.1 | — | ±1.0 | μA | V _{IN} = V _{CC} or GND | |
| | 3 State current | I _{OZ} | 5.5 | — | — | ±0.5 | — | ±5.0 | μA | V _{IN(OE)} = V _{IL} , V _{IH} V _{IN} = V _{CC} or GND V _{OUT} = V _{CC} or GND | |
| | Dynamic output current* | I _{OLD} | 5.5 | — | — | — | 86 | — | mA | V _{OLD} = 1.1 V | |
| I _{OHD} | | 5.5 | — | — | — | -75 | — | mA | V _{OHD} = 3.85 V | | |
| Quiescent supply current | I _{CC} | 5.5 | — | — | 8.0 | — | 80 | μA | V _{IN} = V _{CC} or ground | | |

*Maximum test duration 2.0 ms, one output loaded at a time.

Recommended Operating Conditions: HD74ACT126

| Item | Symbol | Ratings | Unit | Condition |
|--|---------------------------------|----------------------|------|--|
| Supply voltage | V _{CC} | 2 to 6 | V | |
| Input and output voltage | V _I , V _O | 0 to V _{CC} | V | |
| Operating temperature | Ta | -40 to +85 | °C | |
| Input rise and fall time (except Schmitt inputs) V _{IN} 0.8 to 2.0 V | tr, tf | 8 | ns/V | V _{CC} = 4.5V V _{CC} = 5.5V |

DC Characteristics: HD74ACT126

| Item | Symbol | V _{CC} (V) | Ta = 25°C | | | Ta = -40 to +85°C | | Unit | Condition | | | | |
|--------------------------------|-------------------|---------------------|-----------------|-------|------|-------------------|------|------|---|--|--------------------------|----|--|
| | | | min. | typ. | max. | min. | max. | | | | | | |
| Input voltage | V _{IH} | 4.5 | 2.0 | 1.5 | — | 2.0 | — | V | V _{OUT} = 0.1 V or V _{CC} -0.1 V | | | | |
| | | 5.5 | 2.0 | 1.5 | — | 2.0 | — | | | | | | |
| | V _{IL} | 4.5 | — | 1.5 | 0.8 | — | 0.8 | | V _{OUT} = 0.1 V or V _{CC} -0.1 V | | | | |
| | | 5.5 | — | 1.5 | 0.8 | — | 0.8 | | | | | | |
| Output voltage | V _{OH} | 4.5 | 4.4 | 4.49 | — | 4.4 | — | V | V _{IN} = V _{IL} or V _{IH} I _{OUT} = -50 μA | | | | |
| | | 5.5 | 5.4 | 5.49 | — | 5.4 | — | | | | | | |
| | | 4.5 | 3.94 | — | — | 3.80 | — | | | V _{IN} = V _{IL} I _{OH} = -24 mA | | | |
| | | 5.5 | 4.94 | — | — | 4.80 | — | | | | I _{OH} = -24 mA | | |
| | V _{OL} | 4.5 | — | 0.001 | 0.1 | — | 0.1 | | V _{IN} = V _{IL} or V _{IH} I _{OUT} = 50 μA | | | | |
| | | 5.5 | — | 0.001 | 0.1 | — | 0.1 | | | | | | |
| | | 4.5 | — | — | 0.32 | — | 0.37 | | | V _{IN} = V _{IL} I _{OL} = 24 mA | | | |
| | | 5.5 | — | — | 0.32 | — | 0.37 | | | | I _{OL} = 24 mA | | |
| | | Input current | I _{IN} | 5.5 | — | — | ±0.1 | | | — | ±1.0 | μA | V _{IN} = V _{CC} or GND |
| | | 3 State current | I _{OZ} | 5.5 | — | — | ±0.5 | | | — | ±5.0 | μA | V _{IN} = V _{IL} , V _{IH} V _{OUT} = V _{CC} or GND |
| I _{CC} /input current | I _{CC} T | 5.5 | — | 0.6 | — | — | 1.5 | mA | V _{IN} = V _{CC} -2.1 V | | | | |
| Dynamic output current* | I _{OLD} | 5.5 | — | — | — | 86 | — | mA | V _{OLD} = 1.1 V | | | | |
| | I _{OHD} | 5.5 | — | — | — | -75 | — | mA | V _{OHD} = 3.85 V | | | | |
| Quiescent supply current | I _{CC} | 5.5 | — | — | 8.0 | — | 80 | μA | V _{IN} = V _{CC} or ground | | | | |

*Maximum test duration 2.0 ms, one output loaded at a time.

AC Characteristics: HD74AC126

| Item | Symbol | V _{CC} (V)* ¹ | Ta = +25°C C _L = 50 pF | | | Ta = -40°C to +85°C C _L = 50 pF | | Unit |
|-------------------|------------------|-----------------------------------|--------------------------------------|-----|------|---|------|------|
| | | | Min | Typ | Max | Min | Max | |
| Propagation Delay | t _{PLH} | 3.3 | 1.0 | 6.5 | 9.0 | 1.0 | 10.0 | ns |
| | | 5.0 | 1.0 | 5.5 | 7.0 | 1.0 | 7.5 | |
| Propagation Delay | t _{PHL} | 3.3 | 1.0 | 6.5 | 9.0 | 1.0 | 10.0 | |
| | | 5.0 | 1.0 | 5.0 | 7.0 | 1.0 | 7.5 | |
| Enable Time | t _{ZH} | 3.3 | 1.0 | 6.5 | 12.5 | 1.0 | 13.0 | |
| | | 5.0 | 1.0 | 5.5 | 9.0 | 1.0 | 9.5 | |
| Enable Time | t _{ZL} | 3.3 | 1.0 | 7.0 | 12.0 | 1.0 | 13.0 | |
| | | 5.0 | 1.0 | 5.5 | 9.0 | 1.0 | 9.5 | |
| Disable Time | t _{HZ} | 3.3 | 1.0 | 8.0 | 12.0 | 1.0 | 12.5 | |
| | | 5.0 | 1.0 | 6.5 | 10.0 | 1.0 | 10.5 | |
| Disable Time | t _{LZ} | 3.3 | 1.0 | 7.0 | 12.5 | 1.0 | 13.5 | |
| | | 5.0 | 1.0 | 6.0 | 10.0 | 1.0 | 10.5 | |

Note: 1. Voltage Range 3.3 is 3.3 V ± 0.3 V
Voltage Range 5.0 is 5.0 V ± 0.5 V

AC Characteristics: HD74ACT126

| Item | Symbol | V _{CC} (V)* ¹ | Ta = +25°C C _L = 50 pF | | | Ta = -40°C to +85°C C _L = 50 pF | | Unit |
|-------------------|------------------|-----------------------------------|--------------------------------------|-----|------|---|------|------|
| | | | Min | Typ | Max | Min | Max | |
| Propagation Delay | t _{PLH} | 5.0 | 1.0 | 6.5 | 9.0 | 1.0 | 10.0 | ns |
| Propagation Delay | t _{PHL} | 5.0 | 1.0 | 7.0 | 9.0 | 1.0 | 10.0 | |
| Enable Time | t _{ZH} | 5.0 | 1.0 | 6.0 | 9.0 | 1.0 | 10.0 | |
| Enable Time | t _{ZL} | 5.0 | 1.0 | 7.0 | 10.0 | 1.0 | 11.0 | |
| Disable Time | t _{HZ} | 5.0 | 1.0 | 8.0 | 10.5 | 1.0 | 11.5 | |
| Disable Time | t _{LZ} | 5.0 | 1.0 | 7.0 | 10.5 | 1.0 | 11.5 | |

Note: 1. Voltage Range 5.0 is 5.0 V ± 0.5 V




Capacitance

| Item | Symbol | Typ | Unit | Condition |
|-------------------------------|-----------------|------|------|-------------------------|
| Input capacitance | C _{IN} | 4.5 | pF | V _{CC} = 5.5 V |
| Power dissipation capacitance | C _{PD} | 45.0 | pF | V _{CC} = 5.0 V |

Not recommended for new design

Package Dimensions



As of January, 2003
Unit: mm



*Ni/Pd/Au plating

| | |
|------------------------|----------|
| Package Code | FP-14DAV |
| JEDEC | — |
| JEITA | Conforms |
| Mass (reference value) | 0.23 g |

As of January, 2003
Unit: mm



*Ni/Pd/Au plating

| | |
|------------------------|----------|
| Package Code | FP-14DNV |
| JEDEC | Conforms |
| JEITA | Conforms |
| Mass (reference value) | 0.13 g |

Renesas Technology Corp. Sales Strategic Planning Div. Nippon Bldg., 2-6-2, Ohte-machi, Chiyoda-ku, Tokyo 100-0004, Japan

Keep safety first in your circuit designs!

1. Renesas Technology Corp. puts the maximum effort into making semiconductor products better and more reliable, but there is always the possibility that trouble may occur with them. Trouble with semiconductors may lead to personal injury, fire or property damage.
Remember to give due consideration to safety when making your circuit designs, with appropriate measures such as (i) placement of substitutive, auxiliary circuits, (ii) use of nonflammable material or (iii) prevention against any malfunction or mishap.

Notes regarding these materials

1. These materials are intended as a reference to assist our customers in the selection of the Renesas Technology Corp. product best suited to the customer's application; they do not convey any license under any intellectual property rights, or any other rights, belonging to Renesas Technology Corp. or a third party.
2. Renesas Technology Corp. assumes no responsibility for any damage, or infringement of any third-party's rights, originating in the use of any product data, diagrams, charts, programs, algorithms, or circuit application examples contained in these materials.
3. All information contained in these materials, including product data, diagrams, charts, programs and algorithms represents information on products at the time of publication of these materials, and are subject to change by Renesas Technology Corp. without notice due to product improvements or other reasons. It is therefore recommended that customers contact Renesas Technology Corp. or an authorized Renesas Technology Corp. product distributor for the latest product information before purchasing a product listed herein.
The information described here may contain technical inaccuracies or typographical errors.
Renesas Technology Corp. assumes no responsibility for any damage, liability, or other loss rising from these inaccuracies or errors.
Please also pay attention to information published by Renesas Technology Corp. by various means, including the Renesas Technology Corp. Semiconductor home page (<http://www.renesas.com>).
4. When using any or all of the information contained in these materials, including product data, diagrams, charts, programs, and algorithms, please be sure to evaluate all information as a total system before making a final decision on the applicability of the information and products. Renesas Technology Corp. assumes no responsibility for any damage, liability or other loss resulting from the information contained herein.
5. Renesas Technology Corp. semiconductors are not designed or manufactured for use in a device or system that is used under circumstances in which human life is potentially at stake. Please contact Renesas Technology Corp. or an authorized Renesas Technology Corp. product distributor when considering the use of a product contained herein for any specific purposes, such as apparatus or systems for transportation, vehicular, medical, aerospace, nuclear, or undersea repeater use.
6. The prior written approval of Renesas Technology Corp. is necessary to reprint or reproduce in whole or in part these materials.
7. If these products or technologies are subject to the Japanese export control restrictions, they must be exported under a license from the Japanese government and cannot be imported into a country other than the approved destination.
Any diversion or reexport contrary to the export control laws and regulations of Japan and/or the country of destination is prohibited.
8. Please contact Renesas Technology Corp. for further details on these materials or the products contained therein.



RENESAS SALES OFFICES

<http://www.renesas.com>

Refer to "<http://www.renesas.com/en/network>" for the latest and detailed information.

Renesas Technology America, Inc.
450 Holger Way, San Jose, CA 95134-1368, U.S.A
Tel: <1> (408) 382-7500, Fax: <1> (408) 382-7501

Renesas Technology Europe Limited
Dukes Meadow, Millboard Road, Bourne End, Buckinghamshire, SL8 5FH, U.K.
Tel: <44> (1628) 585-100, Fax: <44> (1628) 585-900

Renesas Technology Hong Kong Ltd.
7th Floor, North Tower, World Finance Centre, Harbour City, 1 Canton Road, Tsimshatsui, Kowloon, Hong Kong
Tel: <852> 2265-6688, Fax: <852> 2730-6071

Renesas Technology Taiwan Co., Ltd.
10th Floor, No.99, Fushing North Road, Taipei, Taiwan
Tel: <886> (2) 2715-2888, Fax: <886> (2) 2713-2999

Renesas Technology (Shanghai) Co., Ltd.
Unit2607 Ruijing Building, No.205 Maoming Road (S), Shanghai 200020, China
Tel: <86> (21) 6472-1001, Fax: <86> (21) 6415-2952

Renesas Technology Singapore Pte. Ltd.
1 Harbour Front Avenue, #06-10, Keppel Bay Tower, Singapore 098632
Tel: <65> 6213-0200, Fax: <65> 6278-8001