


3TF3 3-Pole and CRL0F3 Reversing Contactors with AC or DC Coil

 <p>3TF3200</p>	Ordering Information		Coil Voltage Codes																												
	<ul style="list-style-type: none"> Select Contactor from table below. Complete Catalog Number from coil codes table shown. Maximum combination of top and side mount auxiliary contacts is 4 per contactor. Overload Relays see pages 416–418. Accessories see page 419. Replacement Parts see pages 920–921. 		<table border="1"> <thead> <tr> <th colspan="2">AC Voltage</th> <th>Code</th> </tr> <tr> <th>60Hz</th> <th>50Hz</th> <th></th> </tr> </thead> <tbody> <tr><td>24</td><td>24</td><td>C2</td></tr> <tr><td>120</td><td>110</td><td>K6</td></tr> <tr><td>208</td><td>175</td><td>M1</td></tr> <tr><td>277</td><td>220</td><td>U1</td></tr> <tr><td>240</td><td>220</td><td>P6</td></tr> <tr><td>480</td><td>380–415</td><td>V0</td></tr> <tr><td>600</td><td>500</td><td>S0</td></tr> </tbody> </table>		AC Voltage		Code	60Hz	50Hz		24	24	C2	120	110	K6	208	175	M1	277	220	U1	240	220	P6	480	380–415	V0	600	500	S0
	AC Voltage		Code																												
60Hz	50Hz																														
24	24	C2																													
120	110	K6																													
208	175	M1																													
277	220	U1																													
240	220	P6																													
480	380–415	V0																													
600	500	S0																													
		<table border="1"> <thead> <tr> <th colspan="2">DC Voltage</th> <th>Code</th> </tr> </thead> <tbody> <tr><td>12</td><td></td><td>A4</td></tr> <tr><td>24</td><td></td><td>B4</td></tr> <tr><td>48</td><td></td><td>W4</td></tr> <tr><td>125</td><td></td><td>G4</td></tr> <tr><td>240</td><td></td><td>O4</td></tr> </tbody> </table>		DC Voltage		Code	12		A4	24		B4	48		W4	125		G4	240		O4										
DC Voltage		Code																													
12		A4																													
24		B4																													
48		W4																													
125		G4																													
240		O4																													

3TF3 Non-Reversing Contactors

Ampere Rating Enclosed		1 Phase HP Ratings		3 Phase HP Ratings				Auxiliary Contacts		AC Coil Voltage		DC Coil Voltage	
IEC AC-3	UL	115V	230V	200V	230V	460V	575V	NO	NC	Catalog No	Price \$	Catalog No	Price \$
9	20	½	1½	2	3	5	7½	0	0	3TF3000-0A††	101.	3TF3000-0B††	140.
9	20	½	1½	2	3	5	7½	1	0	3TF3010-0A††	114.	3TF3010-0B††	153.
12	20	1	2	3	3	7½	10	0	0	3TF3100-0A††	133.	3TF3100-0B††	172.
12	20	1	2	3	3	7½	10	1	0	3TF3110-0A††	146.	3TF3110-0B††	185.
16	30	1	3	5	5	10	15	0	0	3TF3200-0A††	150.	3TF3200-0B††	195.
16	30	1	3	5	5	10	15	1 ^⓪	1	3TF3211-0A††	176.	3TF3211-0B††	221.
22	30	2	3	7½	7½	15	20	0	0	3TF3300-0A††	159.	3TF3300-0B††	205.
22	30	2	3	7½	7½	15	20	1 ^⓪	1	3TF3311-0A††	185.	3TF3311-0B††	231.
32	55	3	5	10	10	25	30	0	0	3TF3400-0A††	169.	3TF3400-0B††	250.
32	55	3	5	10	10	25	30	1 ^⓪	1	3TF3411-0A††	195.	3TF3411-0B††	276.
38	55	3	7½	10	15	25	30	0	0	3TF3500-0A††	197.	3TF3500-0B††	272.
38	55	3	7½	10	15	25	30	1 ^⓪	1	3TF3511-0A††	223.	3TF3511-0B††	298.

Factory Assembled 3TF3 Reversing Contactors

All CRL0F3 Reversers are mechanically and electrically interlocked and are supplied wired. Reversing contactors can be assembled from components. See Accessories.

Ampere Rating Enclosed		3 Phase HP Ratings				Auxiliary Contacts ^① Per Contactor		AC Coil Voltage		DC Coil Voltage	
IEC AC-3	UL	200V	230V	460V	575V	NO	NC	Catalog No	Price \$	Catalog No	Price \$
9	20	2	3	5	7½	2	2	CRL0F3022††	325.	CRL0F3022††	531.
12	20	3	3	7½	10	2	2	CRL0F3122††	390.	CRL0F3122††	629.
16	30	5	5	10	15	2	1	CRL0F3221††	431.	CRL0F3221††	656.
22	30	7½	7½	15	20	2	1	CRL0F3321††	472.	CRL0F3321††	672.
32	55	10	10	25	30	2	1	CRL0F3421††	533.	CRL0F3421††	711.
38	55	10	15	25	30	2	1	CRL0F3521††	683.	CRL0F3521††	954.

①1 NC auxiliary contact per contactor used for electrical interlock.

②Contactors with side mounted auxiliary contacts cannot be used with mechanical interlock Catalog Number 3TX4091-1A.