MECHANICALLY VARIABLE DELAY LINE (SERIES 1509 & 1509J)



FEATURES PACKAGES

• Ideal for "Set and Forget" applications

 Multi-turn adjustment screw (1509: 20 turns, 1509J: 60 turns)

Stackable for PC board economy


• Fits standard 14-pin DIP socket (1509)

• 20mil x 10mil flat leads (1509)

• #20 gauge leads (1509J)

Resolution: As low as 0.15ns

Dielectric breakdown: 50 Vdc
 Temperature coefficient: 200 PPM/°C



.300 MAX. 1509-xxz 1509J-xxz

 $xx = Max Delay (T_D)$ z = Impedance Code

FUNCTIONAL DESCRIPTION


The 1509- and 1509J-series devices are mechanically variable, passive delay lines. The signal input (IN) is reproduced at the tap output (TAP), shifted by an amount which can be adjusted between 0 and T_D , where T_D is the device dash number. The fixed output (OUT) reproduces the input, delayed by T_D , and must be terminated to match the characteristic impedance of the line, which is given

PIN DESCRIPTIONS

IN Signal Input
TAP Variable Output
OUT Fixed Output
GND Ground

by the letter code that follows the dash number (See Table). The tap output is unbuffered. The 3dB bandwidth of the line is given by $3.5 / T_R$, where T_R is the rise time of the line (See Table).


SERIES SPECIFICATIONS



Functional Diagram

DASH NUMBER SPECIFICATIONS

Part	Max Dly	TR	Imped	RDC
Number	(ns)	(ns)	(Ω)	(Ω)
1509-05B	5	3	100	0.4
1509-20C	20	8	200	1.0
1509-20D	20	8	250	1.0
1509J-10B	10	4	100	0.8
1503J-40C	40	9	200	1.5



1.750 MAX.

1.750 MAX.

1.750 MAX.

OUT TAP

OUT TAP

OUT TAP

1.750 MAX.

Package Dimensions – 1509J

©2001 Data Delay Devices

PASSIVE DELAY LINE TEST SPECIFICATIONS

TEST CONDITIONS

INPUT: OUTPUT:

Ambient Temperature: $25^{\circ}\text{C} \pm 3^{\circ}\text{C}$ R_{load}: $10\text{M}\Omega$ Input Pulse: High = 3.0V typical C_{load}: 10pf


Low = 0.0V typical **Threshold:** 50% (Rising & Falling)

Source Impedance: 50Ω Max.


Rise/Fall Time: 3.0 ns Max. (measured

at 10% and 90% levels)

NOTE: The above conditions are for test only and do not in any way restrict the operation of the device.



Timing Diagram For Testing



Test Setup