

# Double Balanced Mixer

# Model MM134xG-1

Ultra-Broadband

RF 1.5 to 26.5 GHz

## Electrical Specifications:<sup>(1)</sup>

Parameter	Conditions			Specifications		
	RF (GHz)	LO (GHz)	IF (MHz)	Min	Typical	Max
SSB Conversion loss: <sup>(2) (3)</sup>	2.0-26.5	2.0-26.5	DC-500		7.5 dB	9.50 dB
	1.5-26.5	1.5-26.5	DC-700		8.5 dB	10.0 dB
	1.5-26.5	1.5-26.5	DC-1250		9.5 dB	11.5 dB
Third LO Harmonic Conversion Loss: <sup>(2) (3)</sup>	6.0-26.5	2.0-9.0	DC-500		17.5 dB	22 dB
	6.0-26.5	2.0-9.0	DC-700		18.5 dB	23 dB
	6.0-26.5	2.0-9.0	DC-1250		19.5 dB	24 dB
Isolation	LO to RF:	1.5-3.0	18 dB	25 dB	20 dB	30 dB
		3.0-26.5		5 dB		
	LO to IF:	1.5-4.0	18 dB	25 dB	20 dB	35 dB
		4.0-18.0		23 dB		
	RF to IF:	1.5-4.0	20 dB	35 dB	20 dB	35 dB
		4.0-26.5		23 dB		
Input 1-dB Compression Point:	1.5-26.5	1.5-26.5	DC-1250		+3 dBm	
Input Third Order Intercept Point:	1.5-26.5	1.5-26.5	DC-1250		+12 dBm	
LO Power: <sup>(4)</sup>	1.5-26.5	1.5-26.5	DC-1250		+9 dBm	

Model MM134xG-1

Drop-In  
 Module or With  
 SMA(F) Connectors  
 M = Module  
 P = With Connectors

### Notes:

- Specifications are guaranteed when tested as a downconverter in a 50 Ohm system at +25 °C with the nominal LO power. Specifications indicated as typical are not guaranteed.
- Noise figure is typically within ±0.5 dB of conversion loss for IF frequencies greater than 10 MHz.
- Conversion loss typically degrades less than 0.5 dB at +100 °C and improves less than 0.5 dB at -55 °C.
- Usable LO drives are up to 2 dB below and 3 dB above nominal.

## Typical Performance at 25°C

