

Linear Systems replaces discontinued Intersil IT120A

The IT120A is a monolithic pair of NPN transistors mounted in a single TO-71 package. The monolithic dual chip design reduces parasitics and gives better performance while ensuring extremely tight matching. The IT120A is a direct replacement for discontinued Intersil IT120A.

The hermetically sealed TO-71 is well suited for hi-rel and harsh environment applications.

(See Packaging Information).

IT120A Features:

- High h_{FE} at low current
- Tight matching
- Tight V_{BE} tracking
- Low Output Capacitance

FEATURES

Direct Replacement for INTERSIL IT120A

HIGH h_{FE} @ LOW CURRENT ≥ 200 @ $10\mu A$

OUTPUT CAPACITANCE $\leq 2.0pF$

V_{BE} tracking $\leq 3.0mV/^\circ C$

ABSOLUTE MAXIMUM RATINGS¹

@ $25^\circ C$ (unless otherwise noted)

Maximum Temperatures

Storage Temperature $-65^\circ C$ to $+200^\circ C$

Operating Junction Temperature $-55^\circ C$ to $+150^\circ C$

Maximum Power Dissipation

Continuous Power Dissipation (One side) 250mW

Continuous Power Dissipation (Both sides) 500mW

Linear Derating factor (One side) $2.3mW/^\circ C$

Linear Derating factor (Both sides) $4.3mW/^\circ C$

Maximum Currents

Collector Current 10mA

MATCHING CHARACTERISTICS @ $25^\circ C$ (unless otherwise stated)

SYMBOL	CHARACTERISTIC	MIN	TYP	MAX	UNITS	CONDITIONS
$ V_{BE1} - V_{BE2} $	Base Emitter Voltage Differential	--	--	1	mV	$I_C = 10\mu A, V_{CE} = 5V$
$\Delta V_{BE1} - V_{BE2} / \Delta T$	Base Emitter Voltage Differential Change with Temperature	--	--	3	$\mu V/^\circ C$	$I_C = 10\mu A, V_{CE} = 5V$ $T_A = -55^\circ C$ to $+125^\circ C$
$ I_{B1} - I_{B2} $	Base Current Differential	--	--	2.5	nA	$I_C = 10\mu A, V_{CE} = 5V$

ELECTRICAL CHARACTERISTICS @ $25^\circ C$ (unless otherwise noted)

SYMBOL	CHARACTERISTICS	MIN.	TYP.	MAX.	UNITS	CONDITIONS
BV_{CBO}	Collector to Base Voltage	45	--	--	V	$I_C = 10\mu A, I_E = 0$
BV_{CEO}	Collector to Emitter Voltage	45	--	--	V	$I_C = 10\mu A, I_B = 0$
BV_{EBO}	Emitter-Base Breakdown Voltage	6.2	--	--	V	$I_E = 10\mu A, I_C = 0$
BV_{CCO}	Collector to Collector Voltage	60	--	--	V	$I_C = 10\mu A, I_E = 0$
h_{FE}	DC Current Gain	200	--	--		$I_C = 10\mu A, V_{CE} = 5V$
		225	--	--		$I_C = 1.0mA, V_{CE} = 5V$
$V_{CE(SAT)}$	Collector Saturation Voltage	--	--	0.5	V	$I_C = 0.5mA, I_B = 0.05mA$
I_{EBO}	Emitter Cutoff Current	--	--	1	nA	$I_C = 0, V_{EB} = 3V$
I_{CBO}	Collector Cutoff Current	--	--	1	nA	$I_E = 0, V_{CB} = 45V$
C_{OBO}	Output Capacitance	--	--	2	pF	$I_E = 0, V_{CB} = 5V$
C_{C1C2}	Collector to Collector Capacitance	--	--	2	pF	$V_{CC} = 0V$
I_{C1C2}	Collector to Collector Leakage Current	--	--	10	nA	$V_{CC} = \pm 60V$
f_T	Current Gain Bandwidth Product	220	--	--	MHz	$I_C = 1mA, V_{CE} = 5V$
NF	Narrow Band Noise Figure	--	--	3	dB	$I_C = 100\mu A, V_{CE} = 5V, BW = 200Hz, R_G = 10K\Omega, f = 1KHz$

Notes:

1. Absolute Maximum ratings are limiting values above which serviceability may be impaired
2. The reverse base-to-emitter voltage must never exceed 6.2 volts; the reverse base-to-emitter current must never exceed $10\mu A$.

Available Packages:

IT120A in TO-71
IT120A available as bare die



Please contact Micross for full package and die dimensions:

Email: chipcomponents@micross.com
Web: www.micross.com/distribution.aspx

TO-71 (Bottom View)

