

# DOUBLE TRIODE

# ECC32

Double triode with separate cathodes for use as a paraphase A.F. amplifier and in phase inverters, multi-vibrators, etc.

## HEATER

$V_h$	6.3	V
$I_h$	0.95	A

## CAPACITANCES

$C_{a-b}$	0.8	$\mu\mu\text{F}$
$C_{a-g}$ (each section)	4.3	$\mu\mu\text{F}$
$C_{g-k}$ (each section)	4.3	$\mu\mu\text{F}$
$C_{a-k}$ (each section)	2.0	$\mu\mu\text{F}$

## CHARACTERISTICS (each section)

$V_a$	250	V
$V_g$	-4.6	V
$I_a$	6.0	mA
$g_m$	2.3	mA/V
$\mu$	32	
$r_a$	14	k $\Omega$

## OPERATING CONDITIONS AS RESISTANCE-CAPACITY-COUPLED AMPLIFIER

$V_b$ (V)	$R_a$ (k $\Omega$ )	$I_a$ (mA)	$R_k$ (k $\Omega$ )	$\frac{V_{out}}{V_{in}}$	$V_{out}^*$ (V)	$D_{tot}$ (%)	$R_{g1}^{**}$ (k $\Omega$ )
400	47	3.9	1.2	21	67	3.7	150
350	47	3.4	1.2	20.5	57	3.6	150
300	47	2.9	1.2	20	48	3.5	150
250	47	2.4	1.2	19.5	37	3.4	150
200	47	1.9	1.2	19.5	26	3.2	150
400	100	2.1	2.7	25	81	3.0	330
350	100	1.8	2.2	25	69	2.9	330
300	100	1.6	2.2	24.5	54	2.8	330
250	100	1.3	2.2	24.5	44	2.6	330
200	100	1.05	2.2	24	32	2.4	330
400	220	1.1	3.9	27.5	81	2.3	680
350	220	0.95	3.9	27.5	68	2.2	680
300	220	0.85	3.9	27	56	2.2	680
250	220	0.7	3.9	27	45	2.1	680
200	220	0.55	3.9	26.5	34	2.0	680

\* $V_{out}$ =Output voltage at start of  $I_{g1}$  or at  $D_{tot}=10\%$ .

\*\* $R_{g1}$ =Grid resistance of following valve.

## LIMITING VALUES (each section)

$V_a$ max.	300	V
$p_a$ max.	5	W
$I_k$ max.	50	mA
$R_{g-k}$ max.	1.5	M $\Omega$
$V_{h-k}$ max.	50	V
$R_{h-k}$ max.	20	k $\Omega$



# ECC32

## DOUBLE TRIODE

Double triode with separate cathodes for use as a  
paraphase A.F. amplifier and in phase inverters,  
multi-vibrators, etc.

