



Sparkle Power Inc.
A Leading Power Supply
Manufacturer Website:
www.sparklepower.com



FSP500-60EGA

(80PLUS Gold, RoHS Compliant)

**500 Watts ATX12V 2.3 Switching Power Supply
Meet 2010 ErP**

Features

- Complied with ATX12V 2.3 standard
- Active Power Factor Correction (PFC) meet EN61000-3-2
- High efficiency and reliability
- Compatible with European Union Directive 2002/95/EC (Restriction on Hazardous Substances).
- Remote ON/OFF function
- Internal 12V DC fan included
- Noise Killer (thermal fan speed control function)
- Low noise and ripple
- Output over voltage, short circuit, and over current protection
- 100% Hi-pot, ATE, and burn-in tested
- Re-settable power shut down
- Complies with FCC part 15 subpart J class B 115Vac operation, and CISPR 22 class B at 230Vac operation
- Approved by CUL/UL60950-1, TUV EN60950-1, CB 60950-1 report, FCC, EMC.

Input Characteristics

Input Range: 90 ~ 264Vac, Full Range Input

Frequency: 47 ~ 63Hz

Input Current: Max 6A @ 115Vac, 3A @ 230Vac

Inrush Current: No damage.

Output Characteristics

	MINIMUM LOAD	NORMAL LOAD	MAXIMUM LOAD	LOAD REG.	LINE REG.	RIPPLE & NOISE
+3.3V	0.1A	12A	24/3A	±5%	±1%	50mV P-P
+5V	0.2A	12A	11/24A	±5%	±1%	50mV P-P
+12V1	0.1A	8A	18A	±5%	±1%	120mV P-P
+12V2	0A	8A	18A	±5%	±1%	120mV P-P
-12V	0A	0.15A	0.3A	±10%	±2%	200mV P-P
+5Vsb	0A	1.5A	3.5A	±5%	±1%	50mV P-P

*+3.3V & +5V total output does not exceed 130W
when +5V is loaded to 24A, then +3.3V maximum load is 3A
when +3.3V is loaded to 24A, then +5V maximum load is 10A
*+12V1 & +12V2 total output does not exceed 432W(36A)

Sparkle Power Inc.

Main Office

1000 Rock Avenue
San Jose, CA 95131
TEL: 408-519-8888
FAX: 408-519-9999
E-MAIL: info@sparklepower.com

Sparkle Power Inc.

Los Angeles Office

17071 Green Drive
City of Industry, CA 91745
TEL: 626-839-7180
FAX: 626-839-3395