

SPECIFICATIONS

Mechanical

Contact Retention Force: 1.36kg min.

Electrical

Current Rating: 3A Per Pin Min.

Dielectric Withstanding Voltage: 1000V RMS

Insulation Resistance: 1000MW min.

Physical


Housing: High temperature, UL 94V-0 Color Black

Contact: Copper Alloy


Plating: See "ORDERING INFORMATION" **Operating Temperature:** -55 to +105


SHROUDED Connector


HL35 Series R/A, T/H Type Plug 2.54mmX2.54mm [.100] X [.100] Pitch




DRAWING









ORDERING INFORMATION

PRODUCT NO.: HL35 Header See Drawing No.307-0000-297 Shrouded Header NONE: DIM. D=2.79mm Termination&Contact Type L: DIM. D=2.29mm Contact Area Plating No. Of Pos 05 = 05 Pos 1= Gold Flish 3=30u" Gold 6=10u" Gold 7=15u" Gold 25 = 25 Pos F=Gold Flish With Lead Free RoHS COMPLIANCE v=15u" Min Gold With Lead Free RoHS COMPLIANCE E=Tin Plated With Lead Free RoHS COMPLIANCE H=30 u" Min Gold With Lead Free RoHS COMPLIANCE

See The Attachment 1



HLNNNNN-(X) (XX) XN



CODE
DO
D1 LAST PIN IS REMOVED D2 20th PIN IS REMOVED D3 21th PIN IS REMOVED D4 8th PIN IS REMOVED D6 25th PIN IS REMOVED D7 26th PIN IS REMOVED D8 28th PIN IS REMOVED D9 15th PIN IS REMOVED E2 22th PIN IS REMOVED E3 30th PIN IS REMOVED E4 38th PIN IS REMOVED P0 4th PIN IS REMOVED P1 6th PIN IS REMOVED P3 7th PIN IS REMOVED P4 5th PIN IS REMOVED P5 10th PIN IS REMOVED P6 2nd PIN IS REMOVED P7 3rd PIN IS REMOVED P8 17th PIN IS REMOVED L1 12th PIN IS REMOVED L3 32th PIN IS REMOVED L5 18th PIN IS REMOVED L6 14th PIN IS REMOVED
D2 20th PIN IS REMOVED D3 21th PIN IS REMOVED D4 8th PIN IS REMOVED D6 25th PIN IS REMOVED D7 26th PIN IS REMOVED D8 28th PIN IS REMOVED D9 15th PIN IS REMOVED E2 22th PIN IS REMOVED E3 30th PIN IS REMOVED E4 38th PIN IS REMOVED P0 4th PIN IS REMOVED P1 6th PIN IS REMOVED P3 7th PIN IS REMOVED P4 5th PIN IS REMOVED P5 10th PIN IS REMOVED P6 2nd PIN IS REMOVED P7 3rd PIN IS REMOVED P8 17th PIN IS REMOVED P9 9th PIN IS REMOVED L1 12th PIN IS REMOVED L3 32th PIN IS REMOVED L5 18th PIN IS REMOVED L6 14th PIN IS REMOVED
D3 21th PIN IS REMOVED D4 8th PIN IS REMOVED D6 25th PIN IS REMOVED D7 26th PIN IS REMOVED D8 28th PIN IS REMOVED D9 15th PIN IS REMOVED E2 22th PIN IS REMOVED E3 30th PIN IS REMOVED E4 38th PIN IS REMOVED P0 4th PIN IS REMOVED P1 6th PIN IS REMOVED P3 7th PIN IS REMOVED P4 5th PIN IS REMOVED P5 10th PIN IS REMOVED P6 2nd PIN IS REMOVED P7 3rd PIN IS REMOVED P8 17th PIN IS REMOVED P9 9th PIN IS REMOVED L1 12th PIN IS REMOVED L3 32th PIN IS REMOVED L5 18th PIN IS REMOVED L6 14th PIN IS REMOVED
D4 8th PIN IS REMOVED D6 25th PIN IS REMOVED D7 26th PIN IS REMOVED D8 28th PIN IS REMOVED D9 15th PIN IS REMOVED E2 22th PIN IS REMOVED E3 30th PIN IS REMOVED E4 38th PIN IS REMOVED P0 4th PIN IS REMOVED P1 6th PIN IS REMOVED P3 7th PIN IS REMOVED P4 5th PIN IS REMOVED P5 10th PIN IS REMOVED P6 2nd PIN IS REMOVED P7 3rd PIN IS REMOVED P8 17th PIN IS REMOVED P9 9th PIN IS REMOVED P9 9th PIN IS REMOVED L1 12th PIN IS REMOVED L3 32th PIN IS REMOVED L5 18th PIN IS REMOVED L6 14th PIN IS REMOVED
D6 25th PIN IS REMOVED D7 26th PIN IS REMOVED D8 28th PIN IS REMOVED D9 15th PIN IS REMOVED E2 22th PIN IS REMOVED E3 30th PIN IS REMOVED E4 38th PIN IS REMOVED P0 4th PIN IS REMOVED P1 6th PIN IS REMOVED P3 7th PIN IS REMOVED P4 5th PIN IS REMOVED P5 10th PIN IS REMOVED P6 2nd PIN IS REMOVED P7 3rd PIN IS REMOVED P8 17th PIN IS REMOVED P9 9th PIN IS REMOVED P9 9th PIN IS REMOVED L1 12th PIN IS REMOVED L3 32th PIN IS REMOVED L5 18th PIN IS REMOVED L6 14th PIN IS REMOVED
D7 26th PIN IS REMOVED D8 28th PIN IS REMOVED D9 15th PIN IS REMOVED E2 22th PIN IS REMOVED E3 30th PIN IS REMOVED E4 38th PIN IS REMOVED P0 4th PIN IS REMOVED P1 6th PIN IS REMOVED P3 7th PIN IS REMOVED P4 5th PIN IS REMOVED P5 10th PIN IS REMOVED P6 2nd PIN IS REMOVED P7 3rd PIN IS REMOVED P8 17th PIN IS REMOVED P9 9th PIN IS REMOVED P9 9th PIN IS REMOVED L1 12th PIN IS REMOVED L3 32th PIN IS REMOVED L5 18th PIN IS REMOVED L6 14th PIN IS REMOVED
D8 28th PIN IS REMOVED D9 15th PIN IS REMOVED E2 22th PIN IS REMOVED E3 30th PIN IS REMOVED E4 38th PIN IS REMOVED P0 4th PIN IS REMOVED P1 6th PIN IS REMOVED P3 7th PIN IS REMOVED P4 5th PIN IS REMOVED P5 10th PIN IS REMOVED P6 2nd PIN IS REMOVED P7 3rd PIN IS REMOVED P8 17th PIN IS REMOVED P9 9th PIN IS REMOVED P9 9th PIN IS REMOVED L1 12th PIN IS REMOVED L3 32th PIN IS REMOVED L5 18th PIN IS REMOVED L6 14th PIN IS REMOVED
D9 15th PIN IS REMOVED E2 22th PIN IS REMOVED E3 30th PIN IS REMOVED E4 38th PIN IS REMOVED P0 4th PIN IS REMOVED P1 6th PIN IS REMOVED P3 7th PIN IS REMOVED P4 5th PIN IS REMOVED P5 10th PIN IS REMOVED P6 2nd PIN IS REMOVED P7 3rd PIN IS REMOVED P8 17th PIN IS REMOVED P9 9th PIN IS REMOVED L1 12th PIN IS REMOVED L3 32th PIN IS REMOVED L5 18th PIN IS REMOVED L6 14th PIN IS REMOVED
E2 22th PIN IS REMOVED E3 30th PIN IS REMOVED E4 38th PIN IS REMOVED P0 4th PIN IS REMOVED P1 6th PIN IS REMOVED P3 7th PIN IS REMOVED P4 5th PIN IS REMOVED P5 10th PIN IS REMOVED P6 2nd PIN IS REMOVED P7 3rd PIN IS REMOVED P8 17th PIN IS REMOVED P9 9th PIN IS REMOVED L1 12th PIN IS REMOVED L3 32th PIN IS REMOVED L5 18th PIN IS REMOVED L6 14th PIN IS REMOVED
E3 30th PIN IS REMOVED E4 38th PIN IS REMOVED P0 4th PIN IS REMOVED P1 6th PIN IS REMOVED P3 7th PIN IS REMOVED P4 5th PIN IS REMOVED P5 10th PIN IS REMOVED P6 2nd PIN IS REMOVED P7 3rd PIN IS REMOVED P8 17th PIN IS REMOVED P9 9th PIN IS REMOVED L1 12th PIN IS REMOVED L3 32th PIN IS REMOVED L5 18th PIN IS REMOVED L6 14th PIN IS REMOVED
E4 38th PIN IS REMOVED
P0 4th PIN IS REMOVED P1 6th PIN IS REMOVED P3 7th PIN IS REMOVED P4 5th PIN IS REMOVED P5 10th PIN IS REMOVED P6 2nd PIN IS REMOVED P7 3rd PIN IS REMOVED P8 17th PIN IS REMOVED P9 9th PIN IS REMOVED L1 12th PIN IS REMOVED L3 32th PIN IS REMOVED L5 18th PIN IS REMOVED L6 14th PIN IS REMOVED
P1 6th PIN IS REMOVED P3 7th PIN IS REMOVED P4 5th PIN IS REMOVED P5 10th PIN IS REMOVED P6 2nd PIN IS REMOVED P7 3rd PIN IS REMOVED P8 17th PIN IS REMOVED P9 9th PIN IS REMOVED L1 12th PIN IS REMOVED L3 32th PIN IS REMOVED L5 18th PIN IS REMOVED L6 14th PIN IS REMOVED
P3 7th PIN IS REMOVED P4 5th PIN IS REMOVED P5 10th PIN IS REMOVED P6 2nd PIN IS REMOVED P7 3rd PIN IS REMOVED P8 17th PIN IS REMOVED P9 9th PIN IS REMOVED L1 12th PIN IS REMOVED L3 32th PIN IS REMOVED L5 18th PIN IS REMOVED L6 14th PIN IS REMOVED
P4 5th PIN IS REMOVED P5 10th PIN IS REMOVED P6 2nd PIN IS REMOVED P7 3rd PIN IS REMOVED P8 17th PIN IS REMOVED P9 9th PIN IS REMOVED L1 12th PIN IS REMOVED L3 32th PIN IS REMOVED L5 18th PIN IS REMOVED L6 14th PIN IS REMOVED
P5 10th PIN IS REMOVED P6 2nd PIN IS REMOVED P7 3rd PIN IS REMOVED P8 17th PIN IS REMOVED P9 9th PIN IS REMOVED L1 12th PIN IS REMOVED L3 32th PIN IS REMOVED L5 18th PIN IS REMOVED L6 14th PIN IS REMOVED
P6 2nd PIN IS REMOVED P7 3rd PIN IS REMOVED P8 17th PIN IS REMOVED P9 9th PIN IS REMOVED L1 12th PIN IS REMOVED L3 32th PIN IS REMOVED L5 18th PIN IS REMOVED L6 14th PIN IS REMOVED
P7 3rd PIN IS REMOVED P8 17th PIN IS REMOVED P9 9th PIN IS REMOVED L1 12th PIN IS REMOVED L3 32th PIN IS REMOVED L5 18th PIN IS REMOVED L6 14th PIN IS REMOVED
P8 17th PIN IS REMOVED P9 9th PIN IS REMOVED L1 12th PIN IS REMOVED L3 32th PIN IS REMOVED L5 18th PIN IS REMOVED L6 14th PIN IS REMOVED
P9 9th PIN IS REMOVED L1 12th PIN IS REMOVED L3 32th PIN IS REMOVED L5 18th PIN IS REMOVED L6 14th PIN IS REMOVED
L1
L3 32th PIN IS REMOVED L5 18th PIN IS REMOVED L6 14th PIN IS REMOVED
L6 14th PIN IS REMOVED

L7 16th PIN IS REMOVED
L' TOUTT IN TO INCINIO VED
L8 1st&2nd&3rd&4th&14th&15th
&16th PIN IS REMOVED
L9 25th PIN IS REMOVED
T2 3rd,25th,26th PIN IS REMOVED
T3 8th & LAST PINS ARE REMOVED
T4 3rd,19th,20th&29th PINS ARE REMOVED
T5 8th & 9th PINS ARE REMOVED
T6 3rd & the last PINS ARE REMOVED
T7 8th & 19th PINS ARE REMOVED
T8 30th & 32th PINS ARE REMOVED
T9 25th,27th & 28th PINS ARE REMOVED
U0 3rd,5th,7th &9th PINS ARE REMOVED
U1 3rd & 5th PINS ARE REMOVED
U2 11th PIN IS REMOVED
U3 19th PIN IS REMOVED
U4 13th PIN IS REMOVED
U5 13th,15th &16th PIN IS REMOVED

CODE	DESCRIPTION			
NONE	STANDARD PRODUCT			
U6	4th & 7th PINS ARE REMOVED			
U7	8th & 13th PINS ARE REMOVED			
U8	4th 5th & 6th PINS ARE REMOVED			
U9	1st & 11 pins are removed.			

REMARK: (1) NONE: STANDARD PRODUCT

(X): TO BE SPECIFIED ON CORREL. CUSTOMER DWG

(2) NONE: STANDARD PRODUCT (COLOR BLACK)

K: THE FIRST & LAST PAIRS OF TERMINALS ARE DEFORMED WITH KINKS

W: HOUSING COLOR IVORY, PANTONE WARM GRAY 1C U: HOUSING COLOR BLUE, PANTONE2935C R: HOUSING COLOR RED, PANTONE 199C

G: HOUSING COLOR GREEN, PANTONE 346U

KW: THE FIRST & LAST PAIRS OF TERMINALS ARE DEFORMED WITH KINKS, HOUSING

K3: THE FIRST & LAST PAIRS OF TERMINALS
ARE DEFORMED WITH KINKS (SPECIAL MODIFICATION CODE)

(3) FOR REMOVED PIN(S) LOCATED AT FIRST OR LAST PAIR, KINK
POSITION(S) SHOULD BE CHANGED TO THE NEAREST PAIR

See The Attachment 1

111 7505* ****		71.12	68.58	60.96
HL3525*-***	50	[2.802]	[2.702]	[2.402]
		58.42	55.88	48.26
HL3520*-****	40	[2.302]		
HL3517*-***	34	50.80	48.26	40.64
		[2.002]	[1.901]	[1.601]
HL3515*-**** HL3513*-***	30 26	45.72	43.18	35.56
		[1.801]	[1.701]	[1.401]
		40.64	38.10	38.48
		[1.601]	[1.501]	[1.516]
HL3512*-***	24 20	38.10	35.56	27.94
		[1.501]	[1.401]	[1.101]
7540		33.02	30.48	22.86
HL3510*-****		[1.301]	[1.201]	[.901]
75054 4444	10	20.32	17.78	10.16
HL3505*-***		[.801]	[.701]	[.400]
P/N	POS.	DIM. A	DIM. B	DIM. C