



COAXIAL TERMINATIONS

TNC

6 to 12 WATTS MEDIUM POWER

Part Number	Power		Frequency range (GHz)	V.S.W.R. (MAX)					Imp. (Ω)	Type
	avg. (W)	peak (W)		DC-2	2-4	4-8	8-12.4	12.4-18		
R404506000	6	4000	DC-2	1.10					50 \pm 5%	M
R404511000	6	4000	DC-8	1.10	1.15	1.25			50 \pm 5%	M
R404516000	6	4000	DC-12.4	1.10		1.20	1.30		50 \pm 5%	M
R404521000	6	300	DC-18	1.15		1.20	1.25	1.30	50 \pm 5%	M
R404521500	6	300	DC-18	1.15		1.20	1.25	1.30	50 \pm 5%	F
R404556000	12	4000	DC-2	1.10					50 \pm 5%	M
R404561000	12	4000	DC-8	1.10	1.15	1.25			50 \pm 5%	M
R404566000	12	4000	DC-12.4	1.10		1.20	1.30		50 \pm 5%	M
R404571000	12	300	DC-18	1.15		1.20	1.25	1.30	50 \pm 5%	M
R404571500	12	300	DC-18	1.15		1.20	1.25	1.30	50 \pm 5%	F



Part Number	A inch (mm)	B inch (mm)	Weight (g)
R404506000	1.30" (33)	1.02" (26)	27
R404511000			
R404516000			
R404521000	1.85" (47)		45
R404521500	1.81" (46)		

Part Number	A inch (mm)	B inch (mm)	Weight (g)
R404556000	1.81" (46)	1.38" (35)	70
R404561000			
R404566000			
R404571000	2.04" (52)		75
R404571500	2.01" (51)		

20 WATTS MEDIUM POWER

Part Number	Power		Frequency range (GHz)	V.S.W.R. (MAX)				Impedance (Ω)	Type	Weight (g)
	avg. (W)	peak (W)		DC-4	4-8	8-12.4	12.4-18			
R404585000	20	300	DC-12.4	1.15	1.20	1.25		50 \pm 5%	M	85
R404585500	20	300	DC-12.4	1.15	1.20	1.25		50 \pm 5%	F	85
R404586000	20	300	DC-18		1.20	1.25	1.35	50 \pm 5%	M	85
R404586500	20	300	DC-18		1.20	1.25	1.35	50 \pm 5%	F	85

