



CMA806

AWS / BAS Interference Mitigation Filter

Revision 3 • February 1, 2012

Passband 1: 2030 – 2109.5 MHz
Insertion Loss: 2.20 dB max.
Return Loss: 15 dB min.

Passband 2: 2450 – 2500 MHz
Insertion Loss: 0.3 dB max.
Return Loss: 18.0 dB min.

Rejection: 60 dB min 2110.6 – 2121.5 MHz

Connectors: Type “N” Female
Operational Temp: +20°C to +40°C
Finish: Unpainted, Silver Finish

