

## SmartPro 1.5kVA Line Interactive Sine Wave UPS, SNMPWEBCARD option, Tower, USB, Serial, 100/110/120V

MODEL NUMBER: SMART1500SLT





#### **Highlights**

- 1.5kVA / 1500VA line interactive tower UPS; Sine wave output
- 100/110/120V output, Corrects brownouts and overvoltages
- USB, RS232 and slot for optional SNMP/Web card
- Detailed status LEDs, Single line TEL / DSL surge suppression
- NEMA 5-15P input, 8 5-15R outlets

### Package Includes

- SMART 1500SLT UPS System
- PowerAlert Software CD-Rom
- USB and serial cabling

#### Description

1500VA line-interactive tower UPS system for server, networking and telecommunications equipment. Upright tower form factor. Offers sine wave 100V, 110V or 120V nominal output in both AC and battery modes. Switches to battery-derived AC output during power failures and extreme voltage variations. Line-interactive automatic voltage regulation (AVR) provides voltage boost/cut during brownouts/overvoltages to maintain regulated 100V, 110V or 120V nominal output over an input voltage range of 95-145V. Includes NEMA 5-15P input plug and 8 UPS-supported NEMA 5-15R output receptacles. Network-grade AC surge and noise suppression. Network management interfaces support simultaneous communications via USB port, DB9 serial port and SNMPWEBCARD slot. HID-compliant USB interface enables integration with built-in power management and auto shutdown features of Windows and Mac OS X. Supports simultaneous detailed monitoring of equipment load levels, self-test data and utility power conditions via all 3 network interfaces. Includes PowerAlert monitoring software and complete cabling. Three-stage metered current monitoring and battery charge status LEDs. Data line surge suppression for dialup, DSL or network Ethernet connections. Utility power and voltage regulation LEDs. Audible alarm. Self-test. Field-replaceable, hot-swappable internal batteries. Attractive all-black color scheme.

#### **Features**

- SMART 1500SLT line-interactive UPS offers battery derived sine wave AC output during power outages, voltage regulation during brownouts and overvoltages, plus network-grade AC surge suppression
- 1500VA/900 watt power handling capability with full-time sine wave output offers guaranteed compatibility with networking, telecom and other sensitive electronic devices
- Large internal batteries offer runtimes of 17 minutes at half load (750VA/450 watts) and 6 minutes at full load (1500VA/900 watts)
- Automatic Voltage Regulation (AVR) circuits maintain user-selectable 100, 110, 120 or 127V nominal output over an input voltage range of 91 to 145V
- Includes 8 fully-protected NEMA 5-15R output receptacles arranged in a single load bank that can be powered off and back on again via software interface
- PowerAlert UPS monitoring and unattended shutdown software enables configurable network broadcast messaging, pager & email notification, event logging and running user-defined script commands
- Offers simultaneous monitoring by up to 3 directly-connected devices through included USB, DB9 and SNMP\* interfaces (\*requires optional SNMPWEBCARD), or the monitoring of any number of additional UPS systems over IP with included PowerAlert monitoring software.



- Communications ports support messaging of UPS and line power status, including on-battery, low-battery, power restored, AC line voltage, DC battery voltage and remaining battery capacity
- Supports timed inverter shutoff after unattended shutdown, activate self-test and UPS output power control for scheduled or immediate reboot of connected equipment
- Supports Tripp Lite's WatchDog software application to restore unresponsive programs by systematically restarting applications, operating systems and ultimately rebooting completely locked computers by momentarily switching UPS power off and back on again (requires optional WATCHDOGSW)
- . LEDs offer continuous detailed status information of UPS operating parameters and site power quality
- Hot-swappable batteries allow on-site battery replacement without powering off connected equipment

## **Specifications**

ОИТРИТ				
Output Volt Amp Capacity (VA)	1500			
Output kVA capacity (kVA)	1.5			
Output Watt Capacity (watts)	900			
Output power factor	0.6			
Nominal Output Voltage(s) Supported	100V; 110V; 120V			
Nominal Voltage details	120V default (voltage selection via back panel switches)			
Frequency compatibility	50 / 60 Hz			
Output voltage regulation (line mode)	-13%, + 15%			
Output voltage regulation (Battery mode)	+/- 5%			
Built-in UPS output receptacles	8 5-15R outlet(s)			
Output AC waveform (AC mode)	Sine wave			
Output AC waveform (battery mode)	Pure Sine wave			
INPUT				
Rated input current (at maximum load)	10.1A (100V), 9.3A (110V), 8.6A (120V)			
Nominal Input Voltage(s) Supported	100V AC; 110V AC; 120V AC			
UPS input connection type	5-15P			
UPS Input cord length (ft.)	6			
UPS Input cord length (m)	1.8			
Recommended Electrical Service	15A 120V			
Phase	Single-Phase			
BATTERY				
Full load runtime (minutes)	8 min. (900w)			
	2/6			





11.151 1 1 1 1 1	Inc. : 450			
Half load runtime (minutes)	20 min. (450w)			
DC system voltage (VDC)	36			
Battery recharge rate (included batteries)	Less than 8 hours from 10% to 90%			
Replacement battery cartridge (internal UPS battery replacement)	RBC36-SLT			
Battery Access	Battery access door			
Battery replacement description	Hot-swappable, user replaceable batteries			
VOLTAGE REGULATION				
Voltage regulation description	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 95 to 145 (120v), 87 to 133 (110v), 83 to 121 (100v)			
Overvoltage correction	Voltage reduction of 12% applies when input is 127 to 145 (120v), 116 to 133 (110v), 111 to 121 (100v)			
Undervoltage correction	Voltage boost of 14% applies when input is 95 to 108 (120v), 87 to 99 (110v), 83 to 90 (100v)			
LEDS ALARMS & SWITCHES				
LED Indicators	Status LEDs indicate line power, battery power, AVR, overload and replace battery status - with a 3-LED level meter for load and battery charge level			
Site wiring fault indication	Rear panel site wiring fault LED			
Alarms	Audible alarm indicates power failure and overload conditions			
Alarm cancel operation	Power-fail alarm can be silenced using alarm-cancel switch			
Switches	2 Switches control off/on power status and alarm-cancel/self-test operation; rear panel protected switches support nominal voltage selection			
SURGE / NOISE SUPPRESSION				
UPS AC suppression joule rating	690			
UPS AC suppression response time	Instantaneous			
UPS Dataline suppression	1 line TEL/DSL (1 in / 1 out); 10/100Base T Ethernet			
EMI / RFI AC noise suppression	Yes			
PHYSICAL				
Installation form factors supported with included accessories	Tower			
Primary form factor	Tower			
UPS / Power Module dimensions in primary form factor (height x width x depth / inches)	10.2 x 6.8 x 13.2			
UPS / Power Module dimensions in primary form factor (height x width x depth / cm)	26 x 17.1 x 33.7			
UPS / Power Module weight (lbs)	45			
	•			





UPS Shipping dimensions (height x width x depth / inches)  UPS Shipping dimensions (height x width x depth / inches)  UPS Shipping dimensions (height x width x depth / cm)  35.6 x 24.8 x 47  Shipping weight (lbs)  49.2  Shipping weight (kg)  22.3  Cooling method  UPS housing material  ENVIRONMENTAL  Operating Temperature Range  432 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius  Storage Temperature Range  45 to +122 degrees Fahrenheit / -15 to +50 degrees Celsius  Relative Humidity  0 to 95%, non-condensing  AC mode BTU / hr. (full load)  Battery mode BTU / hr. (full load)  498.1  AC mode efficiency rating (100% load)  Audible Noise  Audible Noise < 50 dBA at Front Side 1 Meter  Communications cable  USB and DB9 cabling included  WatchDog compatibility  Supports Watchdog application, OS and hard-reboot restart options for removed to the prover (setpoint)  4-6 milliseconds  LINE / BATTERY TRANSFER  Transfer time  4-6 milliseconds  5V (120V), 87V (110V), 83V (100V)  POWER (setpoint)  45V (120V), 133V (110V), 121V (100V)  SPECIAL FEATURES  Cold Start (slartup in battery mode during a power failure)  High availability UPS features  High availability UPS features	
width x depth / inches)  UPS Shipping dimensions (height x width x depth / cm)  Shipping weight (lbs)  Shipping weight (kg)  Cooling method  UPS housing material  ENVIRONMENTAL  Operating Temperature Range  +32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius  Storage Temperature Range  +5 to +122 degrees Fahrenheit / -15 to +50 degrees Celsius  Relative Humidity  O to 95%, non-condensing  AC mode BTU / hr. (full load)  Battery mode BTU / hr. (full load)  498.1  AC mode efficiency rating (100% load)  Audible Noise  Audible Noise  Audible Noise  Audible Noise  COMMUNICATIONS  Communications interface  USB; DB9 Serial; Slot for SNMP/Web interface  Network monitoring port description  Supports detailed monitoring of UPS and site power conditions  Included  Communications cable  WatchDog compatibility  Supports Watchdog application, OS and hard-reboot restart options for remover (setpoint)  LINE / BATTERY TRANSFER  Transfer time  4-6 milliseconds  USV (120V), 87V (110V), 83V (100V)  SPECIAL FEATURES  Cold Start (startup in battery mode during a power failure)  Coid-start operation supported	
Shipping weight (lbs) 49.2  Shipping weight (kg) 22.3  Cooling method Fan  UPS housing material Steel  ENVIRONMENTAL  Operating Temperature Range +32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius  Storage Temperature Range +5 to +122 degrees Fahrenheit / -16 to +50 degrees Celsius  Relative Humidity 0 to 95%, non-condensing  AC mode BTU / hr. (full load) 161.1  Bettery mode BTU / hr. (full load) 498.1  AC mode efficiency rating (100% load) 95%  Audible Noise Audible Noise <50 dBA at Front Side 1 Meter  COMMUNICATIONS  Communications interface USB; DB9 Serial; Slot for SNMP/Web interface  Network monitoring port description Supports detailed monitoring of UPS and site power conditions  PowerAlert software Included  Communications cable USB and DB9 cabling included  WatchDog compatibility Supports Watchdog application, OS and hard-reboot restart options for remote time  Line / BATTERY TRANSFER  Transfer time 4-6 milliseconds  Low voltage transfer to battery power (setpoint) 145V (120V), 133V (110V), 121V (100V)  SPECIAL FEATURES  Cold Start (startup in battery mode during a power failure) Cold-start operation supported	
Shipping weight (kg)  Cooling method  Fan  UPS housing material  Steel  ENVIRONMENTAL  Operating Temperature Range  +32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius  Storage Temperature Range  +5 to +122 degrees Fahrenheit / -15 to +50 degrees Celsius  Relative Humidity  0 to 95%, non-condensing  AC mode BTU / hr. (full load)  Battery mode BTU / hr. (full load)  498.1  AC mode efficiency rating (100% load)  Audible Noise  Audible Noise  Audible Noise <50 dBA at Front Side 1 Meter  COMMUNICATIONS  Communications interface  Network monitoring port description  Supports detailed monitoring of UPS and site power conditions  PowerAlert software  Included  Communications cable  WatchDog compatibility  Supports Watchdog application, OS and hard-reboot restart options for remove the power (setpoint)  LINE / BATTERY TRANSFER  Transfer time  4-6 milliseconds  Low voltage transfer to battery power (setpoint)  145V (120V), 87V (110V), 83V (100V)  SPECIAL FEATURES  Cold Start (startup in battery mode during a power failure)  Cold-start operation supported	
Cooling method Fan  UPS housing material Steel  ENVIRONMENTAL  Operating Temperature Range +32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius  Storage Temperature Range +5 to +122 degrees Fahrenheit / -15 to +50 degrees Celsius  Relative Humidity 0 to 95%, non-condensing  AC mode BTU / hr. (full load) 498.1  AC mode efficiency rating (100% load) 95%  Audible Noise Audible Noise <50 dBA at Front Side 1 Meter  COMMUNICATIONS  Communications interface USB; DB9 Serial; Slot for SNMP/Web interface  Network monitoring port description Supports detailed monitoring of UPS and site power conditions  PowerAlert software Included  Communications cable USB and DB9 cabling included  WatchDog compatibility Supports Watchdog application, OS and hard-reboot restart options for remove the company of	
UPS housing material  ENVIRONMENTAL  Operating Temperature Range	
ENVIRONMENTAL  Operating Temperature Range	
Operating Temperature Range +32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius  Storage Temperature Range +5 to +122 degrees Fahrenheit / -15 to +50 degrees Celsius  Relative Humidity 0 to 95%, non-condensing  AC mode BTU / hr. (full load) 161.1  Battery mode BTU / hr. (full load) 498.1  AC mode efficiency rating (100% 95% Audible Noise Audible Noise Audible Noise Audible Noise Audible Noise Audible Noise Sto dBA at Front Side 1 Meter  COMMUNICATIONS  Communications interface USB; DB9 Serial; Slot for SNMP/Web interface  Network monitoring port description Supports detailed monitoring of UPS and site power conditions  PowerAlert software Included  Communications cable USB and DB9 cabling included  WatchDog compatibility Supports Watchdog application, OS and hard-reboot restart options for remove the foliage transfer to battery power (selpoint) 95V (120V), 87V (110V), 83V (100V)  SPECIAL FEATURES  Cold Start (startup in battery mode during a power failure) Cold-start operation supported	
Storage Temperature Range	
Relative Humidity 0 to 95%, non-condensing  AC mode BTU / hr. (full load) 498.1  AC mode efficiency rating (100% 10ad) 95%  Audible Noise Audible Noise Audible Noise < 50 dBA at Front Side 1 Meter  COMMUNICATIONS  Communications interface USB; DB9 Serial; Slot for SNMP/Web interface  Network monitoring port description Supports detailed monitoring of UPS and site power conditions  PowerAlert software Included  Communications cable USB and DB9 cabling included  WatchDog compatibility Supports Watchdog application, OS and hard-reboot restart options for remove the power (setpoint) 95V (120V), 87V (110V), 83V (100V)  High voltage transfer to battery power (setpoint) 145V (120V), 133V (110V), 121V (100V)  SPECIAL FEATURES  Cold Start (startup in battery mode during a power failure) Cold-start operation supported	
AC mode BTU / hr. (full load)  Battery mode BTU / hr. (full load)  AC mode efficiency rating (100% load)  AC mode efficiency rating (100% load)  AC mode efficiency rating (100% load)  Audible Noise  Audible Noise  Audible Noise > 50 dBA at Front Side 1 Meter  COMMUNICATIONS  Communications interface  VSB; DB9 Serial; Slot for SNMP/Web interface  Network monitoring port description  PowerAlert software  Included  Communications cable  USB and DB9 cabling included  WatchDog compatibility  Supports Watchdog application, OS and hard-reboot restart options for removed the start options for removed to the start options for removed to the start option in the start	
Battery mode BTU / hr. (full load)  AC mode efficiency rating (100% load)  Audible Noise  Audible Noise  Audible Noise > 50 dBA at Front Side 1 Meter  COMMUNICATIONS  Communications interface  Network monitoring port description  PowerAlert software  Included  Communications cable  USB and DB9 cabling included  WatchDog compatibility  Supports Watchdog application, OS and hard-reboot restart options for remove the firm of the monitoring of UPS and site power conditions.  LINE / BATTERY TRANSFER  Transfer time  4-6 milliseconds  Low voltage transfer to battery power (setpoint)  High voltage transfer to battery power (setpoint)  High voltage transfer to battery power (setpoint)  PECIAL FEATURES  Cold Start (startup in battery mode during a power failure)  Cold-start operation supported	
AC mode efficiency rating (100% load)  Audible Noise  Audible Noise	
Audible Noise Audible Noise < 50 dBA at Front Side 1 Meter  COMMUNICATIONS  Communications interface USB; DB9 Serial; Slot for SNMP/Web interface  Network monitoring port description Supports detailed monitoring of UPS and site power conditions  PowerAlert software Included  Communications cable USB and DB9 cabling included  WatchDog compatibility Supports Watchdog application, OS and hard-reboot restart options for removed the following power (setpoint)  LINE / BATTERY TRANSFER  Transfer time 4-6 milliseconds  Low voltage transfer to battery power (setpoint) 95V (120V), 87V (110V), 83V (100V)  High voltage transfer to battery power (setpoint) 145V (120V), 133V (110V), 121V (100V)  SPECIAL FEATURES  Cold Start (startup in battery mode during a power failure) Cold-start operation supported	
COMMUNICATIONS  Communications interface USB; DB9 Serial; Slot for SNMP/Web interface  Network monitoring port description Supports detailed monitoring of UPS and site power conditions  PowerAlert software Included  Communications cable USB and DB9 cabling included  WatchDog compatibility Supports Watchdog application, OS and hard-reboot restart options for removed the following power (setpoint) Serial (120V), 87V (110V), 83V (100V)  High voltage transfer to battery power (setpoint) 145V (120V), 133V (110V), 121V (100V)  SPECIAL FEATURES  Cold Start (startup in battery mode during a power failure) Cold-start operation supported	
Communications interface  Network monitoring port description  PowerAlert software  Included  Communications cable  WatchDog compatibility  USB and DB9 cabling included  Supports Watchdog application, OS and hard-reboot restart options for remove the company of	
Network monitoring port description  Supports detailed monitoring of UPS and site power conditions  PowerAlert software  Included  Communications cable  USB and DB9 cabling included  WatchDog compatibility  Supports Watchdog application, OS and hard-reboot restart options for remove the company of the com	
PowerAlert software Included  Communications cable USB and DB9 cabling included  WatchDog compatibility Supports Watchdog application, OS and hard-reboot restart options for remove the company of the c	
Communications cable  WatchDog compatibility  Supports Watchdog application, OS and hard-reboot restart options for remove the company of the	
WatchDog compatibility  Supports Watchdog application, OS and hard-reboot restart options for remove the company of the compan	
LINE / BATTERY TRANSFER  Transfer time	
Transfer time  4-6 milliseconds  Low voltage transfer to battery power (setpoint)  High voltage transfer to battery power (setpoint)  145V (120V), 87V (110V), 83V (100V)  SPECIAL FEATURES  Cold Start (startup in battery mode during a power failure)  Cold-start operation supported	note applications
Low voltage transfer to battery power (setpoint)  High voltage transfer to battery power (setpoint)  145V (120V), 87V (110V), 83V (100V)  SPECIAL FEATURES  Cold Start (startup in battery mode during a power failure)  Cold-start operation supported	
Power (setpoint)  High voltage transfer to battery power (setpoint)  145V (120V), 133V (110V), 121V (100V)  SPECIAL FEATURES  Cold Start (startup in battery mode during a power failure)  Cold-start operation supported	
special Features  Cold Start (startup in battery mode during a power failure)  Cold-start operation supported	
Cold Start (startup in battery mode during a power failure)  Cold-start operation supported	
during a power failure)	
High availability LIPS features Hot swannable batteries	
Tight arangeming of a reaction and phase batteries	
Green & high efficiency features Greater than 95% efficiency - GREEN UPS	



CERTIFICATIONS				
UPS Certifications	Tested to UL1778 (USA); Tested to CSA (Canada); Tested to NOM (Mexico); Meets FCC Part 15 Category A (EMI)			
WARRANTY				
Product Warranty Period (Worldwide)	2-year warranty, 3 year with registration. Note: Registration is required for 3-year warranty.			
Connected Equipment Insurance (U.S., Canada & Puerto Rico)	\$250,000 Ultimate Lifetime Insurance			

## **Related Items**

## **Optional Products**

Model Number	Description	Qty.
SNMPWEBCARD	For remote monitoring and control via SNMP, Web, or Telnet.	1
ENVIROSENSE	Monitors temperature, humidity and contact-closure inputs. (Requires SNMPWEBCARD or switched PDU.)	1
MODBUSCARD	For remote monitoring and control via MODBUS protocol	1
WEXT5-500-1500	5-Year Extended Warranty - For Smart Line-Interactive and Online Tower or Rack models, 1500VA or less	1
RBC36-SLT	UPS Replacement Battery Cartridge for select Tripp Lite SLT UPS	1
WATCHDOGSW	WatchDog Service Monitoring / Reboot Software	1
PDUB15	Dual source Power Distribution Unit / PDU with Manual Transfer Switch enables Hot-swappable UPS Replacement in Critical Network Applications	1
PDU1215	Basic PDU / Power Distribution Unit - Safe, reliable power distribution for critical networking equipment	1
PDUNV	Basic PDU / Power Distribution Unit - Safe, reliable power distribution for critical networking equipment	1
PDUMH15	Metered PDU / Power Distribution Unit - Safe, reliable power distribution with digital current meter	1
PDUMH15AT	Metered PDU with ATS - Power Distribution Unit with dual-input Auto Transfer Switching	1
PDUMNH15	Monitored PDU / Power Distribution Unit supports real-time remote monitoring of load level, voltage and frequency with options for remote environmental and security monitoring	1
PDUMNV15	Monitored PDU / Power Distribution Unit supports real-time remote monitoring of load level, voltage and frequency with options for remote environmental and security monitoring	1
PDUMH15ATNET	Switched, Metered PDU with ATS - Power Distribution Unit with dual-input Auto Transfer Switching, individual outlet control and remote network interface	1
PDUMV15NET	Switched, Metered PDU with Remote Monitoring - 0U Vertical Rackmount Power Distribution Unit for Networks with Individually Switchable Outlets, Current Metering, Remote Monitoring and Control	1
P007-002	2-ft. Heavy-Duty 14AWG Power cord (IEC-320-C13 to NEMA 5-15P)	1
P007-006	6-ft. Heavy-Duty 14AWG Power cord (IEC-320-C13 to NEMA 5-15P)	1



# Tripp Lite 1111 W. 35th Street Chicago, IL 60609 USA Telephone: 773.869.1234 www.tripplite.com

P007-010	10-ft. Heavy-Duty 14AWG Power cord (IEC-320-C13 to NEMA 5-15P)	1
P010-012	12-ft. 18AWG Power cord (NEMA 5-15P to IEC-320-C13)	1
P022-001	1-ft. 18AWG Power Extension cord (NEMA 5-15R to NEMA 5-15P)	1
P023-001	1-ft. 14AWG Power Adapter cord (NEMA L5-15R to NEMA 5-15P)	1
P034-010	10-ft. 14AWG Heavy Duty Power cord ( IEC-320-C19 to NEMA 5-15P)	1
RELAYIOCARD	Programmable Relay I/O Card	1

More information, including related products, owner's manuals, and additional technical specifications, can be found online at: http://www.tripplite.com/sku/SMART1500SLT.

© 2014 Tripp Lite. All rights reserved. All trademarks are the sole property of their respective owners. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Photos may differ slightly from final products.

## **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Tripp Lite:

SMART1500SLT