

MN101C12D , MN101C12F , MN101C12G

Type	MN101C12D , MN101C12F , MN101C12G
ROM (×8-Bit)	64 K / 96 K / 128 K (External memory can be expanded)
RAM (×8-Bit)	2 048 / 4 096 / 4 096 (External memory can be expanded)
Minimum Instruction Execution Time	<p>Standard: 0.10 μs (at 4.5 V to 5.5 V, 20 MHz) 0.25 μs (at 2.7 V to 5.5 V, 8 MHz) 125 μs (at 2.0 V to 5.5 V, 32 kHz)*</p> <p>Double speed: 0.12 μs (at 4.5 V to 5.5 V, 8.38 MHz) 0.25 μs (at 3.0 V to 5.5 V, 4 MHz) 62.5 μs (at 2.0 V to 5.5 V, 32 kHz)*</p> <p>* The lower limit for operation guarantee for EPROM built-in version is 2.7 V.</p>
Interrupts	<ul style="list-style-type: none"> • RESET • Watchdog • External 0 • External 1 • External 2 • External 3 • External 4 • Timer 0 • Timer 1 • Timer 2 • Timer 3 • Timer 4 • Timer 6 • Time Base • Serial 3 • Serial 1 • Serial 2 • Automatic Transfer finish • A/D Conversion finish • External 5 • Timer 7 (2 systems) • Key Interrupts (8 lines)
Timer Counter	<p>Timer Counter 0 : 8-Bit × 1 (Square-Wave/8-Bit PWM Output, Event Count, Generation of Remote Control Carrier, Pulse Width Measurement)</p> <p>Clock Source 1/2, 1/4 of System Clock, 1/1, 1/4, 1/16, 1/32, 1/64 of OSC Oscillation Clock, 1/1 of XI Oscillation Clock, External Clock Input</p> <p>Interrupt Source Coincidence with Compare Register 0</p> <p>Timer Counter 1 : 8-Bit × 1 (Square-Wave Output, Event Count, Synchronous Output Event)</p> <p>Clock Source 1/2, 1/8 of System Clock, 1/1, 1/4, 1/16, 1/64, 1/128 of OSC Oscillation Clock, 1/1 of XI Oscillation Clock, External Clock Input</p> <p>Interrupt Source Coincidence with Compare Register 1</p> <p>Timer Counter 0, 1 can be cascade-connected.</p> <p>Timer Counter 2 : 8-Bit × 1 (Square-Wave/8-Bit PWM Output, Event Count, Synchronous Output Event, Pulse Width Measurement)</p> <p>Clock Source 1/2, 1/4 of System Clock, 1/1, 1/4, 1/16, 1/32, 1/64 of OSC Oscillation Clock, 1/1 of XI Oscillation Clock, External Clock Input</p> <p>Interrupt Source Coincidence with Compare Register 2</p> <p>Timer Counter 3 : 8-Bit × 1 (Square-Wave Output, Event Count, Generation of Remote Control Carrier)</p> <p>Clock Source 1/2, 1/8 of System Clock, 1/1, 1/4, 1/16, 1/64, 1/128 of OSC Oscillation Clock, 1/1 of XI Oscillation Clock, External Clock Input</p> <p>Interrupt Source Coincidence with Compare Register 3</p> <p>Timer Counter 2, 3 can be cascade-connected.</p> <p>Timer Counter 4 : 8-Bit × 1 (Square-Wave/8-Bit PWM Output, Event Count, Pulse Width Measurement, Serial 1 Baud Rate Timer)</p> <p>Clock Source 1/2, 1/4 of System Clock, 1/1, 1/4, 1/16, 1/32, 1/64 of OSC Oscillation Clock, 1/1 of XI Oscillation Clock, 1/1 of External Clock Input</p> <p>Interrupt Source Coincidence with Compare Register 4</p> <p>Timer Counter 6 : 8-Bit Freerun Timer</p> <p>Clock Source 1/1 of System Clock, 1/1, 1/4096, 1/8192 of OSC Oscillation Clock, 1/1, 1/4096, 1/8192 of XI Oscillation Clock</p> <p>Interrupt Source Coincidence with Compare Register 6</p>

Timer Counter (Continue)	Timer Counter 7 : 16-Bit × 1 (Square-Wave/16-Bit PWM Output, Cycle / Duty continuous variable, Event Count, Synchronous Output Event, Pulse Width Measurement, Input Capture)	
	Clock Source	1/1, 1/2, 1/4, 1/16 of System Clock, 1/1, 1/2, 1/4, 1/16 of OSC Oscillation Clock, 1/1, 1/2, 1/4, 1/16 of External Clock Input
	Interrupt Source	Coincidence with Compare Register 7 (2 lines)
	Time Base Timer (One-Minute Count Setting)	
	Clock Source	1/1 of OSC Oscillation Clock, 1/1 of XI Oscillation Clock
	Interrupt Source	1/128, 1/256, 1/512, 1/1024, 1/8192, 1/32768, of Clock Source
	Watchdog Timer	
	Interrupt Source	1/65536, 1/262144, 1/1048576 of System Clock
	DMA Controller (Automatic data transfer)	
	Max Transfer Cycles	255
Starting Factor	External Request, Various Types of Interrupt, Software	
Transfer Mode	1-Byte Transfer, Word Transfer, Burst Transfer	

Serial Interface	Serial 1 : 8-Bit × 1 (Synchronous Type/Simple UART[Half-Duplex])	
	Clock Source	1/2, 1/4 of System Clock Pulse Output of Timer Counter 4 1/2, 1/4, 1/16, 1/64 of OSC Oscillation Clock
	Serial 2 : 8-Bit × 1 (Synchronous Type)	
	Clock Source	1/2, 1/4 of System Clock Pulse Output of Timer Counter 3 1/2, 1/4, 1/16, 1/32 of OSC Oscillation Clock
	Serial 3 : 8-Bit × 1 (Synchronous Type/Simple I ² C)	
	Clock Source	1/2, 1/4 of System Clock Pulse Output of Timer Counter 3 1/2, 1/4, 1/16, 1/32 of OSC Oscillation Clock

I/O Pins	I/O	73	• Common use • Specified pull-up Resistor available • Input / Output selectable (bit unit)
	Input	15	• Common use • Specified pull-up Resistor available

A/D Inputs	10-Bit × 8ch (with S/H)
-------------------	-------------------------

D/A Inputs	8-Bit × 4ch
-------------------	-------------

Special Ports	Buzzer Output, Remote Control Carrier Signal Output, High-Current Drive Port
----------------------	--

Package	QFP100-P-1818B
----------------	----------------

Electrical Characteristics

Supply Current


Parameter	Symbol	Condition	Limit			Unit
			min	typ	max	
Operating Supply Current	IDD1	fosc = 20 MHz, VDD = 5 V			60	mA
	IDD2	fosc = 8 39 MHz, VDD = 5 V			25	mA
	IDD3	fx = 32 768 kHz, VDD = 3 V			100	μA
Supply Current at HALT	IDD4	fx = 32 kHz, VDD = 3 V			8	μA
	IDD5	fx = 32 768 kHz, VDD = 3 V, Ta = -40 °C to +85 °C			20	μA
Supply Current at STOP	IDD6	VDD = 5 V, Ta = 25 °C			1	μA
	IDD7	VDD = 5 V, Ta = -40 °C to +85 °C			30	μA

See the next page for support tool and pin assignment.

Support Tool

In-Circuit Emulator	PX-ICE101C / D + PX-PRB101C12-C / D	
EPROM built-in Type	Type	MN101CP12GAF
	ROM (× 8-Bit)	128 K
	RAM (× 8-Bit)	4 096
	Minimum Instruction Execution Time	Standard 0 10 μs (at 4 5 V to 5 5 V, 20 MHz) 0 25 μs (at 2 7 V to 5 5 V, 8 MHz) Double speed 0 12 μs (at 4 5 V to 5 5 V, 8 38 MHz) 0 25 μs (at 3 0 V to 5 5 V, 4 MHz)
	Package	QFP100-P-1818B

Pin Assignment



QFP100-P-1818B

Request for your special attention and precautions in using the technical information and semiconductors described in this book

- (1) If any of the products or technical information described in this book is to be exported or provided to non-residents, the laws and regulations of the exporting country, especially, those with regard to security export control, must be observed.
- (2) The technical information described in this book is intended only to show the main characteristics and application circuit examples of the products, and no license is granted under any intellectual property right or other right owned by our company or any other company. Therefore, no responsibility is assumed by our company as to the infringement upon any such right owned by any other company which may arise as a result of the use of technical information described in this book.
- (3) The products described in this book are intended to be used for standard applications or general electronic equipment (such as office equipment, communications equipment, measuring instruments and household appliances).
Consult our sales staff in advance for information on the following applications:
 - Special applications (such as for airplanes, aerospace, automobiles, traffic control equipment, combustion equipment, life support systems and safety devices) in which exceptional quality and reliability are required, or if the failure or malfunction of the products may directly jeopardize life or harm the human body.
 - Any applications other than the standard applications intended.
- (4) The products and product specifications described in this book are subject to change without notice for modification and/or improvement. At the final stage of your design, purchasing, or use of the products, therefore, ask for the most up-to-date Product Standards in advance to make sure that the latest specifications satisfy your requirements.
- (5) When designing your equipment, comply with the range of absolute maximum rating and the guaranteed operating conditions (operating power supply voltage and operating environment etc.). Especially, please be careful not to exceed the range of absolute maximum rating on the transient state, such as power-on, power-off and mode-switching. Otherwise, we will not be liable for any defect which may arise later in your equipment.
 - Even when the products are used within the guaranteed values, take into the consideration of incidence of break down and failure mode, possible to occur to semiconductor products. Measures on the systems such as redundant design, arresting the spread of fire or preventing glitch are recommended in order to prevent physical injury, fire, social damages, for example, by using the products.
- (6) Comply with the instructions for use in order to prevent breakdown and characteristics change due to external factors (ESD, EOS, thermal stress and mechanical stress) at the time of handling, mounting or at customer's process. When using products for which damp-proof packing is required, satisfy the conditions, such as shelf life and the elapsed time since first opening the packages.
- (7) This book may be not reprinted or reproduced whether wholly or partially, without the prior written permission of Matsushita Electric Industrial Co., Ltd.