

FS1000 Series Fast Switching Synthesizer



Supports hundreds of fast switching, high spectral purity applications.

Description:

The Aeroflex FastSource 1000 RF source represents a milestone in Synthesizer development and reflects years of design experience in Fast Switching Synthesis.

Designed specifically to meet the needs of today's Telecommunications industry, this high speed source offers a cost effective solution without sacrificing performance. The source covers a frequency range of 4.5 MHz to 6.0 GHz with a switching speed of 100 Microseconds. Spurious levels are greater than -65 dBc and Phase noise at 1.0 GHz is greater than -130 dBc/Hz at 10 KHz offset.

Specifications:

Frequency Range: 4.5 MHz to 6010 MHz

Step Size: 2 Hz - 2000 MHz
2 Hz - 2000 to 4000 MHz
4 Hz - 4000 to 6010 MHz

Power Output: +7 dBm

Flatness: ± 1.5 dB

Output Isolation:

25 dB minimum between ports
<5 microseconds switching time between ports

VSWR: 1.8:1

External Reference: 10 MHz, 3 dBm ± 4 dB, 50 Ω

Frequency Stability:

Same as Reference Oscillator

Reference Output:

10 MHz, +3 dBm ± 2 dB, 50 W

Features:

- <100 Microsecond switching
- Low phase noise -130 dBc/Hz
- 2 Hz resolution
- Low spurious
- Dual configuration available

Phase Noise of External Reference:

dBc/Hz	Offset
-130	100 Hz
-140	1 KHz
-143	10 KHz
-145	50 KHz

Switching Time:

<100 μ seconds to within 1.0 radian of final phase

Noise Floor:

10 MHz OFFSET	Frequency Range
-140 dBc/Hz	4.5 to 180 MHz
-145 dBz/Hz	180 to 1000 MHz
-147 dBc/Hz	1000 to 2000 MHz
-138 dBc/Hz	2000 to 4000 MHz
-134 dBc/Hz	4000 to 6010

Specifications (con't):

Output Phase Noise:

OFFSET	<250 MHz		.25 to <5 GHz		0.5 to <1.0 GHz		1.0 to <2.0 GHz		2.0 to <4.0 GHz		4.0 to <6.0 GHz	
	Typ.	Guar.	Typ.	Guar.	Typ.	Guar.	Typ.	Guar.	Typ.	Guar.	Typ.	Guar.
10 kHz	-125	-122	-135	-132	-131	-127	-125	-122	-119	-116	-113	-110
20 kHz	-127	-124	-137	-133	-133	-129	-127	-124	-121	-118	-115	-112
100 kHz	-128	-125	-138	-134	-134	-130	-128	-123	-122	-118	-116	-113

Harmonics

-25 dBc max. 4.5 to 6010 MHz

Sub Harmonics:

-60 dBc, Typical
-50 dBc Max except for components at FC noted below

@ FC=4.0 to 4.25, 5F/2 may be -45 dBc
@ Offsets $\leq \pm 2.8$ MHz from the carrier, spurs will be as follows:

FC < 180 MHz:	-60 dBc
180 MHz < FC < 1.0 GHz	-66 dBc
1.0 GHz < FC < 2.0 GHz	-60 dBc
2.0 GHz < FC < 4.0 GHz	-54 dBc
4.0 GHz < FC < 6.01 GHz	-48 dBc

For 1.0 GHz < FC < 2 GHz, fixed spurs at the following frequencies may be -60 dBc: 1175, 1225, 1275, 1325, 1375, 1425, 1475, 1525, 1575 and 1625 MHz

Spurious:

dBc (maximum)	Frequency Range
-65	4 to 2000 MHz
-60	2000 to 4000 MHz
-55	4000 to 6010MHz

For FC less than 180 MHz a spur may exist between 1609 Mz and 1960 MHz at -35 dBc: A fixed 800 MHz spur may exist at -60 dBc all carrier frequencies

Physical Dimensions:

Dimensions: 16.75" W X 5.22" H X 23.86" D

Residual FM:

Residual FM	Frequency Range
< 7	4 to 2000 MHz
< 16	2000 to 4000 MHz
< 32	4000 to 6010MHz

Frequency Control:

Parallel BCD positive or negative true with strobe. Strobe normally low, trigger on trailing edge

Output Fault: TTL level logic, "1" normal operation

Remote On/Off (RF): 0 MHz = Off
On/Off Ratio
<25 dBc

Logic Connector: 50 Pin receptacle, AMP 554216-3

Initialization: Unit will initialize with RF Off

Random Vibration: 10 Hz to 300 Hz @ 1.2 G RMS

Power: 105 to 125 VAC, 50-60 Hz

Temperature Range: +10° to +45 °C

CONFIGURATION

S = Single Synthesizer
D = Dual, Two independent synthesizers in a common chassis

FS1000 Series Fast Switching Synthesizer



Programming Input (BCD Connector)

SIGNAL	PIN	SIGNAL	PIN
Logic Ground	50	NC	25
400 MHz	49	Strobe	24
NC	48	NC	23
NC	47	NC	22
NC	46	Chassis Ground	21
Fault	45	8 MHz	20
200 MHz	44	4 MHz	19
100 MHz	43	2 MHz	18
NC	42	1 MHz	17
80 MHz	41	20 MHz	16
40 MHz	40	10 MHz	15
MUX	39	2 GHz	14
800 MHz	38	1 GHz	13
8 Hz	37	2 Hz	12
4 Hz	36	4 GHz	11
80 Hz	35	20 Hz	10
40 Hz	34	10 Hz	9
800 Hz	33	200 Hz	8
400 Hz	32	100 Hz	7
8 kHz	31	2 kHz	6
4 kHz	30	1 kHz	5
80 kHz	29	20 kHz	4
40 kHz	28	10 kHz	3
800 kHz	27	200 kHz	2
400 kHz	26	100 kHz	1

Note: Mating Connector is 3M P/N 3564-1001
(50 Pin Ribbon, Bail mount, Plug)

Aeroflex Signal & Control Solutions

Aeroflex Microelectronic Solutions
40 Industrial Way East
Eatontown, NJ 07724 [USA]
Fax: (732) 460-0214

35 South Service Rd
Plainview, NY 11803 [USA]
Fax: (516) 694-4823

ISO 9001:2008 certified

Sales
Phone: (732) 460-0212
ASCS-sales@aeroflex.com

www.aeroflex.com/Microwave www.aeroflex.com/ASCS

Aeroflex Control Componen. reserves the right to make changes to any products and services herein at any time without notice. Consult Aeroflex or an authorized sales representative to verify that the information in this data sheet is current before using this product. Aeroflex does not assume any responsibility or liability arising out of the application or use of any product or service described herein, except as expressly agreed to in writing by Aeroflex; nor does the purchase, lease, or use of a product or service from Aeroflex convey a license under any patent rights, copyrights, trademark rights, or any other of the intellectual rights of Aeroflex or of third parties.

Copyright 2013 Aeroflex Signal & Control Solutions. All rights reserved.



Our passion for performance is defined by three attributes represented by these three icons: solution-minded, performance-driven and customer-focused.