

# Series 804 Push-Pull Mighty Mouse Protective Plug Cover

## 809-198 Ordering Information



**Protect Connectors From Damage**  
Machined aluminum covers prevent ingress of contamination and water.

**Stainless Steel Fittings and Rings**  
Choose small diameter eye fittings for panel attachment. Larger rings fit under the jam nut or over cable jackets. Split rings can be installed on fully assembled cables.


**Polyurethane-Coated SST Wire Rope** offers high strength, excellent abrasion resistance and good flexibility. Or, choose Teflon® jacket for high temperature exposure.

**Braided Nylon Rope** provides excellent flexibility and good abrasion resistance, and can be ordered with slip knot fittings for easy installation on any size cable.

How To Order	
<b>Sample Part Number</b>	<b>809-198 M 9 H 6 -14 A</b>
<b>Series (See Table I)</b>	<b>809-198 = Receptacle Cover</b>
<b>Shell Material / Finish</b>	<p><b>C</b> = Aluminum / Black Anodize (Non-Conductive) RoHS Compliant</p> <p><b>M</b> = Aluminum / Electroless Nickel RoHS Compliant</p> <p><b>NF</b> = Aluminum / Cadmium with Olive Drab Chromate</p> <p><b>ZN</b> = Aluminum / Zinc-Nickel with Olive Drab Chromate</p> <p><b>ZNU</b> = Aluminum / Zinc-Nickel with Black Chromate</p> <p><b>MT</b> = Aluminum / Nickel-PTFE RoHS Compliant</p> <p><b>Z1</b> = Stainless Steel / Passivated RoHS Compliant</p>
<b>Shell Size</b>	<b>5, 6, 7, 8, 9, 10, 11, 12, 14, 15</b>
<b>Attachment Type</b>	<p><b>D</b> = Bead Chain, CRES, Passivate</p> <p><b>F</b> = Wire Rope, Nylon Jacket</p> <p><b>G</b> = Nylon Rope</p> <p><b>H</b> = SST Wire Rope, Teflon® Jacket</p> <p><b>N</b> = No Attachment</p> <p><b>R</b> = Wire Rope, PVC Jacket</p> <p><b>S</b> = SST Sash Chain</p> <p><b>SK</b> = Nylon Rope With Slip Knot</p> <p><b>T</b> = SST Wire Rope, No Jacket</p> <p><b>U</b> = SST Wire Rope, Polyurethane Jacket</p> <p>"SST" = Stainless Steel</p>
<b>Attachment Length (inches)</b>	Omit for attachment Type N (No Attachment) Example: "-6" equals six inch length
<b>Attachment Code (See Table II)</b>	<p>Small Ring = <b>01</b> thru <b>06</b></p> <p>Large Ring = <b>14</b> thru <b>33</b></p> <p>Split Ring = <b>50</b> thru <b>68</b></p>
<b>Alternate Key Position</b>	Omit for master keyway only, for all other positions indicate <b>A, B, C, D, E, or F</b>

Table I: Cover Style

<b>809-198</b> Push-Pull Plug Cover

Table II: Attachment Code	
Omit for attachment Type <b>N</b> (No Attachment) and <b>SK</b> (Slip Knot)	
 <b>Small Ring</b>	<p><b>-01</b> - .126 (3.20) I.D.</p> <p><b>-02</b> - .145 (3.68) I.D.</p> <p><b>-04</b> - .188 (4.78) I.D.</p> <p><b>-06</b> - .197 (5.00) I.D.</p>
 <b>Solid Ring</b>	<p><b>-32</b> - .265 (6.73)</p> <p><b>-29</b> - .315 (8.00)</p> <p><b>-14</b> - .385 (9.78)</p> <p><b>-33</b> - .510 (12.95)</p> <p><b>-15</b> - .445 (11.30)</p> <p><b>-16</b> - .570 (14.48)</p> <p><b>-17</b> - .635 (16.13)</p> <p><b>-18</b> - .695 (17.65)</p> <p><b>-27</b> - .766 (19.46)</p> <p><b>-26</b> - .950 (24.13)</p> <p><b>-31</b> - .820 (20.83)</p> <p><b>-28</b> - 1.015 (25.78)</p> <p><b>-20</b> - 1.070 (27.18)</p> <p><b>-21</b> - 1.135 (28.83)</p>
 <b>Split Ring</b>	<p><b>-50</b> - .420 (10.67) I.D.</p> <p><b>-52</b> - .480 (12.19) I.D.</p> <p><b>-54</b> - .635 (16.13) I.D.</p> <p><b>-56</b> - .745 (18.92) I.D.</p> <p><b>-58</b> - .885 (22.48) I.D.</p> <p><b>-60</b> - 1.010 (25.65) I.D.</p> <p><b>-64</b> - 1.125 (28.58) I.D.</p> <p><b>-68</b> - 1.345 (34.16) I.D.</p>

Dimensions in Inches (millimeters) are subject to change without notice.