

Audio Transformer

# PC Mount

## TY-146P

#### **Description:**

These transformers operate in the 200 Hz to 15,000 Hz range, making them suitable for a broad application spectrum in the audio industry. These devices are used in line matching, telephone coupling, pulse trigger, driver, interstage, output, isolation and input applications.

#### **Operating Temperature Range:** 0° C to 105° C

#### Electrical Specifications at 25° C:

1. Pi	rimary Impedance:	600Ω CT / 150§		
		+ 15% with 600Ω load		
2. S	econdary Impedance:	600Ω CT / 150§		
3. O	utput:	1W		
4. Pi	rimary DC Unbalance:	0 Ma		
5. Fr	requency Response:	+ 2db from 200 to 15,000 Hz		
	npedance Matching:	10% over full frequency range		
7. Lo	ongitudinal Balance	> 45db		
8. In	sertion Loss @ 1K Hz:	< 1.5db		
9. R	eturn Loss:	> 26db		
10. Total Harmonic Distortion		< 0.5% between 275Hz and3.5KHz		
11. DCR:				
	Primary (1-2)	17Ω Nominal		
	Primary (3-4)	19Ω Nominal		
	Secondary (5-6)	14.5Ω Nominal		
	Secondary (7-8)	22 $\Omega$ Nominal		
12. Tu	Irns Ratio:	1:1		
13. Di	electric Strength	1500V Pri to Sec to Core		
	-			


### Construction:

Bobbin has plug-in terminals which are spaced to provide fixed mounting centers. Pins are a rugged .042" square, minimizing the incidence of bent pins from handling.

## **Outline Dimensions:**

- A. Dimensions: As figures show B. PIN DIM. : .0375" x .020"
- C. Weight. : 3.0 oz.

## Schematic:



**RoHS Compliance:** As of manufacturing date February 2005, all standard products meet the requirements of 2011/65/EU, known as the RoHS initiative.

\*Upon printing, this document is considered "uncontrolled".Please contact Triad Magnetics' website for the most current version.

web:www.TriadN Phone 951-277- Fax 951-277-27	Perris, California		Publish Date: December 4, 2013
--	--------------------	--	--------------------------------



