

## Power Transformer Chassis Mount: Quick Pack

# FD7-16

### **Description:**

The FD7-16 Quick Pack small power transformer offers a significant reduction in size and weight over a standard transformer. This transformer can be used for a wide variety of applications. It is bobbin wound for reduced size and small operating space.

Electrical Specifications (@25C): Maximum Power: 56.0VA Input Voltage: Series: 230VAC@50/60Hz Parallel: 115VAC@50/60Hz Output Voltage: 16.0VCT@3.5A Hipot: 2500VAC primary to secondary; 1500VAC windings to core.

#### **Construction:**

Split bobbin non concentric winding eliminates costly electrostatic shielding. Termination is suitable for quick connects or soldering. Built with UL Class B Insulation System.

#### Safety:

UL: File E53148, UL 5085-1 and 2 (formerly UL 506), General Purpose.




#### **Dimensions:**

А	В	С	D	Е	F	G
2.250	3.125	3.687	1.812	2.687	.187 Dia	1.062

Notes: 1. Units: inches.

- 2. Terminal size: .187" X 0.021".
- 3. Weight: 1.70 lbs

#### Schematic:



Input (115V): Input 1 & 2 Connect 1&4, 2&5 Input (230V): Input 1 & 5 Connect 2&4

Output: 6 & 10

**RoHS Compliance:** As of manufacturing date February 2005, all standard products meet the requirements of 2011/65/EU, known as the RoHS initiative..

\* Upon printing, this document is considered "uncontrolled". Please contact Triad Magnetics' website for the most current version.

Web: www.TriadMagnetics.com Phone 951-277-0757 Fax 951-277-2757

460 Harley Knox Blvd. Perris, California 92571



