



AOS Semiconductor Reliability Report

AOTF42S60

600V 42A α MOSTM Power Transistor
Rev. A

ALPHA & OMEGA Semiconductor, Inc

www.aosmd.com



This report applies for 600V 42A α MOS™ Power Transistor AOTF42S60.

AOTF42S60 has been fabricated using the advanced α MOS™ high voltage process that is designed to deliver high levels of performance and robustness in switching applications. By providing low $R_{DS(on)}$, Q_g and E_{OSS} along with guaranteed avalanche capability these parts can be adopted quickly into new and existing offline power supply designs.

For Halogen Free add "L" suffix to part number:
AOTTF42S60L

“Commitment to Excellence at Quality & Reliability!”

To achieve this vision, AOS continuously strive for the excellence in design, manufacturing, reliability and proactively response to the customer’s feedback.

AOS ensures that all the product quality and reliability exceed the customer’s expectation by constantly assessing any potential risk, identifying cause of the suspected failures, driving corrective actions and developing prevention plan within the committed time through the continuously improvement.

This AOS product reliability report summarizes AOS Product Reliability result. The published product reliability data combines the results from new product Qualification Test Plan and routine Reliability Program activities. Accelerated environmental tests are performed on a specific sample size, and then followed by electrical test at end point. The released product will be categorized by the process family and be monitored on a quarterly basis for continuously improving the product quality. Table 1 lists the generic reliability qualification requirements and conditions:

Table 1: AOS Generic Reliability Qualification Requirements

Test Item	Test Condition	Time Point	Sample size	Acc/Reject
HTGB	Temp = 150°C , Vgs=100% of Vgsmax	168 / 500 hrs 1000 hrs	77 pcs / lot	0/1
HTRB	Temp = 150°C , Vds=80% of Vdsmax	168 / 500 hrs 1000 hrs	77 pcs / lot	0/1
Solder reflow precondition	168hr 85°C /85%RH + 3 cycle reflow @250°C (MSL level 1)	-	The sum of PCT ,TC and HAST	0/1
HAST	130 +/- 2°C , 85%RH, 33.3 psi, Vgs = 100% of Vgs max	100 hrs	55 pcs / lot	0/1
Pressure Pot	121°C , 29.7psi, 100%RH	96 hrs	77 pcs / lot	0/1
Temperature Cycle	-65°C to 150°C, air to air,	250 / 500 cycles	77 pcs / lot	0/1
Power Cycle	$\Delta T_j = 125 \text{ }^\circ\text{C}$	4286 cycles	77 pcs / lot	0/1

High Temperature Gate Bias (HTGB) & High Temperature Reverse Bias (HTRB)

HTGB burn-in stress is used to stress gate oxide at the elevated temperature environment hence any of the gate oxide integrity issue can be identified. HTRB burn-in stress is used to verify junction degradation under the maximum operation temperature.

Through HTGB & HTRB B/I stress test, the device lifetime in field operation & long term device level reliability can be determined. FIT rate is calculated by applying the Arrhenius equation with the activation energy of 0.7eV and 60% of upper confidence level at 55 deg C operating conditions.

Solder reflow precondition (pre-con)

Solder reflow precondition is the test that simulates shipment and storage of package in under uncontrollable environment. Precondition is the pre-requirement for the mechanical related reliability tests (such as Temperature Cycle, Pressure Pot and High Acceleration Stress TEST (HAST). The routine of the test are: parts will be soaked in moisture then bake in pressure pot, or being placed into 85% RH, 85 deg C environment for 168 hrs. Then they will be run through a solder reflow oven with temperature at 250°C± 5°C. The test condition totally complies with MSL level 1. Pre-condition is a test that is detected package delamination, lifted bond wire issue.

Temperature Cycling (TC)

Temperature cycling test is to evaluate the mechanical integrity of the package and the interaction between the die and the package. This is an air to air test at temperature range from -65°C/150°C and stress duration is from 250 cycles to 500 cycles.

Pressure Pot (PCT)

PCT test is the test that measures the ability of the device withstand to moisture and contaminant environment. The test is done under enclosed chamber with the condition 121°C 15± 1PSIG, 100%RH and stress duration is 96 hrs.

High Acceleration Stress Test (HAST)

High acceleration stress test is to stress the devices under high humidity, high pressure environment under DC bias condition. If ionic contamination involved, the corrosion from metal layer can be accelerated by the HAST stress condition.

Power Cycle

The power cycle test is performed to determine that the ability of a device to withstand alternate exposures at high and low junction temperature extremes with operating biases periodically applied and removed. It is intended to simulate worst case conditions encountered in typical application.

The following tables summarize the qualification results based on the device/process families and the package types, respectively.

Table 2 Reliability Test and Package test Result:

Test Item	Test Condition	Time Point	Total Sample size	Number of failure
HTGB	Temp = 150°C , Vgs=100% of Vgsmax	168 / 500 hrs 1000 hrs	308	0
HTRB	Temp = 150°C , Vds=80% of Vdsmax	168 / 500 hrs 1000 hrs	308	0
Solder reflow precondition	168hr 85°C /85%RH + 3 cycle reflow @250°C (MSL level 1)	-	627	0
HAST	130 +/- 2°C , 85%RH, 33.3 psi, Vgs = 100% of Vgs max	100 hrs	165	0
Pressure Pot	121°C , 29.7psi, 100%RH	96 hrs	231	0
Temperature Cycle	-65°C to 150°C, air to air,	250 / 500 cycles	231	0
Power Cycle	$\Delta T_j=125^\circ\text{C}$	4286 cycles	231	0

Reliability Evaluation:

FIT rate (per billion): 10

MTTF = 11579 years

The presentation of FIT rate for product reliability is restricted by the actual burn-in sample size of the selected product. Failure Rate Determination is based on JEDEC Standard JESD 85. FIT means one failure per billion hours.

$$\text{Failure Rate (FIT)} = \text{Chi}^2 \times 10^9 / [2 (N) (H) (Af)]$$

$$= 1.83 \times 10^9 / [2 (2 \times 2 \times 77 \times 168 + 2 \times 2 \times 77 \times 1000) \times (258)] = 10$$

$$\text{MTTF} = 10^9 / \text{FIT} = 1.01 \times 10^8 \text{hrs} = 11579 \text{ years}$$

Chi² = Chi Squared Distribution, determined by the number of failures and confidence interval

N = Total Number of units from HTRB and HTGB tests

H = Duration of HTRB/HTGB testing

Af = Acceleration Factor from Test to Use Conditions (Ea = 0.7eV and Tuse = 55°C)

Acceleration Factor [**Af**] = **Exp** [Ea / k (1/Tj u – 1/Tj s)]

Acceleration Factor ratio list:

	55 deg C	70 deg C	85 deg C	100 deg C	115 deg C	130 deg C	150 deg C
Af	258	87	32	13	5.64	2.59	1

Tj s = Stressed junction temperature in degree (Kelvin), K = C+273.16

Tj u = The use junction temperature in degree (Kelvin), K = C+273.16

k = Boltzmann's constant, 8.617164 X 10⁻⁵eV / K