# **Technical Data Sheet**

## **Top View LED With Lens(Preliminary)**

#### Features

- P-LCC-2 package.
- High flux output.
- High current capability.
- White package.
- Optical indicator.
- Colorless clear window.
- Ideal for backlight and light pipe application.
- Inter reflector.
- Suitable for automatic placement equipment.
- Suitable for reflow and wave solder processes.
- Available on tape and reel (12mm Tape).
- Pb-free.

#### Descriptions

The 67-21B series is available in soft orange, red and yellow. Due to the package design, the LED has optimized light coupling by inter reflector.

This feature makes the 67-21B series LED ideal for light pipe application. The low current requirement makes this device ideal for portable equipment or any other application where power is at a premium.


#### Applications

- Indicator and backlight for audio and video equipment.
- Indicator and backlight in office and family equipment.
- Flat backlight for LCD's, switches and symbols.
- Light pipe application.
- General use.

#### **Device Selection Guide**


Chip	Emitted Color	Resin Color	
Material	Emitted Color		
AlGaInP	Deep Red	Water Clear	

### 67-21BSDRC/S530-A6/TR8



# Technical Data Sheet Top View LED With Lens(Preliminary)

### **Package Dimensions**



**Note:** The tolerances unless mentioned is  $\pm 0.1$  mm ;Unit = mm

http://www.everlight.com prepared date:1-Jun-2007 67-21BSDRC/S530-A6/TR8

## **Technical Data Sheet Top View LED With Lens(Preliminary)**

### 67-21BSDRC/S530-A6/TR8

### Absolute Maximum Ratings (T<sub>a</sub>=25°C)

Parameter	Symbol	Rating	Unit
Reverse Voltage	V <sub>R</sub>	5	V
Forward Current	$I_{\rm F}$	25	mA
Peak Forward Current(Duty 1/10 @ 1KHz)	$I_{FP}$	60	mA
Power Dissipation	Pd	60	mW
Electrostatic Discharge	ESD	2000	V
Operating Temperature	Topr	-40 ~ +85	°C
Storage Temperature	Tstg	-40~ +90	°C
Soldering Temperature	Tsol	Reflow Soldering : 260 °C for 10 sec. Hand Soldering : 350 °C for 3 sec.	

### Electronic Optical Characteristics (T\_a=25°C) :

<b>L</b>	( u - )						
Parameter	Symbol	Min.	Тур.	Max.	Unit	Condition	
Luminous Intensity	Iv	170	240		mcd	I <sub>F</sub> =20mA	
Viewing Angle	201/2		60		deg	I <sub>F</sub> =20mA	
Peak Wavelength	λp		650		nm	I <sub>F</sub> =20mA	
Dominant Wavelength	λd	629.5		645.5	nm	I <sub>F</sub> =20mA	
Spectrum Radiation Bandwidth	$ riangle \lambda$		20		nm	I <sub>F</sub> =20mA	
Forward Voltage	$\mathbf{V}_{\mathrm{F}}$		2.0	2.4	V	I <sub>F</sub> =20mA	
Reverse Current	I <sub>R</sub>			10	μΑ	V <sub>R</sub> =5V	

#### Notes:

1. Tolerance of Luminous Intensity  $\pm 11\%$ 


2. Tolerance of Dominant Wavelength  $\pm 1$ nm


3. Tolerance of Forward Voltage  $\pm 0.1 V$ 

# Technical Data Sheet Top View LED With Lens(Preliminary)

### 67-21BSDRC/S530-A6/TR8

#### **Typical Electro-Optical Characteristics Curves**





Everlight Electronics Co., Ltd. Device No. :

http://www.everlight.com prepared date:1-Jun-2007 Rev. 1.0 Page: 4 of 9 Prepared by: Tracy

0.4

0.6

0. 2

0.1


0.5 0.3

# Technical Data Sheet Top View LED With Lens(Preliminary)


### 67-21BSDRC/S530-A6/TR8

#### Label explanation

- **CAT: Luminous Intensity Rank**
- HUE: Dom. Wavelength Rank
- **REF: Forward Voltage Rank**



#### **Reel Dimensions**




**Note:** The tolerances unless mentioned is  $\pm 0.1$  mm ,Unit = mm

# Technical Data Sheet Top View LED With Lens(Preliminary)


### 67-21BSDRC/S530-A6/TR8

### **Carrier Tape Dimensions: Loaded quantity 500 PCS per reel.**



**Note:** The tolerances unless mentioned is  $\pm 0.1$  mm Unit = mm

### **Moisture Resistant Packaging**



## **Technical Data Sheet**

## **Top View LED With Lens(Preliminary)**

## 67-21BSDRC/S530-A6/TR8

#### **Reliability Test Items And Conditions**

The reliability of products shall be satisfied with items listed below. Confidence level : 90% LTPD : 10%

No.	Items	Test Condition	Test Hours/Cycles	Sample Size	Ac/Re
1	Reflow Soldering	Temp. : 260°C±5°C Min. 5sec.	6 Min.	22 PCS.	0/1
2	Temperature Cycle	H : +100°C 15min ∫ 5 min L : -40°C 15min	300 Cycles	22 PCS.	0/1
3	Thermal Shock	H : +100°C 5min ∫ 10 sec L : -10°C 5min	300 Cycles	22 PCS.	0/1
4	High Temperature Storage	Temp. : 100°C	1000 Hrs.	22 PCS.	0/1
5	Low Temperature Storage	Temp. : -40°C	1000 Hrs.	22 PCS.	0/1
6	DC Operating Life	$I_F = 20 \text{ mA}$	1000 Hrs.	22 PCS.	0/1
7	High Temperature / High Humidity	85℃/ 85%RH	1000 Hrs.	22 PCS.	0/1

## **Technical Data Sheet**

## **Top View LED With Lens(Preliminary)**


## 67-21BSDRC/S530-A6/TR8

### **Precautions For Use**

1. Over-current-proof

Customer must apply resistors for protection, otherwise slight voltage shift will cause big current change ( Burn out will happen ).

- 2. Storage
  - 2.1 Do not open moisture proof bag before the products are ready to use.
  - 2.2 Before opening the package: The LEDs should be kept at  $30^{\circ}$ C or less and 90%RH or less.
  - 2.3 After opening the package: The LED's floor life is 1 year under 30°C or less and 60% RH or less. If unused LEDs remain, it should be stored in moisture proof packages.
  - 2.4 If the moisture absorbent material (silica gel) has faded away or the LEDs have exceeded the storage time, baking treatment should be performed using the following conditions.Baking treatment : 60±5°C for 24 hours.
- 3. Soldering Condition
- 3.1 Pb-free solder temperature profile



- 3.2 Reflow soldering should not be done more than two times.
- 3.3 When soldering, do not put stress on the LEDs during heating.
- 3.4 After soldering, do not warp the circuit board.

## Technical Data Sheet Top View LED With Lens(Preliminary)


#### 67-21BSDRC/S530-A6/TR8

4.Soldering Iron

Each terminal is to go to the tip of soldering iron temperature less than  $350^{\circ}$ C for 3 seconds within once in less than the soldering iron capacity 25W. Leave two seconds and more intervals, and do soldering of each terminal. Be careful because the damage of the product is often started at the time of the hand solder.

5.Repairing

Repair should not be done after the LEDs have been soldered. When repairing is unavoidable, a double-head soldering iron should be used (as below figure). It should be confirmed beforehand whether the characteristics of the LEDs will or will not be damaged by repairing.



**EVERLIGHT ELECTRONICS CO., LTD.** Office: No 25, Lane 76, Sec 3, Chung Yang Rd, Tucheng, Taipei 236, Taiwan, R.O.C *Tel:* 886-2-2267-2000, 2267-9936 *Fax:* 886-2267-6244, 2267-6189, 2267-6306 *http://www.everlight.com* 

Everlight Electronics Co., Ltd. Device No. :

http://www.everlight.com prepared date:1-Jun-2007 Rev. 1.0 Page: 9 of 9 Prepared by: Tracy