

# VR4111 (μPD30111) 64-Bit MIPS RISC Microprocessor

Product Brief September 1997

### **Description**


The 64-bit VR4111™(µPD30111) microprocessor is a member of NEC's VR Series™ devices created for Windows® CE-based embedded consumer applications. Designed around the popular MIPS® RISC architecture, the VR4111 offers excellent power consumption and performance in a high-integration, low-cost system on a chip.

This microprocessor is the first NEC device to use the VR4110™ CPU core, an ultra-low power consumption device based on advanced 0.25-micron technology. The VR4110 CPU has a 16K instruction cache, 8K data cache, multiply-and-accumulate (MAC) unit, memory management unit, and an optimized 100-MHz five-stage pipeline that deliver high performance in a compact, low-cost chip. Integrated peripherals include a power management unit, direct memory access unit, interrupt control unit, timers, real-time clock, serial interface, IrDA® interface, keyboard interface, touch-panel interface, LED interface, host signal processing unit (software modem), and A/D and D/A converters.

The VR4111 complies with MIPS I/II/III and MIPS16 instruction set architectures (ISAs). The MIPS16 ISA compliance enables the VR4111 to incorporate 16-bit instructions with conventional 32-bit instructions in a compact code size that reduces the memory requirement and thus system cost.

The VR4111 is an easy choice for VR4102™ customers in terms of upgrade because the VR4111 and VR4102 are fully pin compatible in the 224-pin FPBGA package. The VR4111 microprocessor's high speed, compact size, and low power consumption make it ideal for use in a battery-driven, portable handheld system.

## **Block Diagram**





#### **Features**

□ VR4110 CPU core MIPS I, II, III ISA-compliant (without FPU, LL, LLD, SC, and SCD instructions) MIPS16 ISA-compliant for compact code density Five-stage pipeline running at 100 MHz (130 Dhrystone MIPS) Single-cycle MAC instruction for DSP operations Memory management unit 32-bit physical addressing range of 4 GB with 40-bit virtual address space 32 double-entry TLBs supporting a 1K to 256K page size Up to 64 MB DRAM and 64 MB flash/mask ROM Cache memory unit 16K direct-mapped instruction cache 8K data cache Write-back cache for reducing store operations □ Bus control unit 32-bit and 16-bit addressing mode — Dynamic bus sizing (subset of ISA bus) Power management unit 180 mW at full-speed power (typical) 30 mW in standby mode 10 mW in suspend mode 240 mW in hibernate mode □ Clock generator unit Built-in phase-locked loop for frequency multiplication External bus frequency of 16/33 MHz 32-kHz and 18-MHz resonators Real-time clock with four built-in timers ☐ Interrupt control unit with internal and external interrupts DMA address unit and DMA control unit with four different DMA channels ☐ General-purpose I/O unit with 49 general-purpose I/O pins ☐ Keyboard (96-key), touch-panel, and LED interface ☐ Serial interface unit (16550 compliant) Up to 115 kbps Separate serial debugging port ☐ Fast infrared unit operating at 0.5 to 4 Mbps (IrDA 1.1 standard communication) ☐ Audio interface unit and 10-bit D/A converter with audio output and microphone input sampling ☐ Host signal processing unit (software modem) ☐ AC/DC specifications 100-MHz maximum frequency 2.5-V and 3.3-V operation 180 mW typical power consumption □ 224-pin FPBGA package



## VR4102 and VR4111 Comparison

	Vr4102	Vr4111
CPU	Vn4100	Vn4110
Pipeline clock	66 MHz	100 MHz
Performance	80 Dhrystone MIPS	130 Dhrystone MIPS
Cache size	Instruction: 4K Data: 1K	Instruction: 16K Data: 8K
Instruction set	MIPS I, II, III	MIPS I, II, III MIPS16
Operating voltage	3.3 volts	2.5 volts (core), 3.3 volts
Integrated peripherals	Same	Same
Memory interface	32 M DRAM 32 M ROM	64 M DRAM 64 M ROM
Power consumption	250 mW	180 m <b>W</b>
Package	216-pin LQFP 224-pin FPBGA	224-pin FPBGA
Process technology	0.35 micron	0.25 micron

## **Ordering Information**

Part Number	Package	Operating Frequency
μPD30111S1-100-3C	224-pin FPBGA	100 MHz
μPD30111S1-80-3C	224-pin FPBGA	80 MHz


VR Series, VR4100, VR4110, VR4111 and VR4102 are trademarks of NEC Corporation.

IrDA is a registered trademark of Infrared Data Association.

Windows and Windows CE are either registered trademarks or trademarks of Microsoft Corporation in the United States and/or other countries.

MIPS is a registered trademark of MIPS Group, a division of Silicon Graphics, Inc

### Handheld PC Application Example



NEC Electronics Inc.

2880 Scott Boulevard P.O. Box 58062 Santa Clara, CA 95052-8062 TEL 408-588-6000 For literature, call toll-free 7 a.m. to 6 p.m. Pacific time: 1-800-366-9782

or FAX your request to: 1-800-729-9288

No part of this document may be copied or reproduced in any form or by any means without the prior written consent of NEC Electronics Inc. (NECEL). The information in this document is subject to change without notice. ALL DEVICES SOLD BY NECEL ARE COVERED BY THE PROVISIONS APPEARING IN NECEL TERMS AND CONDITIONS OF SALES ONLY. INCLUDING THE LIMITATION OF LIABILITY, WARRANTY, AND PATENT PROVISIONS. NECEL makes no warranty, express, statutory, implied or by description, regarding information set forth herein or regarding the freedom of the described devices from patent infringement. NECEL assumes no responsibility for any errors that may appear in this document. NECEL makes no commitments to update or to keep current information contained in this document. The devices listed in this document are not suitable for use in applications such as, but not limited to, aircraft control systems, aerospace equipment, submarine cables, nuclear reactor control systems and life support systems. "Standard" quality grade devices are recommended for computers, office equipment, communication equipment, test and measurement equipment, machine tools, industrial robots, audio and visual equipment, and other consumer products. For automotive and transportation equipment, traffic control systems, anti-disaster and anti-crime systems, it is recommended that the customer contact the responsible NECEL salesperson to determine the reliability requirements for any such application and any cost adder. NECEL does not recommend or approve use of any of its products in life support devices or systems or in any application where failure could result in injury or death. It customers wish to use NECEL devices in applications not intended by NECEL, customer must contact the responsible NECEL salespeople to determine NECEL's willingness to support a given application.