

ML6415 DEMO

Demonstration board for the ML6415

Features

- 7.1MHz Y and C filters, with CV out
- 14dB notch at 4.5 MHz for sound trap
- 42dB stopband attenuation at 27 MHz on Y, C, and CV
- Better than 1dB flatness to 4.5MHz on Y, C, and CV
- Capable of driving 75 Ohm cable
- AC coupled inputs and outputs
- No external frequency select components or clocks
- 5% overshoot on Y, C, and CV output edges


Applications

- Cable Set-top Boxes
- Satellite Set-top Boxes
- DVD Players

Description

The ML6415 DEMO demonstration board provides a flexible base for evaluating the performance of the ML6415. The ML6415 is a dual Y/C 4th-order Butterworth lowpass video filter optimized for minimum overshoot and flat group delay. The device also contains a summing circuit to generate filtered composite video, an audio trap and group delay compensation circuit to notch-out audio, providing an area for the addition of the FM audio carrier(s) and mimic the group delay distortion introduced at the transmitter. For a complete description of the ML6415 including typical applications, please refer to the ML6415 data sheet. The ML6415 DEMO also has an option to connect YIN, CIN, YOUT, COUT, CVOUT, or RFOUT to 75 Ohm terminated to Ground (Jumpers labeled as JP1-6).

Block Diagram



ML6415 DEMO Schematic




Table 1. Bill of Materials

Item	Quantity	Reference	Part
1	4	C5, C6, C7, C51	0.1uF
2	4	C15,C16,C17,C18	220uF
3	1	C50	22uF /25v
4	1	C52	0.47uF /25v
5	1	C53	0.01uF
6	1	D1	1N4004 (Diode)
7	1	D2	GREEN LED
8	1	FB1	10 uH (Inductor)
9	4	G1,G2,G3,G4	GND LOOP
10	6	JP1,JP2,JP3,JP4,JP5,JP6	JUMPER
11	1	JP7	PWRCON3
12	6	J1, J2,J3,J4,J5,J6	BNC Connectors
13	10	R5, R6, R29, R30, R31,R32, R33, R34, R35, R36	75 Ohms
14	6	TP1,TP2,TP3,TP4,TP5,TP6	TP (Test Points)
15	1	U1	ML6415 (8-Pin SOIC)

LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF THE PRESIDENT OF FAIRCHILD SEMICONDUCTOR CORPORATION. As used herein:

1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury of the user.
2. A critical component in any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.