# Zener diode

## **VMZ6.8N**

#### Applications

Constant voltage control.


#### Features

- 1) Ultra small mold type. (VMD3)
- 2) Composite type with two anode common elements.
- 3) High reliability.

#### ●Construction

Silicon epitaxial planar.

#### ●External dimensions (Units : mm)




#### ● Absolute maximum ratings (Ta=25°C)

Parameter	Symbol	Limits	Unit
Power dissipation*	Р	150	mW
Junction temperature	Tj	150	°C
Storage temperature	Tstg	<b>−55~+150</b>	°C

<sup>\*</sup> Total of 2 elements

#### ●Equivalent circuit




#### ●Electrical characteristics (Ta=25°C)


Parameter	Symbol	Min.	Тур.	Max.	Unit	Conditions
Zener voltage	Vz	6.47	_	7.14	V	Iz=5mA
Reverse current	IR	_	_	0.5	μΑ	V <sub>R</sub> =3.5V
Capacitance between terminals	Ст	_	9	-	pF	f=1MHz, V <sub>R</sub> =5V

### ●Others

Parameter	IEC61000-4-2			
Davis	· Charge / discharge capacitance : 150pF			
Device configuration	· Discharge resistance	: 330 $\Omega$		
Judgment contents	· 10 repetitions			
	· No malfunction			
	· Contact	: ±8kV		
	·Suspended	: ±15kV		

#### ●Electrical characteristic curves (Ta=25°C)








Fig.1 Zener current characteristic

Fig.2 Reverse current characteristics

Fig.3 Capacitance between terminals characteristics




Fig.4 Reverse power disapation

#### **Notes**

- No technical content pages of this document may be reproduced in any form or transmitted by any
  means without prior permission of ROHM CO.,LTD.
- The contents described herein are subject to change without notice. The specifications for the
  product described in this document are for reference only. Upon actual use, therefore, please request
  that specifications to be separately delivered.
- Application circuit diagrams and circuit constants contained herein are shown as examples of standard
  use and operation. Please pay careful attention to the peripheral conditions when designing circuits
  and deciding upon circuit constants in the set.
- Any data, including, but not limited to application circuit diagrams information, described herein are intended only as illustrations of such devices and not as the specifications for such devices. ROHM CO.,LTD. disclaims any warranty that any use of such devices shall be free from infringement of any third party's intellectual property rights or other proprietary rights, and further, assumes no liability of whatsoever nature in the event of any such infringement, or arising from or connected with or related to the use of such devices.
- Upon the sale of any such devices, other than for buyer's right to use such devices itself, resell or
  otherwise dispose of the same, no express or implied right or license to practice or commercially
  exploit any intellectual property rights or other proprietary rights owned or controlled by
- ROHM CO., LTD. is granted to any such buyer.
- Products listed in this document use silicon as a basic material.
   Products listed in this document are no antiradiation design.

The products listed in this document are designed to be used with ordinary electronic equipment or devices (such as audio visual equipment, office-automation equipment, communications devices, electrical appliances and electronic toys).

Should you intend to use these products with equipment or devices which require an extremely high level of reliability and the malfunction of with would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), please be sure to consult with our sales representative in advance.

About Export Control Order in Japan

Products described herein are the objects of controlled goods in Annex 1 (Item 16) of Export Trade Control Order in Japan.

In case of export from Japan, please confirm if it applies to "objective" criteria or an "informed" (by MITI clause) on the basis of "catch all controls for Non-Proliferation of Weapons of Mass Destruction.

