


## FEATURES


- \* Built-in bias resistors enable the configuration of an inverter circuit without connecting input resistors (see equivalent circuit).
- \* Only the on/off conditions need to be set for operation, making device design easy.
- \* The bias resistors consist of thin-film resistors with complete isolation to allow negative biasing of the input. They also have the advantage of almost completely eliminating parasitic effects.

●Equivalent circuit



## PIN CONNECTIONS AND MARKING

### DTC143XE



SOT-523

Abbreviated symbol: 43


### DTC143XUA



SOT-323

Abbreviated symbol: 43


### DTC143XKA



SOT-23-3L

Abbreviated symbol: 43


### DTC143XCA



SOT-23

Abbreviated symbol: 43

### DTC143XSA



TO-92S

**Absolute maximum ratings (Ta=25°C)**

Parameter	Symbol	Limits (DTC143X)					Unit
		E	UA	CA	KA	SA	
Supply voltage	V <sub>CC</sub>	50					V
Input voltage	V <sub>IN</sub>	-7~+20					V
Output current	I <sub>O</sub>	100					mA
	I <sub>C(MAX)</sub>	100					
Power dissipation	P <sub>d</sub>	150		200		300	mW
Junction temperature	T <sub>j</sub>	150					°C
Storage temperature	T <sub>stg</sub>	-55~150					°C

**Electrical characteristics (Ta=25°C)**

Parameter	Symbol	Min.	Typ	Max.	Unit	Conditions
Input voltage	V <sub>I(off)</sub>			0.3	V	V <sub>CC</sub> =5V, I <sub>O</sub> =100μA
	V <sub>I(on)</sub>	2.5				V <sub>O</sub> =0.3V, I <sub>O</sub> =20 mA
Output voltage	V <sub>O(on)</sub>		0.1	0.3	V	I <sub>O</sub> /I <sub>I</sub> =10mA/0.5mA
Input current	I <sub>I</sub>			1.8	mA	V <sub>I</sub> =5V
Output current	I <sub>O(off)</sub>			0.5	μA	V <sub>CC</sub> =50V, V <sub>I</sub> =0
DC current gain	G <sub>I</sub>	30				V <sub>O</sub> =5V, I <sub>O</sub> =10mA
Input resistance	R <sub>1</sub>	3.29	4.7	6.11	KΩ	
Resistance ratio	R <sub>2</sub> /R <sub>1</sub>	1.7	2.1	2.6		
Transition frequency	f <sub>T</sub>		250		MHz	V <sub>O</sub> =10V, I <sub>O</sub> =5mA, f=100MHz

**Typical Characteristics**




Fig.1 Input voltage vs. output current (ON characteristics)




Fig.2 Output current vs. input voltage (OFF characteristics)




Fig.3 DC current gain vs. output current




Fig.4 Output voltage vs. output current