



APPLIED CONCEPTS INC.

397 Route 281 - P.O. BOX 453
Tully, New York 13159-0453
Phone: (315) 696-6676 Fax: (315) 696-9923
www.acipower.com

AC7-12-1396

PRODUCT DATA SHEET

03/05/03

CCFL INVERTER (For Dual Tube Applications)

The AC7-12-1396 is designed to drive 2 CCFL'S to a nominal current level of 6.0mA per tube.
The lamp outputs are open and short circuit protected.

Specifications:

- Vin = +12V +/- 10%
- CCFL strike voltage = 1450Vrms @ Vin=12V
- CCFL tube current = 6.0mA/tube @ 100% intensity/Vin=12V)
- Recommended CCFL sustaining voltage = 400Vrms - 800Vrms
- Nominal tube current frequency = 54khz +/- 10%
- Average electrical efficiency >88%

Additional control capability:*

- Enable/Disable function
- Simple button intensity control
- CDS ambient light sensor control
- Synchronization to display frame-rate capable
- Two-wire(variable resistance) intensity control
- Serial communication control

* Please contact factory for information

