CMOS 8-BIT MICROCONTROLLER

TMP87C447U, TMP87C847U, TMP87CH47U, TMP87C847LU, TMP87CH47LU

87C447/847/H47 are high speed and high performance 8-bit single chip microcomputers. These MCU contain CPU core, ROM, RAM, input/output ports, an A/D converter, six multi-function timer/counters, a serial interface, a high speed serial output, and two clock generators on a chip.

PART No.	ROM	RAM	PACKAGE	OTP MCU
TMP87C447U	4K × 8-bit			TMD07DLI47LL
TMP87C847U	8K×8-bit			TMP87PH47U
TMP87CH47U	16K × 8-bit	512 × 8-bit	QFP44-P-1010-0.80	
TMP87C847LU	8K x 8-bit			TM 4 D 0 7 D 1 4 7 1 1 1
TMP87CH47LU	16K × 8-bit			TMP87PH47LU

FEATURES

- ◆8-bit single chip microcomputer TLCS-870 Series
- lacktriangle Instruction execution time : 0.5 μ s (at 8 MHz), 122 μ s (at 32.768 kHz)
- ◆412 basic instructions
 - Multiplication and Division (8bits × 8bits, 16bits ÷ 8bits)
 - Bit manipulations (Set/Clear/Complement/Move/Test/Exclusive or)
 - 16-bit data operations
 - 1-byte jump/subroutine-call (Short relative jump / Vector call)
- ◆14 interrupt sources (External: 6, Internal: 8)
 - All sources have independent latches each, and nested interrupt control is available.
 - 4 edge-selectable external interrupts with noise reject
 - High-speed task switching by register bank changeover
- ◆Input/Output ports (37 pins)
 - I/O 5ports 35pinsOutput 1port 2pins
 - Output 1port
 High current output
 - LED direct drive capability (typ. 20 mA x 8bits)
- ◆Two 16-bit Timer/Counters
 - Timer, Event counter, Programmable pulse generator output,
 Pulse width measurement, External trigger timer, Window modes
- ◆Two 8-bit Timer/Counters
 - Timer, Event counter, Capture (Pulse width/duty measurement), PWM output, Programmable divider output modes
- ◆Time Base Timer (Interrupt frequency : 1 Hz to 16 kHz)
- ◆Divider output function (frequency: 1 kHz to 8 kHz)
- **♦**Watchdog Timer
- ◆8-bit Serial Interface
 - With 8 bytes transmit/receive data buffer
 - Internal/external serial clock, and 4/8-bit mode
- **lack 8-bit** High Speed Serial Output (rate: max. 1bit/ μ s)
- ◆8-bit successive approximate type A/D converter with sample and hold
 - 8 analog inputs
 - Conversion time: 23 μ s/92 μ s at 8MHz programmable selectable
- ◆ Dual clock operation
- ◆ Five Power saving operating modes
 - STOP mode : Oscillation stops. Battery/Capacitor back-up. Port output hold/high-impedance.
 - SLOW mode: Low power consumption operation using low-frequency clock (32.768kHz).
 - IDLE1 mode: CPU stops, and Peripherals operate using high-frequency clock. Release by interrupts.
 - IDLE2 mode: CPU stops, and Peripherals operate using high and low frequency clock. Release by interrupts.
- SLEEP mode: CPU stops, and Peripherals operate using low-frequency clock. Release by integrupt seet 4U.com

 Wide operating voltage: 2.7 to 5.5 V at 4.2 MHz/32.768 kHz, 4.5 to 5.5 V at 8 MHz/32.768 kHz
- (TMP87C447/847/H47) ♦ Low voltage operation available : 1.8 to 4.0 V at 4.2 MHz/32.768 kHz (TMP87C847L/H47L)
- ◆Emulation Pod4i CBM87CH47U0A

