

TABLE 2 : PNP GENERAL PURPOSE

The devices shown in this table are general purpose transistors designed for small signal amplification from d.c. to radio frequencies. Typical application areas include: AUDIO FREQUENCY AMPLIFIERS, DRIVERS and OUTPUT STAGES, OSCILLATORS, AND GENERAL PURPOSE SWITCHES.

Type	V _{CB0} V	V _{CEO} V	Max I _C mA	Max V _{CE(sat)} at			h _{FE} at			Min f _T at		P _{tot} at T _{amb} = 25°C mW	Complement
				V	I _C mA	I _B mA	Min	Max	I _C mA	MHz	I _C mA		
BC556P	80	65	200	0.25	10	0.5	75	450	2	150*	10	500	BC546P
ZTX504	70	70	500	0.6	50	5	50	300	10	150	10	300	ZTX304
ZTX212	60	50	200	0.25	10	0.5	60	400	2	200	10	500	ZTX107
BC212P	60	50	200	0.6	100	5	60	400	2	200	10	300	BC182P
BC557P	50	45	200	0.25	10	0.5	75	450	2	150*	10	500	BC547P
BC177P	50	45	200	0.2	10	0.5	120	460	2	130	10	300	BC107P
BC307P	50	45	200	0.2	10	0.5	120	460	2	130*	10	300	BC237P
ZTX503	45	45	500	0.35	50	5	50	300	10	150	10	300	ZTX303
ZTX531	45	45	500	0.7	10	0.5	40	120	0.01	30	0.5	250	ZTX331
ZTX213	45	30	200	0.25	10	0.5	80	550	2	200	10	500	ZTX108
BC213P	45	30	200	0.6	100	5	80	600	2	200	10	300	BC183P
ZTX502	35	35	500	0.25	50	5	100	300	10	150	10	300	ZTX302
ZTX501	35	35	500	0.25	50	5	50	300	10	150	10	300	ZTX301
ZTX530	30	30	500	0.7	10	0.5	100	400	0.1	30	0.5	250	ZTX330
BC558P	30	30	200	0.25	10	0.5	75	800	2	150*	10	500	BC548P
BC178P	30	25	200	0.2	10	0.5	120	800	2	130	10	300	BC108P
BC308P	30	25	200	0.2	10	0.5	120	800	2	130*	10	300	BC238P
ZTX500	25	25	500	0.35	50	5	50	300	10	150	10	300	ZTX300

*Typical