## **Timers Star Delta** Types DAC01, PAC01







- Time range (Star): 0.1 to 600 s
- Time range (Star to Delta): 50 to 130 ms
- . Knob selection of star time range
- Knob adjustable time setting
- Automatic start
- Repeatability: ≤ 0.2%
- Output: 8 A SPDT relay with neutral centre position
- For mounting on DIN-rail in accordance with DIN/EN
- 22.5 mm Euronorm housing or 36 mm Plug-in module housing
- LED indication for relay status and power supply ON

#### **Product Description**

Star-delta control relay with two adjustable time ranges: Star function (0.1 to 600 s) and star to delta function (50 to 130 ms). For mounting on DIN-rail (DAC 01) on Plug-in (PAC01).

#### Ordering key **DAC 01 C M24** Housing **Function** Type Item number -Output -**Power Supply**

#### **Type Selection**

Mounting	Output	Housing	Supply: 24 to 240 VAC/DC	Supply: 380 to 415 VAC
For DIN-rail	1 x SPDT	D - 22.5 mm	DAC 01 C M24	DAC 01 C M40
Plug-in		P - Housing	PAC 01 C M24	PAC 01 C M40

Time Specifications		
Time ranges (star) Knob selectable	0.1 to 1 s 1 to 10 s 6 to 60 s 60 to 600s 50 to 130 ms between star and delta position	
Star to delta delay Neutral centre position		
Setting accuracy	≤ 5%	
Repeatability	≤ 0.2%	
<b>Time variation</b> Within rated power supply Within ambient temperature	≤ 0.05% ≤ 0.2%	
Reset Time and relay	Power supply interruption ≥ 200 ms	

## **Output Specifications**

Output	SPDT relay with neutral centre position	
Rated insulation voltage	250 VAC (RMS)	
Contact Ratings (AgSnO <sub>2</sub> )	μ	
Resistive loads AC 1	8 A @ 250 VAC	
DC 12 Small inductive loads AC 15 DC 13	5 A @ 24 VDC 2.5 A@ 250 VAC 2.5 A@ 24 VDC	
Mechanical life	≥ 30 x 10 <sup>6</sup> operations	
Electrical life	$\geq$ 10 <sup>5</sup> operations (at 8 A, 250 V, cos $\varphi$ = 1)	
Operating frequency	< 7200 operations/h	
Dielectric strength Dielectric voltage Rated impulse withstand	2 kVAC (RMS)	
voltage	4 kV (1.2/50µs)	



## **Supply Specifications**

Power supply Rated operational voltage through terminals: A1 and A2 (DAC01) 2, 10 (PAC01)		Overvoltage cat. III (IEC 60664, IEC 60038)
_,	M24	24 to 240 VAC/DC
		+10% -15%, 45 to 65 Hz
	M40:	380 to 415 VAC
		+10% -15%, 45 to 65 Hz
Voltage inter	ruption	≤ 10 ms
Rated opera	tional power	
M24	AC Supply:	4 VA
	DC Supply:	1.5 W
M40	AC Supply:	13 VA @ 400 VAC, 50 Hz

#### **Time Setting**

Upper knob:

Setting of star time range

Centre knob:

Star time setting on relative

scale: 1 to 10 with respect to the chosen range.

Lower knob:

Star to delta time setting (50 to 130 ms)

#### **General Specifications**

<del>John Speamannin</del>				
Power ON delay	≤ 100 ms			
Power OFF delay	≤ 100 ms			
Indication for				
Power supply ON	LED, green			
Output relays ON	LED, yellow (flashing when timing)			
Environment	(EN 60529)			
Degree of protection	IP 20			
Pollution degree	3 (DAC01) ,2 (PAC01) (IEC 60664)			
Operating temperature	-20 to 60 °C, R.H. < 95%			
Storage temperature	-30 to 80 °C, R.H. < 95%			
Housing dimensions				
DIN-rail version	22.5 x 80 x 99.5 mm			
Plug-in version	36 x 80 x 94 mm			
Weight	Approx 110 g			
Screw terminals	DAC01			
Tightening torque	Max 0.5 Nm according to IEC EN 60947			
Approvals	UL, CSA			
CE Marking	Yes			
EMC	Electromagnetic Compatibility			
Immunity	According to EN 61000-6-2			
Emission	According to EN 61000-6-3			
Timer Specifications	According to EN 61812-1			

## **Mode of Operation**

The output relay is normally in the neutral centre position. When the power supply is applied, the relay switches to star position (pin 16 or 4) and the star period starts.


At the end of the set time period, the relay returns to the neutral centre position and the set delay between star and delta position starts. At the end of the star to delta delay (adjustable from


50 to 130 ms), the relay switches in delta position (pin 18 or 3) and does not release until the power supply is interrupted for at least 200 ms.

If the power supply is inter-

rupted for more than 200 ms before the star time period has expired, the relay does not operate and the time circuit is set to zero. The relay is ready for a new time period.


## **Wiring Diagrams**







# **Operation Diagram**



## **Dimensions**

