


# MOS FIELD EFFECT POWER TRANSISTORS 2SK2133, 2SK2133-Z

# SWITCHING N-CHANNEL POWER MOS FET INDUSTRIAL USE



#### DESCRIPTION

The 2SK2133, 2SK2133-Z are N-channel Power MOS Field Effect Transistors designed for high voltage switching applications.

## **FEATURES**

- Low On-state Resistance RDS(on) = 0.21  $\Omega$  MAX. (Vgs = 10 V, ID = 8.0 A)
- Low Ciss Ciss = 1090 pF TYP.
- High Avalanche Capability Ratings

#### QUALITY GRADE

Standard

Please refer to "Quality grade on NEC Semiconductor Devices" (Document number IEI-1209) published by NEC Corporation to know the specification of quality grade on the devices and its recommended applications.

#### **ABSOLUTE MAXIMUM RATINGS**

	Maximum	Temperatures								
	Storage 1	Temperature	-55 to +150	°C						
	Channel	Temperature	150	°C MAX						
	Maximum	Power Dissipation								
	Total Pov	wer Dissipation (T <sub>A</sub> = 25 °C)	1.5	W						
	Total Pov	wer Dissipation (Tc = 25 °C)	75	W						
Maximum Voltages and Currents (T <sub>A</sub> = 25 °C)										
	Voss	Drain to Source Voltage	250	V						
	Vgss	Gate to Source Voltage	±30	V						
	ID(DS)	Drain Current (DC)	±16	Α						
	ID(pulse)*	Drain Current (pulse)	±64	Α						
	Maximum .	Avalanche Capability Rating	s**							
	las	Single Avalanche Current	16	Α						
	Eas	Single Avalanche Energy	320	mJ						

<sup>\*</sup> PW  $\leq$  10  $\mu$ s, Duty Cycle  $\leq$  1%

<sup>\*\*</sup> Starting T<sub>ch</sub> = 25 °C, R<sub>G</sub> = 25  $\Omega$ , V<sub>GS</sub> = 20 V  $\rightarrow$  0




## **ELECTRICAL CHARACTERISTICS (TA = 25 °C)**


CHARACTERISTIC	SYMBOL	MIN.	TYP.	MAX.	UNIT	TEST CONDITIONS	
Drian to Source On-state Resistance	Ros (on)		0.21	0.26	Ω	Vgs = 10 V, Ip = 8.0 A	
Gate to Source Cutoff Voltage	V gs (off)	2.0		4.0	V	V <sub>DS</sub> = 10 V, I <sub>D</sub> = 1 mA	
Forward Transfer Admittance	Y fs	4.0			S	Vos = 10 V, lo = 8.0 A	
Drain Leakage Current	Ipss			100	μΑ	Vps = 250 V, Vgs = 0	
Gate to Source Leakage Current	Igss			±10	μΑ	V gs = ±30 V, V ps = 0	
Input Capacitance	Ciss		1 090		pF	V <sub>DS</sub> = 10 V V <sub>GS</sub> = 0	
Output Capacitance	Coss		420		pF		
Reverse Transfer Capacitance	Crss		80		рF	f = 1 MHz	
Turn-On Delay Time	ta (on)		20		ns	$V_{GS} = 10 \text{ V}$ $V_{DD} = 150 \text{ V}$ $I_{D} = 8.0 \text{ A, Rg} = 10 \Omega$ $R_{L} = 18.75 \Omega$	
Rise Time	tr		40		ns		
Turn-Off Delay Time	ta (off)		60		ns		
Fall Time	tr		20		ns		
Total Gate Charge	QG		25		nC	V gs = 10 V	
Gate to Source Charge	QGS		8.0		nC	Ip = 16 A	
Gate to Drain Charge	Q <sub>GD</sub>		14		nC	VDD = 200 V	
Diode Forward Voltage	V F(S-D)		1.0		٧	IF = 16 A, Vgs = 0	
Reverse Recovery Time	trr		400		ns	IF = 16 A	
Reverse Recovery Charge	Qrr		2.0		μC	$di/dt = 50 A/\mu s$	

## **Test Circuit 1: Avalanche Capability**


**Test Circuit 2: Switching Time** 




**Test Circuit 3: Gate Charge** 




## TYPICAL CHARACTERISTICS (TA = 25 °C)







## FORWARD BIAS SAFE OPERATING AREA




### TRANSFER CHARACTERISTICS












### TRANSIENT THERMAL RESISTANCE vs. PULSE WIDTH




FORWARD TRANSFER ADMITTANCE vs DRAIN CURRENT




DRAIN TO SOURCE ON-STATE RESISTANCE vs.




DRAIN TO SOURCE ON-STATE RESISTANCE vs. GATE TO SOURCE VOLTAGE




GATE TO SOURCE CUTOFF VOLTAGE vs. CHANNEL TEMPERATURE







## SOURCE TO DRAIN DIODE FORWARD VOLTAGE









SWITCHING CHARACTERISTICS




DYNAMIC INPUT/ OUTPUT CHARACTERISTICS




REVERSE RECOVERY TIME vs. REVERSE DRAIN CURRENT



## SINGLE AVALANCHE CURRENT vs. INDUCTIVE LOAD



## SINGLE AVALANCHE ENERGY vs. STARTING CHENNEL TEMPERATURE





[MEMO]

[MEMO]

No part of this document may be copied or reproduced in any form or by any means without the prior written consent of NEC Corporation. NEC Corporation assumes no responsibility for any errors which may appear in this document.

NEC Corporation does not assume any liability for infringement of patents, copyrights or other intellectual property rights of third parties by or arising from use of a device described herein or any other liability arising from use of such device. No license, either express, implied or otherwise, is granted under any patents, copyrights or other intellectual property rights of NEC Corporation or others.

While NEC Corporation has been making continuous effort to enhance the reliability of its semiconductor devices, the possibility of defects cannot be eliminated entirely. To minimize risks of damage or injury to persons or property arising from a defect in an NEC semiconductor device, customers must incorporate sufficient safety measures in its design, such as redundancy, fire-containment, and anti-failure features.

NEC devices are classified into the following three quality grades:

"Standard", "Special", and "Specific". The Specific quality grade applies only to devices developed based on a customer designated "quality assurance program" for a specific application. The recommended applications of a device depend on its quality grade, as indicated below. Customers must check the quality grade of each device before using it in a particular application.

Standard: Computers, office equipment, communications equipment, test and measurement equipment, audio and visual equipment, home electronic appliances, machine tools, personal electronic equipment and industrial robots

Special: Transportation equipment (automobiles, trains, ships, etc.), traffic control systems, anti-disaster systems, anti-crime systems, safety equipment and medical equipment (not specifically designed for life support)

Specific: Aircrafts, aerospace equipment, submersible repeaters, nuclear reactor control systems, life support systems or medical equipment for life support, etc.

The quality grade of NEC devices is "Standard" unless otherwise specified in NEC's Data Sheets or Data Books. If customers intend to use NEC devices for applications other than those specified for Standard quality grade, they should contact an NEC sales representative in advance.

Anti-radioactive design is not implemented in this product.