



SD103AW - SD103CW

SCHOTTKY BARRIER SWITCHING DIODE

Features

- Low Forward Voltage Drop
- Guard Ring Construction for Transient Protection
- Negligible Reverse Recovery Time
- Very Low Reverse Capacitance
- Lead Free/RoHS Compliant (Note 3)


Mechanical Data

- Case: SOD-123
- Case Material: Molded Plastic. UL Flammability Classification Rating 94V-0
- Moisture Sensitivity: Level 1 per J-STD-020C
- Leads: Solderable per MIL-STD-202, Method
- Lead Free Plating (Matte Tin Finish annealed over Alloy 42 leadframe)
- Polarity: Cathode Band
- Marking: Date Code and Type Code, See Page 3

Type Codes: SD103AW SD103BW S5 or S4

S6 or S5 or S4 SD103CW

Ordering Information: See Page 3 Weight: 0.01 grams (approximate)



SOD-123									
Dim	Min	Max							
Α	3.55	3.85							
В	2.55	2.85							
С	1.40	1.70							
D		1.35							
Е	0.45	0.65							
	0.55 Typical								
G	0.25	I							
н	0.11 T	ypical							
J	_	0.10							
α	0°	8°							
All Dimensions in mm									

Maximum Ratings @T_A = 25°C unless otherwise specified

Characteristic	Symbol	SD103AW	SD103BW	SD103CW	Unit
Peak Repetitive Reverse Voltage	V_{RRM}				
Working Peak Reverse Voltage	V_{RWM}	40	30	20	V
DC Blocking Voltage	V_R				
RMS Reverse Voltage	$V_{R(RMS)}$	28	21	14	V
Forward Continuous Current (Note 1)	I _{FM}		mA		
Non-Repetitive Peak Forward Surge Current @ t ≤ 1.0s	I _{FSM}		Α		
Power Dissipation (Note 1)	P _d		mW		
Thermal Resistance, Junction to Ambient Air (Note 1)	$R_{\theta JA}$		°C/W		
Operating and Storage Temperature Range	T_i, T_{STG}		°C		

Electrical Characteristics @T_A = 25°C unless otherwise specified


Characteristic		Symbol	Min	Тур	Max	Unit	Test Condition
Reverse Breakdown Voltage (Note 2)	SD103AW SD103BW SD103CW	$V_{(BR)R}$	40 30 20	ı	_	V	$I_R = 100 \mu A$
Forward Voltage Drop		V_{FM}	_		0.37 0.60	V	$I_F = 20mA$ $I_F = 200mA$
Peak Reverse Current (Note 2)	SD103AW SD103BW SD103CW	I _{RM}	_		5.0	μА	$egin{array}{l} V_R = 30V \\ V_R = 20V \\ V_R = 10V \\ \hline \end{array}$
Total Capacitance		C _T	_	28	_	pF	$V_R = 0V$, $f = 1.0MHz$
Reverse Recovery Time		t _{rr}	_	10	_	ns	$I_F = I_R = 200 \text{mA},$ $I_{rr} = 0.1 \text{ x } I_R, R_L = 100 \Omega$


Part mounted on FR-4 board with recommended pad layout, which can be found on our website at http://www.diodes.com/datasheets/ap02001.pdf.


Short duration test pulse used to minimize self-heating effect.

No purposefully added lead.










V_F, INSTANTANEOUS FORWARD VOLTAGE (mV) Fig. 2 Typical Forward Characteristics



 $\label{eq:VR} {\rm V_R,\,REVERSE\,\,VOLTAGE\,\,(V)}$ Fig. 4 Typ. Total Capacitance vs. Reverse Voltage




Ordering Information (Note 4)

Device	Packaging	Shipping
SD103AW-7-F	SOD-123	3000/Tape and Reel
SD103BW-7-F	SOD-123	3000/Tape and Reel
SD103CW-7-F	SOD-123	3000/Tape and Reel

4. For Packaging Details, go to our website at http://www.diodes.com/datasheets/ap02007.pdf.

Marking Information



Date Code Key

Year	1998	1999	2000	2001	2002	2003	2004	2005	2006	2007	2008	2009	2010	2011	2012
Code	J	K	L	М	N	Р	R	S	Т	U	V	W	X	Υ	Z
N	Month		Jan	Feb	Mar	Apr	May	Jun	Ju	Αι	ıg	Sep	Oct	Nov	Dec
	Code		1	2	3	4	5	6	7	8	3	9	0	Ν	D

IMPORTANT NOTICE

Diodes Incorporated and its subsidiaries reserve the right to make modifications, enhancements, improvements, corrections or other changes without further notice to any product herein. Diodes Incorporated does not assume any liability arising out of the application or use of any product described herein; neither does it convey any license under its patent rights, nor the rights of others. The user of products in such applications shall assume all risks of such use and will agree to hold Diodes Incorporated and all the companies whose products are represented on our website, harmless against all damages.

LIFE SUPPORT

Diodes Incorporated products are not authorized for use as critical components in life support devices or systems without the expressed written approval of the President of Diodes Incorporated.