

Distributor: Electro-Stock www.electrostock.com Tel: 630-682-1542 Fax: 630-682-1562

#### **FEATURES:**

- Switching capacity up to 20A
- Small size and light weight
- Dual relay available
- Low coil power consumption
- Suitable for automobile and consumer electronics applications





17.8 x 9.6(17.0) x 13.2mm

# **CONTACT DATA**

Contact Arrangement	1A = SPST N.O.
_	1C = SPDT
	2A = (2) SPST N.O.
	2C = (2) SPDT
Contact Rating	20A @ 14VDC N.O.
	15A @ 14VDC N.C.
Contact Resistance	< 50 milliohms initial
Contact Material	AgSnO <sub>2</sub>
Maximum Switching Power	280W
Maximum Switching Voltage	40VDC
Maximum Switching Current	20A

## **COIL DATA**

$ \begin{array}{c c} \text{Coil Voltage} & \text{Coil Resistance} \\ \text{VDC} & \Omega \pm 10\% \\ \end{array} $		Pick Up Voltage VDC (max)	Release Voltage VDC (min)	Coil Power W	Operate Time ms	Release Time ms		
		75%	10%					
Rated	Max.	0.6W	0.8W	of rated voltage	of rated voltage			
12	18	240	180	9.00	1.2	0.60 or 0.80	8	5

### **CAUTION:**

- 1. The use of any coil voltage less than the rated coil voltage may compromise the operation of the relay.
- 2. Pickup and release voltages are for test purposes only and are not to be used as design criteria.

## **GENERAL DATA**

Electrical Life @ rated load	100K cycles, typical
Mechanical Life	10M cycles, typical
Insulation Resistance	100MΩ min @ 500VDC
Dielectric Strength, Coil to Contact	500V rms min. @ sea level
Contact to Contact	500V rms min. @ sea level
Shock Resistance	300m/s <sup>2</sup> for 11ms
Vibration Resistance	1.50mm double amplitude 10-40Hz
Terminal (Copper Alloy) Strength	5N
Operating Temperature	-40 °C to + 85 °C
Storage Temperature	-40 °C to + 155 °C
Solderability	230 °C ± 2 °C for 10 ± 0.5s
Weight	5g, 10g



Distributor: Electro-Stock www.electrostock.com Tel: 630-682-1542 Fax: 630-682-1562

## ORDERING INFORMATION

1. Series:	CTA11	2C	S	12VDC	.80
CTA11					
2.Contact Arrangement: 1A = SPST N.O. 1C = SPDT 2A = (2) SPST N.O. 2C = (2) SPDT					
3. Sealing Options: S = Sealed C = Dust Cover					
5. Coil Voltage: 12VDC					
<b>6. Coil Power:</b> .60 = 0.60W .80 = 0.80W					

# **DIMENSIONS (Units = mm)**



