



Single Junction Gull Wing Circulator 902 MHz—928 MHz


MAFRIN0461 Version 2

Features

- Designed for RFID market
- · 22dB Isolation typical
- 0.25dB Insertion Loss
- Low cost package

Description

This circulator is designed specifically for RFID applications and features high reliability performance at a low cost. It is in a low cost package ideally suited for high volume manufacturing. M/A Com is one of the largest suppliers of isolator and circulators in the world.



Electrical Specifications $T_A = +25$ °C, $Z_0 = 50$ Ohms

Parameter	Test Conditions	Units	Min	Тур	Max
Frequency Range	Over T _{op} ¹	MHz	902		928
Insertion Loss	902 MHz—928 MHz, over T _{op} ¹	dB		0.21	0.30
Isolation	902 MHz—928 MHz, over T _{op} ¹	dB	22.0	29.0	
Return Loss	902 MHz—928 MHz, all ports, over T _{op} ¹	dB	21.0	28.0	
Circulation	Over T _{op} ¹			CW	

^{1.} See "Absolute Maximum Ratings" for Top.

Absolute Maximum Ratings

information.

Parameter	Absolute Maximum
Forward Power	100 Watts
Operating Temperature	-10°C to +85°C
Storage Temperature	-40°C to +100°C

^{1.} Operation of this device above any one of these parameters may cause permanent damage.

M/A-COM Inc. and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice. M/A-COM makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does M/A-COM assume any liability whatsoever arising out of the use or application of any product(s) or

[•] North America Tel: 800.366.2266 / Fax: 978.366.2266

[•] Europe Tel: 44.1908.574.200 / Fax: 44.1908.574.300

Asia/Pacific Tel: 81.44.844.8296 / Fax: 81.44.844.8298





Single Junction Gull Wing Circulator 902 MHz—928 MHz

MAFRIN0461 Version 2

Ordering Information

Part Number	Packaging
MAFRIN0461	Tray


Environmental Specifications

Devices are designed to function after exposure to the shock, vibration, thermal shock and moisture conditions typically encountered in base station and other infrastructure environments.


S-Parameters

S-parameters are available on the M/A Com website at: S-Parameters


Insertion Loss (S21)




Isolation (S12)



Return Loss (S11)



Return Loss (S22)



- North America Tel: 800.366.2266 / Fax: 978.366.2266
- Europe Tel: 44.1908.574.200 / Fax: 44.1908.574.300
- Asia/Pacific Tel: 81.44.844.8296 / Fax: 81.44.844.8298

²






Single Junction Gull Wing Circulator 902 MHz—928 MHz


MAFRIN0461 Version 2

Recommended PCB Layout



- 1. Dimensions in mm.
- 2. Tolerances: ± 0.2 mm unless otherwise noted.
- 3. Use multiple plated thru holes in ground area under the housing.

Outline Drawing



- 1. Dimensions in mm.
- 2. Tolerances: ± 0.3 mm unless otherwise noted.
- 3. Housing: Cold Rolled Steel with SnPb 90/10 plating.
- 4. Cover: CRS with SnPb 90/10 plating.
- 5. Leads: Copper.

- Europe Tel: 44.1908.574.200 / Fax: 44.1908.574.300
- Asia/Pacific Tel: 81.44.844.8296 / Fax: 81.44.844.8298