High Brightness Type ϕ 5.0 Circular Type LED Lamps (Focus Type 2 θ 1/2:12°)

SLI-580 Series

Shape	Emitting Surface Dimension (mm)	Yellow	Orange	Red		
			AIGaInP on GaAs			
		591nm	611nm	630nm		
Circular Type	¢ 5.0					
		SLI-580YT	SLI-580DT	SLI-580UT		

■ Absolute Maximum Ratings (Ta=25°C)


Part No.	Emitting color	Power dissipation Po (mW)	Forward current IF (mA)	Peak forward current IFP (mA)	Reverse voltage VR (V)	Operating temperature Topr (°C)	Stotage temperature Tstg (°C)
SLI-580YT	Yellow						
SLI-580DT	Orange	125	50	200	9	-30 to +85	-40 to +100
SLI-580UT	Red						

* IFP measured under duty $\leq 1/10,1$ kHz


Electrical Optical Characteristics (Ta=25°C)

Part No.	Resin Color	Forward voltage V⊧		Reverse current In		Light wavelength Peak Half-wave λp Δλ			Brightness Iv		
		Тур. (V)	lF (mA)	Max. (μΑ)	Vr (V)	Typ. (nm)	Typ. (nm)	lF (mA)	Min. (mcd)	Typ. (mcd)	lF (mA)
SLI-580YT	Transparent Clear					591	15		1350		
SLI-580DT		1.9	20	100	9	611	17	20	1350	5000	20
SLI-580UT						630	20		2000		


External Dimensions (Unit : mm)




Directivity




Recommemded Pad Layout






Electrical Characteristic Curves

Forward Current - Forward Voltage




SLI-580YT SLI-580DT SLI-580UT

Relative Luminous Intensity - Case Temperature




Relative Luminous Intensity - Forward Current




- SLI-580YT SLI-580DT SLI-580UT

Ratio of Maximum Tolerable Peak Current - Pulse Duration



- SLI-580YT SLI-580DT SLI-580UT

Derating



Notes

- No technical content pages of this document may be reproduced in any form or transmitted by any means without prior permission of ROHM CO.,LTD.
- The contents described herein are subject to change without notice. The specifications for the product described in this document are for reference only. Upon actual use, therefore, please request that specifications to be separately delivered.
- Application circuit diagrams and circuit constants contained herein are shown as examples of standard use and operation. Please pay careful attention to the peripheral conditions when designing circuits and deciding upon circuit constants in the set.
- Any data, including, but not limited to application circuit diagrams information, described herein are intended only as illustrations of such devices and not as the specifications for such devices. ROHM CO.,LTD. disclaims any warranty that any use of such devices shall be free from infringement of any third party's intellectual property rights or other proprietary rights, and further, assumes no liability of whatsoever nature in the event of any such infringement, or arising from or connected with or related to the use of such devices.
- Upon the sale of any such devices, other than for buyer's right to use such devices itself, resell or otherwise dispose of the same, no express or implied right or license to practice or commercially exploit any intellectual property rights or other proprietary rights owned or controlled by
- ROHM CO., LTD. is granted to any such buyer.
- Products listed in this document are no antiradiation design.

The products listed in this document are designed to be used with ordinary electronic equipment or devices (such as audio visual equipment, office-automation equipment, communications devices, electrical appliances and electronic toys).

Should you intend to use these products with equipment or devices which require an extremely high level of reliability and the malfunction of with would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), please be sure to consult with our sales representative in advance.

About Export Control Order in Japan

Products described herein are the objects of controlled goods in Annex 1 (Item 16) of Export Trade Control Order in Japan.

In case of export from Japan, please confirm if it applies to "objective" criteria or an "informed" (by MITI clause) on the basis of "catch all controls for Non-Proliferation of Weapons of Mass Destruction.

ROHM