


Tel : +44 118 979 1238 Fax : +44 118 979 1283 Email: <u>info@actcrystals.com</u>

The ACTR4105/303.825/QCC8C is a true one-port, surface-acoustic-wave (SAW) resonator in a surface-mount ceramic QCC8C case. It provides reliable, fundamental-mode, quartz frequency stabilization i.e. in transmitters or local oscillators operating at 303.825 MHz.


### 1.Package Dimension (QCC8C)



Pin	Configuration		
2	Input / Output		
6	Input / Output		
4,8	Case Ground		
1,3,5,7	NC		


Sign	Data (unit: mm)	Sign	Data (unit: mm)		
А	2.08	ш	1.2		
В	0.6	F	1.35		
С	1.27	G	5.0		
D	2.54	Н	5.0		

## 3.Equivalent LC Model and Test Circuit




# **4.Typical Application Circuits**

1) Low-Power Transmitter Application



2) Local Oscillator Application




In keeping with our ongoing policy of product evolvement and improvement, the above specification is subject to change without notice.

ISO9001: 2000 Registered - Registration number 6830/2 For quotations or further information please contact us at: 3 The Business Centre, Molly Millars Lane, Wokingham, Berks, RG41 2EY, UK http://www.actcrystals.com

Issue : 1 C1 Date : SEPT 04



### 6.Temperature Characteristics



#### 

The curve shown above accounts for resonator contribution only and does not include oscillator temperature characteristics.

### 7.Performance

7-1.Maximum Ratings						
Rating	Value	Units				
CW RF Power Dissipation	0	dBm				
DC Voltage Between Terminals	±30V	VDC				
Case Temperature	-40 to +85	°C				
Soldering Temperature	+250	°C				

	Characteristic	Sym	Minimum	Typical	Maximum	Units			
Centre Frequency (+25°C)	Absolute Frequency	f <sub>C</sub>	303.750		303.900	MHz			
	Tolerance from 303.825 MHz	$\Delta f_{C}$		±75		kHz			
Insertion Loss		IL		1.4	2.0	dB			
Quality Factor	Unloaded Q	QU		13,100					
	50 Ω Loaded Q	QL		1,950					
Temperature Stability	Turnover Temperature	T <sub>0</sub>	25		55	°C			
	Turnover Frequency	f <sub>0</sub>		f <sub>C</sub>		kHz			
	Frequency Temperature Coefficient	FTC		0.03		ppm/∘c ²			
Frequency Aging Absolute Value during the First Year		fA		≤10		ppm/yr			
DC Insulation Resistance Between Any Two Terminals			1.0			MΩ			
RF Equivalent RLC Model	Motional Resistance	R <sub>M</sub>		17.5	26	Ω			
	Motional Inductance	L <sub>M</sub>		120.0852		μH			
	Motional Capacitance	См		2.2874		fF			
	Shunt Static Capacitance	C 0	2.40	2.65	2.90	pF			

### 7-2.Electronic Characteristics

# **i** CAUTION: Electrostatic Sensitive Device. Observe precautions for handling!

In keeping with our ongoing policy of product evolvement and improvement, the above specification is subject to change without notice.

ISO9001: 2000 Registered - Registration number 6830/2

For quotations or further information please contact us at:

3 The Business Centre, Molly Millars Lane, Wokingham, Berks, RG41 2EY, UK

http://www.actcrystals.com



- 1. The centre frequency,  $f_c$ , is measured at the minimum IL point with the resonator in the 50  $\Omega$  test system.
- 2. Unless noted otherwise, case temperature  $T_c = +25^{\circ}C \pm 2^{\circ}C$ .
- Frequency aging is the change in f<sub>C</sub> with time and is specified at +65°C or less. Aging may exceed the specification for prolonged temperatures above +65°C. Typically, aging is greatest the first year after manufacture, decreasing in subsequent years.
- 4. Turnover temperature,  $T_0$ , is the temperature of maximum (or turnover) frequency,  $f_0$ . The nominal frequency at any case temperature,  $T_c$ , may be calculated from:  $f = f_0 [1 FTC (T_0 T_c)^2]$ .
- 5. This equivalent RLC model approximates resonator performance near the resonant frequency and is provided for reference only. The capacitance C<sub>0</sub> is the measured static (non-motional) capacitance between the two terminals. The measurement includes case parasitic capacitance.
- 6. Derived mathematically from one or more of the following directly measured parameters: f<sub>C</sub>, IL, 3 dB bandwidth, f<sub>C</sub> versus T<sub>C</sub>, and C<sub>0</sub>.
- 7. The specifications of this device are based on the test circuit shown above and subject to change or obsolescence without notice.
- 8. Typically, equipment utilizing this device requires emissions testing and government approval, which is the responsibility of the equipment manufacturer.
- 9. Our liability is only assumed for the Surface Acoustic Wave (SAW) component(s) per se, not for applications, processes and circuits implemented within components or assemblies.

In keeping with our ongoing policy of product evolvement and improvement, the above specification is subject to change without notice.

### ISO9001: 2000 Registered - Registration number 6830/2

For quotations or further information please contact us at:

3 The Business Centre, Molly Millars Lane, Wokingham, Berks, RG41 2EY, UK

http://www.actcrystals.com