

# Isolated Single Channel RS-232 Line Driver/Receiver

### **Preliminary Technical Data**

### FEATURES

460 kbps Data Rate 1 Tx and 1 Rx Meets EIA-232E specifications 0.1uF charge pump capacitors Integrated isolated dc-to-dc converter ESD protection to IEC1000-4-2(801.2) on R<sub>IN</sub> and T<sub>OUT</sub> pins. ±8kV: contact discharge ±15kV: air gap discharge Integrated isolated dc-to-dc converter High common-mode transient immunity: >25kV/us Safety and regulatory approvals (pending) UL recognition VDE certificate of conformity 20 Lead WSOIC package

#### APPLICATIONS

High noise data communications Industrial Communications Industrial/Telecom Diagnostic Ports

#### **GENERAL DESCRIPTION**

The ADM3251E is a high speed, single-channel RS-232 transceiver device that operates from a single power supply.

This device is ideally suited to operation in electrically harsh environments or where RS-232 cables are frequently being plugged/unplugged.

The ADM3251E incorporates dual-channel digital isolators with *iso*Power integrated, isolated power. There is no requirement for a separate isolated dc-to-dc converter as the ADM3251E has a chip-scale dc-to-dc converter which is based on Analog Devices, Inc. *i*Coupler\* technology.

Analog Devices' chip-scale transformer *i*Coupler technology is used both for the isolation of the logic signals as well as for the dc-to-dc converter. The result is a small form factor, total isolation solution. ADM3251E

#### FUNCTIONAL BLOCK DIAGRAM




Figure 1.

Five external  $0.1\mu$ F charge pump capacitors are used for the voltage doubler/inverter permitting operation from a single supply.

The ADM3251E conforms to the EIA-232E specifications and operates at data rates up to 460 kbps.

The device is ideally suited to operation in electrically harsh environments. RS-232 pins,  $R_{IN}$  and  $T_{OUT}$  are protected against electrostatic discharges (up to ±15 kV ESD protection).

The ADM3251E is available in a 20 lead Wide Body SOIC package.

Rev. PrA

Information furnished by Analog Devices is believed to be accurate and reliable. However, no responsibility is assumed by Analog Devices for its use, nor for any infringements of patents or other rights of third parties that may result from its use. Specifications subject to change without notice. No license is granted by implication or otherwise under any patent or patent rights of Analog Devices. Trademarks and registered trademarks are the property of their respective owners.

\_ ..

### **TARGET SPECIFICATIONS**

All voltages are relative to their respective ground. All min/max specifications apply over the entire recommended operating range, unless otherwise noted. All typical specifications in Table 1 are at  $T_A = 25^{\circ}$ C,  $V_{CC} = 5.0$ V, unless otherwise noted.

Table 1.					
Parameter	Min	Тур	Max	Unit	Test Conditions/Comments
DC CHARACTERISTICS					
VccOperating Voltage Range	4.5		5.5	V	
DC-to-DC Converter Enable Threshold, V <sub>CC(Enable)</sub> <sup>1</sup>	4.5			V	
DC-to-DC Converter Disable Threshold, V <sub>CC(Disable)</sub> <sup>1</sup>			3.7	V	
DC-to-DC CONVERTER ENABLED					
Input Supply Current			TBD	mA	No Load
			TBD	mA	$R_L = 3k\Omega$
V <sub>ISO</sub> Output <sup>2</sup>		5.0		V	I <sub>ISO</sub> =0uA
DC-to-DC CONVERTER DISABLED					
Primary Side Supply Input Current, I <sub>CC(Disable)</sub>			TBD	mA	$V_{ISO} = 3.3V$ , $Vcc \le 3.7V$
OGIC					
Transmitter Input, T <sub>IN</sub>					
Logic Input Current, ITIN	-10	+0.01	+10	μA	
Logic Low Input Threshold, V <sub>TINL</sub>	0.3 V <sub>CC</sub>			v	
Logic High Input Threshold, V <sub>TINH</sub>			0.7 Vcc	v	
Receiver Output, Rout					
Logic High Output VROUTH	Vcc - 0.1	Vcc		v	I <sub>ROUTH</sub> = - 20 μA
	Vcc - 0.5	V <sub>cc</sub> – 0.2		v	$I_{\text{ROUTH}} = -4 \text{ mA}$
Logic Low Output VROUTL		0.0	0.1	v	$I_{\text{ROUTH}} = 20 \ \mu\text{A}$
		0.0	0.4	v	$I_{\text{ROUTH}} = 4 \text{ mA}$
S-232					
RECEIVER					
EIA-232 Input Voltage Range <sup>3</sup>	-30		+30	v	
EIA-232 Input Threshold Low	0.6	1.3	150	v	
EIA-232 Input Threshold High	0.0	1.6	2.4	V	
EIA-232 Input Hysteresis		0.4	2.1	v	
EIA-232 Input Resistance	3	5	7	kΩ	
TRANSMITTER	5	5	7	K32	
Output Voltage Swing (RS-232)	±5	±5.7		v	$R_{I} = 3k\Omega$ to Gnd
Transmitter Output Resistance	300	± <i>3</i> .7		Ω	$V_{ISO} = 0V$
RS-232 Output Short Circuit Current	300	TBD		mA	VISO - UV
IMING CHARACTERISTICS		שטו			
	160			likeren	
Maximum Data Rate	460			kbps	$R_L = 3k\Omega \text{ to}7k\Omega$ , $C_L=50 \text{ pF to 1000 pF}$
Receiver Propagation Delay		100			
t <sub>PHL</sub>				μs	
				μs	
Transmitter Propagation Delay	- /		μs	$R_L = 3k\Omega$ , $C_L = 1000 \text{ pF}$	
Transmitter Skew		80		ns	
Receiver Skew		70		ns	
Transition Region Slew Rate <sup>3</sup>	5.5	10	30	V/µs	+3V to -3V or -3V to 3V, $V_{cc}$ =+3.3V, $R_L$ =+3kΩ, $C_L$ =1000pF, $T_A$ =25C.
C SPECIFICATIONS					
Output Rise, t <sub>R</sub> /Fall time, t <sub>F</sub> (10% to 90%)		2.3		ns	$C_L = 15 \text{ pF}$ , CMOS signal levels
Common-Mode Transient Immunity at Logic High Output		TBD		KV/ μs	
Common-Mode Transient Immunity at Logic Low Output		TBD		KV/ μs	
SD PROTECTION (R <sub>IN</sub> and T <sub>OUT</sub> Pins)		±15		kV	Human Body Model Air Discharge
		±8		kV	Human Body Model Contact Discharge

1 Enable/disable threshold is the VCC voltage at which the internal DC-to-DC converter is enabled/disabled.

2 To maintain datasheet specifications no current should be drawn from  $V_{\mbox{\scriptsize Iso.}}$  3 Guaranteed by design

### TARGET SPECIFICATIONS

All voltages are relative to their respective ground. All min/max specifications apply over the entire recommended operating range, unless otherwise noted. All typical specifications in Table 2 are at  $T_A = 25$  °C,  $V_{CC} = 3.3$ V (DC-to-DC converter disabled), the secondary side is powered externally by  $V_{ISO}=3.3$ V, unless otherwise noted.

Parameter	Min	Тур	Max	Unit	<b>Test Conditions/Comments</b>
DC CHARACTERISTICS					
Vcc Operating Voltage Range	3.0		3.7	v	
DC-to-DC Converter Disable Threshold, V <sub>CC(Disable)</sub> <sup>1</sup>			3.7	V	
DC-to-DC CONVERTER DISABLED					
V <sub>ISO</sub>	3.0		5.5	V	
Primary Side Supply Input Current, Icc(Disable)			TBD	mA	No Load
Secondary Side Supply Input Current, I <sub>ISO(Disable)</sub>			TBD	mA	$R_L=3k\Omega$
LOGIC					
Transmitter Input, T <sub>IN</sub>					
Logic Input Current, ITIN	-10	+0.01	+10	μA	
Logic Low Input Threshold, VTINL	0.3 Vcc			V	
Logic High Input Threshold, VTINH			0.7 Vcc	V	
Receiver Output, Rout					
Logic High Output VROUTH	Vcc - 0.1	Vcc		v	I <sub>ROUTH</sub> = - 20 μA
	V <sub>CC</sub> - 0.5	V <sub>cc</sub> - 0.2		v	$I_{ROUTH} = -4 \text{ mA}$
Logic Low Output VROUTL		0.0	0.1	v	$I_{ROUTH} = 20 \mu A$
		0.0	0.4	v	$I_{\text{ROUTH}} = 4 \text{ mA}$
RS-232					
RECEIVER					
EIA-232 Input Voltage Range <sup>2</sup>	-30		+30	v	
EIA-232 Input Threshold Low	0.6	1.3		v	
EIA-232 Input Threshold High	0.0	1.6	2.4	v	
EIA-232 Input Hysteresis		0.4		V	
EIA-232 Input Resistance	3	5	7	kΩ	
TRANSMITTER	-	-	-		
Output Voltage Swing (RS-232)	±5	±5.7		v	$V_{ISO} = 3.3V$ , $R_L = 3k\Omega$ to Gnd
Transmitter Output Resistance	300			Ω	$V_{\rm ISO} = 0V$
RS-232 Output Short Circuit Current	500	TBD		mA	
TIMING CHARACTERISTICS		100			
Maximum Data Rate	460			kbps	$V_{ISO} = 3.3V$ , $R_L = 3k\Omega$ to $7k\Omega$ , $C_L = 50$ pF to
	100			Kops	1000pF
Receiver Propagation Delay					
t <sub>PHL</sub>		190		μs	
t <sub>PLH</sub>	135			μs	
Transmitter Propagation Delay	nsmitter Propagation Delay 650			μs	$R_L = 3k\Omega$ , $C_L = 1000 \text{ pF}$
Transmitter Skew		80		ns	
Receiver Skew		55		ns	
Transition Region Slew Rate <sup>2</sup>	5.5	10	30	V/µs	+3V to -3V, or -3V to +3V, $V_{cc}$ = 3.3V, $R_L$ =3k $\Omega$ , $C_L$ =1000pF, $T_A$ =25C.
AC SPECIFICATIONS					
Output Rise, t <sub>R</sub> /Fall time, t <sub>F</sub> (10% to 90%)		2.3		ns	$C_L = 15 \text{ pF}$ , CMOS signal levels
Common-Mode Transient Immunity at Logic High Output		TBD		KV/ μs	_
Common-Mode Transient Immunity at Logic Low Output	TBD			KV/μs	
ESD PROTECTION (R <sub>IN</sub> and T <sub>OUT</sub> Pins)		±15		kV	Human Body Model Air Discharge
· ··· ·/		±8		kV	Human Body Model Contact Discharge

1 Enable/disable threshold is the VCC voltage at which the internal DC-to-DC converter is enabled/disabled. 2 Guaranteed by design

:

### **ABSOLUTE MAXIMUM RATINGS**

#### Table 6.

Parameter	Rating		
Vcc	–0.3 V to +6 V		
V+	$(V_{CC} - 0.3 V)$ to +13 V		
V–	+0.3 V to -13 V		
Input Voltages			
T <sub>IN</sub>	–0.3 V to (V+, +0.3 V)		
R <sub>IN</sub>	±30 V		
Output Voltages			
Тоит	±15 V		
R <sub>OUT</sub>	-0.3 V to (V <sub>CC</sub> + 0.3 V)		
Short Circuit Duration			
Tout	Continuous		
Power Dissipation			
Power dissipation CP-12	TBD		
$ heta_{JA}$ , Thermal Impedance	TBD		
Operating Temperature Range			
Industrial	–40°C to +85°C		
Storage Temperature Range	–65°C to +150°C		
Pb-Free Temperature (Soldering, 30 sec)	260°C		

Stresses above those listed under Absolute Maximum Ratings may cause permanent damage to the device. This is a stress rating only and functional operation of the device at these or any other conditions above those indicated in the operational section of this specification is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

#### **ESD CAUTION**



**ESD** (electrostatic discharge) sensitive device. Charged devices and circuit boards can discharge without detection. Although this product features patented or proprietary protection circuitry, damage may occur on devices subjected to high energy ESD. Therefore, proper ESD precautions should be taken to avoid performance degradation or loss of functionality.

## **PIN CONFIGURATION AND FUNCTION DESCRIPTIONS**




Figure 2. ADM3251E Pin Configuration

Table 7.	Table 7. Pin Function Descriptions				
Pin No.	Mneumonic	Description			
1	NC	Not Connected			
2	V <sub>cc</sub>	Power Supply Input			
3	Vcc	Power Supply Input			
4	GND	Ground Pin			
5	GND	Ground Pin			
6	GND	Ground Pin			
7	GND	Ground Pin			
8	Rout	Receiver Output. This outputs CMOS output logic levels.			
9	T <sub>IN</sub>	Transmitter (Driver) Input. This input accepts TTL/CMOS levels.			
10	GND	Ground Pin			
11	GND <sub>ISO</sub>	Ground reference for Isolator Primary Side.			
12	V-	Internally Generated Negative Supply			
13	C2-	External Capacitor 2 is connected between pins 13 and 14. A 0.1µF capacitor is recommended but larger capacitors up to 47uF may be used.			
14	C2+	External Capacitor 2 is connected between pins 13 and 14. A 0.1µF capacitor is recommended but larger capacitors up to 47uF may be used.			
15	R <sub>IN</sub>	Receiver Input. This input accepts RS-232 signal levels.			
16	Tout	Transmitter (Driver) Output. This outputs RS-232 signal levels.			
17	C1-	External Capacitor 1 is connected between pins 17 and 18. A 0.1µF capacitor is recommended but larger capacitors up to 47uF may be used.			
18	C1+	External Capacitor 1 is connected between pins 17 and 18. A 0.1µF capacitor is recommended but larger capacitors up to 47uF may be used.			
19	V+	Internally Generated Positive Supply			
20	V <sub>ISO</sub>	Isolated Supply Voltage for Isolator Secondary Side.			

### **OUTLINE DIMENSIONS**




Figure 5. 20-Lead Standard Small Outline Package. Dimensions shown in millimeters and (inches).