



telephone 949 252 0522





Product Category: Ceramic Resonator

Series Number	Package	Description	Last Modified
670 ~ 671	ZTACC / ZTTCC Ceramic	SMD Resonator	Jan. 01 2007

FEATURES

- Low frequencies Surface Mount Ceramic Resonator
- Extended temperature range
- High stability
- RoHS Compliant







OPERATING CONDITIONS / ELECTRICAL CHARACTERISTICS

Series No.	Туре	Fig	Frequency Range*	Frequency Accuracy	Stability in Temperature	Aging for Ten Years
			(MHz)	@ 25° (MHz)	-20° ~ +80°C	-
670	ZTACC	1	1.79 ~ 8.00	1.79 ~ 8.00 ±0.5%	±0.3%	±0.3 %
671	ZTTCC	2		±0.5 %	±0.5 %	10.5 %

^{*}Higher Freq. Avail. Contact Oscilent for assistance.


PACKAGE DIMENSIONS (mm)





Recommended Land Pattern

Recommended Land Pattern






Figure 1) ZTACC

Figure 2) ZTTCC

Test Circuit IC

Freq. 1.79 ~ 8.0 MHz:

IC: 1/6TC4069UBPx2

VALUES OF C1 & C2

Frequency Range (MHz)	C1 (pF)	C2 (pF)
1.79 ~ 8.00	30	30

PART NUMBER GUIDE

Par	t Number	Frequency	Load Capacitance	Frequency Accuracy (%)	Operating Temp (°C)	Packaging**
	670	- 3.5M	- 32	- 03	W	
670 = 671 =	ZTACC ZTTCC	e.g3.5M = 3.50 MHz Std. Range = 1.79 ~ 8.00 MHz Higher Freq. Avail. Contact Oscilent for assistance.	Blank* = Standard as shown in above Table or Fill in the blank e.g 32 = 32pF	Blank* = ±0.5% -03 = ±0.3%	Blank* = -20 ~ +80 -N = -40 ~ +85 -W = -40 ~ +125	Blank* = Bulk -TR = Tape/ Reel

NOTE: Deviations on all parameters available. Please consult Oscilent for details.

DEFINITIONS: Click on the characteristic names above, for definitions of the particular characteristic.

*STANDARDS: "Blank" part number selections, indicate standard variables for the particular characteristic.

**PACKAGING: Click on the packaging name above for Tape/Reel specifications

Oscilent Corporation - CALL 949.252.0522

18195 East McDurmott Street . Building D . Irvine . CA 92614 . USA

Fax: 949.252.0599 . E-Mail: Sales@Oscilent.com

Series No.: 670 to 671

Crystal Oscillators | Quartz Crystal | TCXO | VCXO | IF SAW Filter | RF SAW Filter | Ceramic Resonator Crystal Filter | Ceramic Filter | SAW Filter / SAW Devices | Site Map