Combine Type Connector (for SIM Card 8pins, microSD™ Card)

SCHG Series



Double-deck for SIM Card (8pins) combine type.

For SD Memory Card

For microSD™

For SIM Card 8pins

For W-SIM

For Memory Stick Micro™

For Memory Stick™

Combine Type

For Compact Flash™

For PC cards supporting CardBus

For Express Card™

For CMOS Camera Module



Features

 Two-slot, double-deck structure enables two typs cards, the SIM Card (8pins) and microSDTM Card, to be separately inserted.

Applications


 For mobile phones, various personal digital assistants, notebook PCs.

■Typical Specifications

Items			Specifications	
Structure	Applicable media		SIM Card 8pins	
			microSD™ Card	
	Mounting type		Surface mounting type	
	Mounting style		Standard mount	
	Media ejection structure		Manual insertion/removal/Push-push type	
Performance	Operating temperature range		−25°C to +70°C	
	Voltage proof		500V AC 1minute	
	Insulation resistance (Initial)		1,000MΩ min.	
	Contact resistance (Initial)	Connector contacts	100mΩ max.	
		Detection switch	500mΩ max.	
	Insertion and removal cycle		5,000cycles (SIM Card 8pins) 10,000cycles (microSD™ Card)	

Product Line

Media ejection structure	Mounting system	Stand-off (mm)	Packing system	Product No.
Push-push type	Standard mount	0	Taping	SCHG1B0100



For SD Memory Card

For microSD™ Card

For SIM Card 8pins

For W-SIM

For Memory Stick Micro™

For Memory Stick™

Combine Type

For Compact Flash™

For PC cards supporting CardBus


For Express Card™

For CMOS Camera Module

Soldering Conditions

Example of Reflow Soldering Condition (Reference)

- 1. Heating method: Double heating method with infrared heater.
- 2. Temperature measurement: Thermocouple 0.1 to 0.2 ϕ CA (K) or CC (T).
- 3. Temperature profile (Surface of products).



Combine Type

SD Memory Card

microSD™ Card

SIM Card 8pins

For

For W-SIM

Memory Stick Micro™

Memory

Stick™

For Compact Flash™

For PC cards supporting CardBus

For Express Card™

For CMOS Camera Module

Cautions for using this product

- 1. When soldering terminals, there is a danger that load placed on the terminals may cause rattle, deformation or electrical degradation to occur depending on the conditions. Caution is therefore required.
- 2. Avoid use of water-soluble soldering flux, since it may corrode the product.
- 3. Check and conform to reflow soldering requirements under actual mass production conditions.
- 4. PC board warping may alter the characteristics. Please take this into consideration when designing patterns and layout.
- 5. The card specifications are provided by the above manufactures. Products by other manufactures may not be compliant with these specifications and are subject to change without prior notice.