

- Ideal for 433.92 MHz Transmitters
- Very Low Insertion Loss
- Quartz Stability
- Ultra Miniature Ceramic SMD Package (DCC6)

SR5514

Absolute Maximum Rating (Ta=25°C)						
Parameter		Rating	Unit			
CW RF Power Dissipation	Р	0	dBm			
DC Voltage	$V_{ m DC}$	±30	V			
Operating Temperature Range	T_{A}	-10 ~ +60	°C			
Storage Temperature Range	$T_{ m stg}$	-40 ~ +85	°C			

Electronic Characteristics								
	Parameter	Sym	Minimum	Typical	Maximum	Unit		
Frequency (25°C)	Nominal Frequency	f _c	NS	433.92	NS	MHz		
	Tolerance from 433.92 MHz	Δf_c	-	-	± 75	KHz		
Insertion Loss		IL	=	1.5	2.2	dB		
Quality Factor	Unloaded Q-Value	Q_u	-	8,800	-	-		
	50Ω Loaded Q-Value	$Q_{\scriptscriptstyle L}$	-	1,400	-	-		
Temperature Stability	Turnover Temperature	To	25	-	45	°C		
	Turnover Frequency	f _o	=	f_c	-	KHz		
	Frequency Temperature Coefficient	FTC	-	0.032	-	ppm/°C ²		
Frequency Aging	Absolute Value during the First Year	$ f_A $	-	-	10	ppm/yr		
DC Insulation Resistance Between any Two Pins		-	1.0	-	-	MΩ		
RF Equivalent RLC Model	Motional Resistance	R _M	-	19	29	Ω		
	Motional Inductance	$L_{\scriptscriptstyle M}$	-	61.1372	-	μΗ		
	Motional Capacitance	C _M	-	2.2027	-	fF		
	Shunt Static Capacitance	Co	1.9	2.2	2.5	pF		

NS = Not Specified

Note:

- The frequency f_c is the frequency of minimum IL with the resonator in the specified test fixture in a 50Ω test system with VSWR ≤ 1.2:1.
- 2. Unless noted otherwise, case temperature TC = +25°C±2°C.
- 3. Frequency aging is the change in fC with time and is specified at +65°C or less. Aging may exceed the specification for prolonged temperatures above +65°C. Typically, aging is greatest the first year after manufacture, decreasing in subsequent years.
- Turnover temperature, T0, is the temperature of maximum (or turnover) frequency, f0. The nominal frequency at any case temperature, TC, may be calculated from: f = f₀ [1 - FTC (T₀ - T_C)²].
- 5. This equivalent RLC model approximates resonator performance near the resonant frequency and is provided for reference only. The capacitance C₀ is the measured static (nonmotional) capacitance between input terminal and ground or output terminal and ground.

- The measurement includes case parasitic capacitance.
- Derived mathematically from one or more of the following directly measured parameters: f_c, IL, 3 dB bandwidth, f_C versus T_C, and Co.
- 7. The specifications of this device are based on the test circuit shown above and subject to change or obsolescence without notice.
- Typically, equipment utilizing this device requires emissions testing and government approval, which is the responsibility of the equipment manufacturer.
- Our liability is only assumed for the Surface Acoustic Wave (SAW) component(s) per se, not for applications, processes and circuits implemented within components or assemblies.
- For questions on technology, prices and delivery, please contact our sales offices or e-mail to sales@vanlong.com.

Phone: +86 10 6301 4184 Fax: +86 10 6301 9167 Email: sales@vanlong.com Web: http://www.vanlong.com



Nom (mm)

3.80

3.80

1.20

Connection

Input / Output

Output / Input

Ground


Dimensions


Е

F

G

Package Dimensions (DCC6)







Marking

R5514 YWW

- 1. R5514 Part Code
- 2. Date Code:

Y: Last digit of year

WW : Week No.

RM CM LM Co

Electrical Connections

Terminals

5

1,3,4,6

В

C

D

Package Dimensions

Dimensions Nom

Nom (mm)


1.90

0.64

1.00

1.27

Equivalent LC Model and Test Circuit




Equivalent LC Model


Test Circuit

Typical Application Circuit


Low Power Transmitter Application




Typical Frequency Response



Local Oscillator Application



Temperature Characteristics



 $\Delta T = Tc - To (°C)$

The curve shown above accounts for resonator contribution only and does not include oscillator temperature characteristics.

Phone: +86 10 6301 4184

Fax: +86 10 6301 9167

Email: sales@vanlong.com

Web: http://www.vanlong.com