# DMS-20PC-3-LM

## Self-Powered LED Display 480V AC Line Monitor



DATEL's DMS-20PC-3-LM is a low-cost, self-powered, 2-wire digital voltmeter designed for monitoring 480Vac 3-phase primary power. The DMS-20PC-3-LM's unique

### **FEATURES**

Self-powered, two-terminal operation

muRata /

**Murata Power Solutions** 

- 350 to 600Vac operating input range
- Half-wave averaging, rms calibrated
- Large, easy-to-read, bright red LED display
- Rugged, epoxy-encapsulated construction
- Built-in bezel for panel mounting
- Reliable screw terminals for easy installation
- Small 1.38" x 0.88" x 1.0" package

### **Functional Specifications**

#### Input

Voltage Range ① **Current Consumption** 

## Performance

Sampling Rate Measurement Type

Accuracy @ +25°C **Temperature Drift** (-25 to +60°C)

Mechanical

Dimensions **Display Type** Weight Case Material

#### **Environmental**

**Operating Temperature** -25 to +60°C Storage Temperature -40 to +75°C Humidity (Non-condensing) 0 to 95%

① Operation and accuracy at inputs above or below this range are not specified.





www.murata-ps.com

Its large, 0.37<sup>"</sup>/9.4mm, bright red LED display is easily readable under virtually all lighting conditions. DMS-20PC-3-LM employs rms calibrated, halfwave sinusoidal averaging to achieve a display reso-

power-supply design allows a single model to operate

from 350 to 600Vac (47-63Hz). The meter requires no

lution of 1Vac over its full operating range. Packaged in a subminiature (1.38" x 0.88" x 1.0") red-filter case with a built-in bezel, the meter is epoxy encapsulated for ruggedness. An optional bezel assembly, featuring metal fasteners, simplifies panel mounting.

This easy-to-use, vibration-proof voltmeter is the ideal digital upgrade for fragile analog-style panel meters in 480Vac power distribution equipment. It similarly excels in any new application requiring accurate, high-voltage, ac line monitoring,



## **Ordering Information**

DMS-20PC-3-LM-C 350-600Vac line monitor with screw terminals and screws DMS-BZL3-C Panel mount bezel DMS-BZL4-C Panel mount bezel with sealing gasket DMS-20-CP Panel cutout punch

Brass screws (6-32 thread) and a panel-mount retaining clip are supplied with each meter

calibrated for sinusoidal input  $\pm 1V$  (typ.),  $\pm 2V$  (max.) ±0.15 Volts/°C (max.)

Half-wave average, rms

2.5 readings/second

1.38" x 0.88" x 1.00" 3 digit, red LED, 0.37"/9.4mm 1 ounce (28 grams) Polycarbonate

350-600Vrms (47-63Hz) 50mArms (max.)

## muRata Ps Murata Power Solutions

# DMS-20PC-3-LM

Self-Powered LED Display 480V AC Line Monitor



## muRata Ps Murata Power Solutions

Murata Power Solutions, Inc.

11 Cabot Boulevard, Mansfield, MA 02048-1151 U.S.A.

Tel: (508) 339-3000 (800) 233-2765 Fax: (508) 339-6356

www.murata-ps.com email: sales@murata-ps.com ISO 9001 and 14001 REGISTERED 11/24/08

Murata Power Solutions, Inc. makes no representation that the use of its products in the circuits described herein, or the use of other technical information contained herein, will not infringe upon existing or future patent rights. The descriptions contained herein do not imply the granting of licenses to make, use, or sell equipment constructed in accordance therewith. Specifications are subject to change without notice.

USA:	Mansfield (MA), Tel: (508) 339-3000, email: sales@murata-ps.com
Canada:	Toronto, Tel: (866) 740-1232, email: toronto@murata-ps.com
UK:	Milton Keynes, Tel: +44 (0)1908 615232, email: mk@murata-ps.com
France:	Montigny Le Bretonneux, Tel: +33 (0)1 34 60 01 01, email: france@murata-ps.com
Germany:	München, Tel: +49 (0)89-544334-0, email: munich@murata-ps.com
Japan:	Tokyo, Tel: 3-3779-1031, email: sales_tokyo@murata-ps.com Osaka, Tel: 6-6354-2025, email: sales_osaka@murata-ps.com
China:	Shanghai, Tel: +86 215 027 3678, email: shanghai@murata-ps.com Guangzhou, Tel: +86 208 221 8066, email: guangzhou@murata-ps.com
Singapore:	Parkway Centre, Tel: +65 6348 9096, email: singapore@murata-ps.com



www.murata-ps.com

Technical enquiries email: sales@murata-ps.com, tel: +1 508 339 3000