

AK594096AS / AK594096AG 4,194,304 Word x 9 Bit CMOS Dynamic Random Access Memory

DESCRIPTION

The Accutek AK594096A high density memory module is a CMOS random access memory organized in 4 Meg x 9 bit words. The assembly consists of nine standard 4 Meg x 1 DRAMs in plastic leaded chip carriers (SOJ) mounted on the front side of a printed circuit board. The module can be configured as a leadless 30 pad SIM or a leaded 30 pin SIP. The module is only 0.800 inches high (same height as a standard 1 Meg module), making it ideally suited for applications with low height restrictions.

The operation of the AK594096A is identical to nine 4 Meg x 1 DRAMs. For the lower eight bits data input is tied to the data output and brought out separately for each device, with common \overline{RAS} , \overline{CAS} control. This common I/O feature dictates the use of early-write cycles to prevent contention of D and Q. Since the Write-Enable (\overline{WE}) signal must always go low before \overline{CAS} in a write cycle, Read-Write and Read-Modify-Write operation is not possible. For the ninth bit, the data input (D₉) and the data output (Q₉) pins are brought out separately and controlled by a separate \overline{PCAS} for that bit. Bit nine is generally used for parity.

FEATURES

- 4,194,304 x 9 bit organization
- Optional 30 Pad leadless SIM (Single In-Line Module) or 30 Pin leaded SIP (Single In-Line Package)

PIN ASSIGNMENT

SYMBOL

Vcc

CAS

DQ1

Α0

Α1

DO2

A2

АЗ

Vss

DQ3

A4

Α5

DQ4

A6

Α7

2

3

4

5

6

7

8

9

10

11

12

13

14

PIN#

16

17

18

19

20

21

22

23

24

25

26

27

28

29

30

SYMBO

DQ5

Α8

Α9

A10

DQ6

WE

Vss

DQ7


NC

DQ8

Ω9

RAS PCAS

- · JEDEC standard pinout
- Common CAS and RAS control for the lower eight bits
- Separate PCAS for control for D₉ and Q₉
- CAS-before-RAS refresh



- Power
 4.45 Watt Max Active (80 nSEC)
 3.96 Watt Max Active (100 nSEC)
 49.5 mW Max Standby
- Operating free air temperature 0°C to 70°C
- Upward compatible with AK5916384
- Downward compatible with AK591024, AK59256


PIN NOMENCLATURE

DQ ₁ - DQ ₈	Data In / Data Out
D ₉	Data In 9
Q9	Data Out 9
A ₀ - A ₁₀	Address Inputs
CAS, PCAS	Column Address Strobe
RAS	Row Address Strobe
WE	Write Enable
Vcc	5v Supply
Vss	Ground
NC	No Connect

M	O	D	U	Ц	Ε	O	Ρ	Т	IC) [V	S
---	---	---	---	---	---	---	---	---	----	-----	---	---

Leadless SIM: AK594096AS
Leaded SIP: AK594096AG

FUNCTIONAL DIAGRAM



ORDERING INFORMATION

PART NUMBER CODING INTERPRETATION

Position 1 2 3 4 5 6 7 8

1 Product

AK = Accutek Memory

- 2 Type
 - 4 = Dynamic RAM
 - 5 = CMOS Dynamic RAM
 - 6 = Static RAM

3 Organization/Word Width

- $1 = by 1 \quad 16 = by 16$
- 4 = by 4 32 = by 32
- $8 = by 8 \quad 36 = by 36$
- 9 = by 9

4 Size/Bits Depth

5 Package Type

- G = Single In-Line Package (SIP)
- S = Single In-Line Module (SIM)
- D = Dual In-Line Package (DIP)
- W = .050 inch Pitch Edge Connect
- Z = Zig-Zag In-Line Package (ZIP)

6 Special Designation

- P = Page Mode
- N = Nibble Mode
- K = Static Column Mode
- W = Write Per Bit Mode
- V = Video Ram

7 Separator

- = Commercial 0° C to + 70° C
- M = Military Equivalent Screened
 - (-55⁰C to +125⁰C)
- I = Industrial Temperature Tested
 - $(-45^{\circ}C \text{ to } +85^{\circ}C)$
- X = Burned In

8 Speed (first two significant digits)

DR	AM:	S	SR	SRAMS			
50	=	50 nS	8	=	8 nS		
60	=	60 nS	10	=	10 nS		
70	=	70 nS	12	=	12 nS		
80	=	80 nS	15	=	15 nS		

The numbers and coding on this page do not include all variations available but are show as examples of the most widely used variations. Contact Accutek if other information is required.

EXAMPLES:

AK594096ASP-80

4 Meg x 9, 80 nSEC DRAM 30 pin SIM Configuration, Page Mode

AK594096AGP-70

4 Meg x 9, 70 nSEC Dram 30 pin SIP Configuration, Page Mode



ACCUTEK MICROCIRCUIT CORPORATION


BUSINESS CENTER at NEWBURYPORT 2 NEW PASTURE ROAD, SUITE 1 NEWBURYPORT, MA 01950-4054

VOICE: 978-465-6200 FAX: 978-462-3396

Email: sales@accutekmicro.com
Internet: www.accutekmicro.com

MECHANICAL DIMENSIONS

Inches



Accutek reserves the right to make changes in specifications at any time and without notice. Accutek does not assume any responsibility for the use of any circuitry described; no circuit patent licenses are implied. Preliminary data sheets contain minimum and maximum limits based upon design objectives, which are subject to change upon full characterization over the specific operating conditions.