## ETM4-1T-2



4:1 RF Transformer 0.05 - 3.072 MHz

M/A-COM Products Part Status: Released Rev V5


#### **Features**

- **Surface Mount**
- 4:1 Impedance
- CT on Secondary
- 50 Ohm

#### **Description**

M/A-COM's ETM4-1T-2 is a 4:1 RF Transformer in a low cost surface mount package. Ideally suited for high volume CATV application.

#### **Schematic**




## **Pin Configuration**

Function	Pin Number		
Secondary Dot	1		
Secondary Centre Tap	2		
Secondary	3		
Primary	4		
Not Connected	5		
Primary Dot	6		

## **Ordering Information**

Part Number	Package
ETM4-1T-2TR	900 pieces per reel

### Case Style SM-1



Dimensions are inches (millimeters) ±0.015 (0.38) unless otherwise specified.

• North America Tel: 800.366.2266 • Europe Tel: +353.21.244.6400 • China Tel: +86.21.2407.1588 • India Tel: +91.80.4155721

Visit www.macomtech.com for additional data sheets and product information.

# ETM4-1T-2



4:1 RF Transformer M/A-COM Products Part Status: Released Rev V5 0.05 - 3.072 MHz

## Electrical Specifications: $T_A = 25$ °C, 0dBm, $Z_0 = 50\Omega$

Parameter	Test Conditions	Units	Min.	Тур.	Max.
Frequency Range	.05 – 3.072 MHz				
Insertion Loss	.05 – 3.072 MHz	dB	-	_	1
Amplitude Balance	.05 – 3.072 MHz	dB	_	_	±0.1
Phase Balance	.05 – 3.072 MHz	0	_	_	±1
Input Return Loss	.05 – .20 MHz .20 - 3.072 MHz	dB dB	18 25	_	_

### **Absolute Maximum Ratings**

Parameter	Absolute Maximum
RF Power	250mW
DC Current	30mA
Operating Temperature	-20°C to +85°C
Storage Temperature	-55°C to +100°C